

# H3C S12500G-AF 系列交换机

## 单板与光模块适配关系表

---

Copyright © 2024 新华三技术有限公司 版权所有，保留一切权利。

非经本公司书面许可，任何单位和个人不得擅自摘抄、复制本文档内容的部分或全部，并不得以任何形式传播。

除新华三技术有限公司的商标外，本手册中出现的其它公司的商标、产品标识及商品名称，由各自权利人拥有。

本文档中的信息可能变动，恕不另行通知。

# 1 单板与光模块适配关系

本系列产品支持多种光模块或线缆，不同接口支持的光模块或线缆类型不同，具体请参见单板与光模块适配关系表。

当设备上安装 S 系列单板时，电缆仅用于本系列交换机之间互连，作为交换机部分软件特性（如：IRF）的专用线缆。

更多光模块或线缆属性信息，请参见 [《H3C 光模块手册》](#)。

## 1.1 使用限制

### 1. 单板接口双工模式限制

如下单板的 10GE 光接口插千兆光模块时，需要配置接口的双工模式为全双工、速率为 1000Mbps：LSXM1TGS48TE2、LSXM1TGS48TD2。

### 2. 单板接口自协商速率限制

如下单板的 10GE 光接口插千兆光模块，当对端连接的为百兆光模块时，不支持自协商降速到 100Mbps：LSXM1TGS48TE2、LSXM1TGS48TD2。

### 3. 单板接口拆分限制

如下单板的 100GE 光接口拆分成 10GE 光接口后不支持降速：LSXM1CGQ18TE2、LSXM1CGQ36TE2、LSXM1CGQ8TD2、LSXM1CGQ18TD2。

如下单板的 100GE 光接口不支持拆分：LSXM1YGS24CGMODTE2。

拆分后的光接口不支持通过 speed 命令修改端口速率。

100GE 的光接口拆分为 10GE，只能使用 QSFP+ to SFP+ 线缆。

## 1.2 单板与光模块适配关系表

表1-1 单板与光模块适配关系表

单板名称	端口	支持的光模块	版本适配及说明
LSWM124TG2H	1~24	CAB-0.5M-SFP+	R7624P07
		CAB-1M-SFP+	R7624P07
		CAB-3M-SFP+	R7624P07
		LSTM1STK	R7624P07
		LSTM2STK	R7624P07
		LSWM1STK	R7624P07
		LSWM2STK	R7624P07
		LSWM3STK	R7624P07
		SFP-25G-D-AOC-10M	R7624P07

单板名称	端口	支持的光模块	版本适配及说明
		SFP-25G-D-AOC-20M	R7624P07
		SFP-25G-D-AOC-3M	R7624P07
		SFP-25G-D-AOC-5M	R7624P07
		SFP-25G-D-AOC-7M	R7624P07
		SFP-25G-D-CAB-1M	R7624P07
		SFP-25G-D-CAB-3M	R7624P07
		SFP-25G-D-CAB-5M	R7624P07
		SFP-25G-LR-SM1310	R7624P07
		SFP-25G-SR-MM850	R7624P07
		SFP-XG-D-AOC-10M	R7624P07
		SFP-XG-D-AOC-20M	R7624P07
		SFP-XG-D-AOC-7M	R7624P07
		SFP-XG-LH40-SM1270-BIDI	R7624P07
		SFP-XG-LH40-SM1330-BIDI	R7624P07
		SFP-XG-LH40-SM1550	R7624P07
		SFP-XG-LH40-SM1550-D	R7624P07
		SFP-XG-LH80-SM1490-BIDI	R7624P07
		SFP-XG-LH80-SM1550	R7624P07
		SFP-XG-LH80-SM1550-BIDI	R7624P07
		SFP-XG-LH80-SM1550-D	R7624P07
		SFP-XG-LX-SM1270-BIDI	R7624P07
		SFP-XG-LX-SM1310	R7624P07
		SFP-XG-LX-SM1310-D	R7624P07
		SFP-XG-LX-SM1310-E	R7624P07
		SFP-XG-LX-SM1310-S	R7624P07
		SFP-XG-LX-SM1330-BIDI	R7624P07
		SFP-XG-SX-MM850-A	R7624P07
		SFP-XG-SX-MM850-D	R7624P07
		SFP-XG-SX-MM850-E	R7624P07
		SFP-XG-SX-MM850-S	R7624P07

单板名称	端口	支持的光模块	版本适配及说明
		LSWM1QSTK0	R7624P07
		LSWM1QSTK1	R7624P07
		LSWM1QSTK2	R7624P07
		QSFP-100G-CWDM4-SM1300-A	R7624P07
		QSFP-100G-D-AOC-10M	R7624P07
		QSFP-100G-D-AOC-20M	R7624P07
		QSFP-100G-D-AOC-7M	R7624P07
		QSFP-100G-D-CAB-1M	R7624P07
		QSFP-100G-D-CAB-3M	R7624P07
		QSFP-100G-D-CAB-5M	R7624P07
		QSFP-100G-ER4L-WDM1300	R7624P07
		QSFP-100G-eSR4-MM850	R7624P07, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-LR4L-WDM1300	R7624P07
	25~26	QSFP-100G-LR4-WDM1300	R7624P07
		QSFP-100G-LR4-WDM1300-A	R7624P07
		QSFP-100G-PSM4-SM1310	R7624P07, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850	R7624P07, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850-A	R7624P07, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SWDM4-MM850	R7624P07
		QSFP-40G-BIDI-SR-MM850	R7624P07
		QSFP-40G-BIDI-WDM850	R7624P07
		QSFP-40G-CSR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-D-AOC-10M	R7624P07

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-D-AOC-20M	R7624P07
		QSFP-40G-D-AOC-7M	R7624P07
		QSFP-40G-ER4-WDM1300	R7624P07
		QSFP-40G-LR4L-WDM1300	R7624P07
		QSFP-40G-LR4-PSM1310	R7624P07
		QSFP-40G-LR4-WDM1300	R7624P07
		QSFP-40G-SR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports
LSWM124XG2Q	1~24	CAB-0.5M-SFP+	R7624P07
		CAB-1M-SFP+	R7624P07
		CAB-3M-SFP+	R7624P07
		LSTM1STK	R7624P07
		LSTM2STK	R7624P07
		LSWM1STK	R7624P07
		LSWM2STK	R7624P07
		LSWM3STK	R7624P07
		SFP-GE-LH100-SM1550	R7624P07
		SFP-GE-LH40-SM1310	R7624P07
		SFP-GE-LH40-SM1310-BIDI	R7624P07
		SFP-GE-LH40-SM1310-D	R7624P07
		SFP-GE-LH40-SM1550	R7624P07
		SFP-GE-LH40-SM1550-BIDI	R7624P07
		SFP-GE-LH70-SM1490-BIDI	R7624P07
		SFP-GE-LH70-SM1550-BIDI	R7624P07
		SFP-GE-LH80-SM1550	R7624P07
		SFP-GE-LH80-SM1550-D	R7624P07
		SFP-GE-LX-SM1310-A	R7624P07
		SFP-GE-LX-SM1310-BIDI	R7624P07
SFP-GE-LX-SM1310-D	R7624P07		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LX-SM1310-S	R7624P07
		SFP-GE-LX-SM1490-BIDI	R7624P07
		SFP-GE-SX-MM850-A	R7624P07
		SFP-GE-SX-MM850-D	R7624P07
		SFP-GE-SX-MM850-S	R7624P07
		SFP-GE-T	R7624P07
		SFP-GE-T-D	R7624P07
		SFP-XG-D-AOC-10M	R7624P07
		SFP-XG-D-AOC-20M	R7624P07
		SFP-XG-D-AOC-7M	R7624P07
		SFP-XG-LH40-SM1270-BIDI	R7624P07
		SFP-XG-LH40-SM1330-BIDI	R7624P07
		SFP-XG-LH40-SM1550	R7624P07
		SFP-XG-LH40-SM1550-D	R7624P07
		SFP-XG-LH80-SM1490-BIDI	R7624P07
		SFP-XG-LH80-SM1550	R7624P07
		SFP-XG-LH80-SM1550-BIDI	R7624P07
		SFP-XG-LH80-SM1550-D	R7624P07
		SFP-XG-LX-SM1270-BIDI	R7624P07
		SFP-XG-LX-SM1310	R7624P07
		SFP-XG-LX-SM1310-D	R7624P07
		SFP-XG-LX-SM1310-E	R7624P07
		SFP-XG-LX-SM1310-S	R7624P07
		SFP-XG-LX-SM1330-BIDI	R7624P07
		SFP-XG-SX-MM850-A	R7624P07
		SFP-XG-SX-MM850-D	R7624P07
		SFP-XG-SX-MM850-E	R7624P07
		SFP-XG-SX-MM850-S	R7624P07
	25~26	LSWM1QSTK0	R7624P07
		LSWM1QSTK1	R7624P07

单板名称	端口	支持的光模块	版本适配及说明
		LSWM1QSTK2	R7624P07
		QSFP-40G-BIDI-SR-MM850	R7624P07
		QSFP-40G-BIDI-WDM850	R7624P07
		QSFP-40G-CSR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-D-AOC-10M	R7624P07
		QSFP-40G-D-AOC-20M	R7624P07
		QSFP-40G-D-AOC-7M	R7624P07
		QSFP-40G-ER4-WDM1300	R7624P07
		QSFP-40G-LR4L-WDM1300	R7624P07
		QSFP-40G-LR4-PSM1310	R7624P07
		QSFP-40G-LR4-WDM1300	R7624P07
		QSFP-40G-SR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports
LSWM124XGT2Q	25~26	LSWM1QSTK0	R7624P07
		LSWM1QSTK1	R7624P07
		LSWM1QSTK2	R7624P07
		QSFP-40G-BIDI-SR-MM850	R7624P07
		QSFP-40G-BIDI-WDM850	R7624P07
		QSFP-40G-CSR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-D-AOC-10M	R7624P07
		QSFP-40G-D-AOC-20M	R7624P07
		QSFP-40G-D-AOC-7M	R7624P07
		QSFP-40G-ER4-WDM1300	R7624P07
		QSFP-40G-LR4L-WDM1300	R7624P07
		QSFP-40G-LR4-PSM1310	R7624P07
QSFP-40G-LR4-WDM1300	R7624P07		
QSFP-40G-SR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports		

单板名称	端口	支持的光模块	版本适配及说明
			SFP+ ports
LSWM18QC	1~8	LSWM1QSTK0	R7624P07
		LSWM1QSTK1	R7624P07
		LSWM1QSTK2	R7624P07
		QSFP-40G-BIDI-SR-MM850	R7624P07
		QSFP-40G-BIDI-WDM850	R7624P07
		QSFP-40G-CSR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-D-AOC-10M	R7624P07
		QSFP-40G-D-AOC-20M	R7624P07
		QSFP-40G-D-AOC-7M	R7624P07
		QSFP-40G-ER4-WDM1300	R7624P07
		QSFP-40G-LR4L-WDM1300	R7624P07
		QSFP-40G-LR4-PSM1310	R7624P07
		QSFP-40G-LR4-WDM1300	R7624P07
		QSFP-40G-SR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports
LSXM1CGQ18TD2	1~2,17~18	LSWM1QSTK0	R7595
		LSWM1QSTK1	R7595
		LSWM1QSTK2	R7595
		QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.
		QSFP-100G-CWDM4-SM1300-A	R7595
		QSFP-100G-D-AOC-10M	R7595
		QSFP-100G-D-AOC-20M	R7595
		QSFP-100G-D-AOC-7M	R7595
		QSFP-100G-D-CAB-1M	R7595
		QSFP-100G-D-CAB-3M	R7595
		QSFP-100G-D-CAB-5M	R7595



单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-ER4L-WDM1300	R7595
		QSFP-100G-eSR4-MM850	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-LR4L-WDM1300	R7595
		QSFP-100G-LR4-WDM1300	R7595
		QSFP-100G-PSM4-SM1310	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850-A	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850-H	E775303
		QSFP-100G-SWDM4-MM850	R7595
		QSFP-40G-BIDI-SR-MM850	R7595
		QSFP-40G-BIDI-WDM850	R7595
		QSFP-40G-CSR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-CSR4-MM850-H	E7637P01
		QSFP-40G-D-AOC-10M	R7595
		QSFP-40G-D-AOC-10M-H	R7639P03
		QSFP-40G-D-AOC-20M	R7595
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7595
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7595
		QSFP-40G-LR4L-WDM1300	R7595
		QSFP-40G-LR4-PSM1310	R7595
		QSFP-40G-LR4-WDM1300	R7595

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-SR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-SR4-MM850-H	E7637P01
	3~16	LSWM1QSTK0	R7595
		LSWM1QSTK1	R7595
		LSWM1QSTK2	R7595
		LSWM1QSTK3	R7595
		LSWM1QSTK4	R7595
		LSWM1QSTK5	R7595
		QSFP-100G-4SFP-25G-CAB-1M	R7595
		QSFP-100G-4SFP-25G-CAB-3M	R7595
		QSFP-100G-4SFP-25G-CAB-5M	R7595
		QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.
		QSFP-100G-CWDM4-SM1300-A	R7595
		QSFP-100G-D-AOC-10M	R7595
		QSFP-100G-D-AOC-20M	R7595
		QSFP-100G-D-AOC-7M	R7595
		QSFP-100G-D-CAB-1M	R7595
		QSFP-100G-D-CAB-3M	R7595
		QSFP-100G-D-CAB-5M	R7595
		QSFP-100G-ER4L-WDM1300	R7595
		QSFP-100G-eSR4-MM850	R7595
		QSFP-100G-LR4L-WDM1300	R7595
		QSFP-100G-LR4-WDM1300	R7595
		QSFP-100G-PSM4-SM1310	R7595
		QSFP-100G-SR4-MM850	R7595

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-SR4-MM850-A	R7595
		QSFP-100G-SR4-MM850-H	E775303
		QSFP-100G-SWDM4-MM850	R7595
		QSFP-40G-BIDI-SR-MM850	R7595
		QSFP-40G-BIDI-WDM850	R7595
		QSFP-40G-CSR4-MM850	R7595
		QSFP-40G-CSR4-MM850-H	E7637P01
		QSFP-40G-D-AOC-10M	R7595
		QSFP-40G-D-AOC-10M-H	R7639P03
		QSFP-40G-D-AOC-20M	R7595
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7595
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7595
		QSFP-40G-LR4L-WDM1300	R7595
		QSFP-40G-LR4-PSM1310	R7595
		QSFP-40G-LR4-WDM1300	R7595
		QSFP-40G-SR4-MM850	R7595
		QSFP-40G-SR4-MM850-H	E7637P01
		LSXM1CGQ18TE2	1~8,10~17
LSWM1QSTK1	R7595		
LSWM1QSTK2	R7595		
LSWM1QSTK3	R7595		
LSWM1QSTK4	R7595		
LSWM1QSTK5	R7595		
QSFP-100G-4SFP-25G-CAB-1M	R7595		
QSFP-100G-4SFP-25G-CAB-3M	R7595		
QSFP-100G-4SFP-25G-CAB-5M	R7595		

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.
		QSFP-100G-CWDM4-SM1300-A	R7595
		QSFP-100G-D-AOC-10M	R7595
		QSFP-100G-D-AOC-20M	R7595
		QSFP-100G-D-AOC-7M	R7595
		QSFP-100G-D-CAB-1M	R7595
		QSFP-100G-D-CAB-3M	R7595
		QSFP-100G-D-CAB-5M	R7595
		QSFP-100G-ER4L-WDM1300	R7595
		QSFP-100G-eSR4-MM850	R7595
		QSFP-100G-LR4L-WDM1300	R7595
		QSFP-100G-LR4-WDM1300	R7595
		QSFP-100G-PSM4-SM1310	R7595
		QSFP-100G-SR4-MM850	R7595
		QSFP-100G-SR4-MM850-A	R7595
		QSFP-100G-SWDM4-MM850	R7595
		QSFP-40G-BIDI-SR-MM850	R7595
		QSFP-40G-BIDI-WDM850	R7595
		QSFP-40G-CSR4-MM850	R7595
		QSFP-40G-D-AOC-10M	R7595
		QSFP-40G-D-AOC-10M-H	R7639P03
		QSFP-40G-D-AOC-20M	R7595
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7595
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7595
		QSFP-40G-LR4L-WDM1300	R7595

单板名称	端口	支持的光模块	版本适配及说明
		0	
		QSFP-40G-LR4-PSM1310	R7595
		QSFP-40G-LR4-WDM1300	R7595
		QSFP-40G-SR4-MM850	R7595
		LSWM1QSTK0	R7595
		LSWM1QSTK1	R7595
		LSWM1QSTK2	R7595
		QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.
		QSFP-100G-CWDM4-SM1300-A	R7595
		QSFP-100G-D-AOC-10M	R7595
		QSFP-100G-D-AOC-20M	R7595
		QSFP-100G-D-AOC-7M	R7595
		QSFP-100G-D-CAB-1M	R7595
		QSFP-100G-D-CAB-3M	R7595
		QSFP-100G-D-CAB-5M	R7595
		QSFP-100G-ER4L-WDM1300	R7595
		QSFP-100G-eSR4-MM850	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-LR4L-WDM1300	R7595
		QSFP-100G-LR4-WDM1300	R7595
		QSFP-100G-PSM4-SM1310	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850-A	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SWDM4-MM850	R7595
	9,18		

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-BIDI-SR-MM850	R7595
		QSFP-40G-BIDI-WDM850	R7595
		QSFP-40G-CSR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-D-AOC-10M	R7595
		QSFP-40G-D-AOC-10M-H	R7639P03
		QSFP-40G-D-AOC-20M	R7595
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7595
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7595
		QSFP-40G-LR4L-WDM1300	R7595
		QSFP-40G-LR4-PSM1310	R7595
		QSFP-40G-LR4-WDM1300	R7595
		QSFP-40G-SR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports
		LSXM1CGQ36TE2	1~9,11~16,18~27,29~34,36
LSWM1QSTK1	R7595		
LSWM1QSTK2	R7595		
LSWM1QSTK3	R7595		
LSWM1QSTK4	R7595		
LSWM1QSTK5	R7595		
QSFP-100G-4SFP-25G-CAB-1M	R7595		
QSFP-100G-4SFP-25G-CAB-3M	R7595		
QSFP-100G-4SFP-25G-CAB-5M	R7595		
QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.		
QSFP-100G-CWDM4-SM1300-A	R7595		

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-D-AOC-10M	R7595
		QSFP-100G-D-AOC-20M	R7595
		QSFP-100G-D-AOC-7M	R7595
		QSFP-100G-D-AOC-7M-H	E7637P01
		QSFP-100G-D-CAB-1M	R7595
		QSFP-100G-D-CAB-3M	R7595
		QSFP-100G-D-CAB-5M	R7595
		QSFP-100G-ER4L-WDM1300	R7595
		QSFP-100G-eSR4-MM850	R7595
		QSFP-100G-LR4L-WDM1300	R7595
		QSFP-100G-LR4-WDM1300	R7595
		QSFP-100G-PSM4-SM1310	R7595
		QSFP-100G-SR4-MM850	R7595
		QSFP-100G-SR4-MM850-A	R7595
		QSFP-100G-SR4-MM850-H	E775303
		QSFP-100G-SWDM4-MM850	R7595
		QSFP-100G-ZR4-WDM1300	E7637P01, To ensure adequate heat dissipation of transceiver modules with a maximum transmission distance of 80 km (49.71 miles), do not install the transceiver modules in neighbor ports. You can install a maximum of 10 such transceiver modules on a module.
		QSFP-40G-BIDI-SR-MM850	R7595
		QSFP-40G-BIDI-WDM850	R7595
		QSFP-40G-CSR4-MM850	R7595
		QSFP-40G-CSR4-MM850-H	E7637P01
		QSFP-40G-D-AOC-10M	R7595
		QSFP-40G-D-AOC-10M-H	R7639P03

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-D-AOC-20M	R7595
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7595
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7595
		QSFP-40G-LR4L-WDM1300	R7595
		QSFP-40G-LR4-PSM1310	R7595
		QSFP-40G-LR4-WDM1300	R7595
		QSFP-40G-SR4-MM850	R7595
		QSFP-40G-SR4-MM850-H	E7637P01
	10,17,28,35	LSWM1QSTK0	R7595
		LSWM1QSTK1	R7595
		LSWM1QSTK2	R7595
		QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.
		QSFP-100G-CWDM4-SM1300-A	R7595
		QSFP-100G-D-AOC-10M	R7595
		QSFP-100G-D-AOC-20M	R7595
		QSFP-100G-D-AOC-7M	R7595
		QSFP-100G-D-AOC-7M-H	E7637P01
		QSFP-100G-D-CAB-1M	R7595
		QSFP-100G-D-CAB-3M	R7595
		QSFP-100G-D-CAB-5M	R7595
		QSFP-100G-ER4L-WDM1300	R7595
		QSFP-100G-eSR4-MM850	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-LR4L-WDM1300	R7595
		QSFP-100G-LR4-WDM1300	R7595



单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-PSM4-SM1310	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850-A	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850-H	E775303
		QSFP-100G-SWDM4-MM850	R7595
		QSFP-100G-ZR4-WDM1300	E7637P01, Supports mixed installation of twelve 80 km (49.71 miles) transceiver modules and five 40 km (24.86 miles) transceiver modules.
		QSFP-40G-BIDI-SR-MM850	R7595
		QSFP-40G-BIDI-WDM850	R7595
		QSFP-40G-CSR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-CSR4-MM850-H	E7637P01
		QSFP-40G-D-AOC-10M	R7595
		QSFP-40G-D-AOC-10M-H	R7639P03
		QSFP-40G-D-AOC-20M	R7595
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7595
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7595
		QSFP-40G-LR4L-WDM1300	R7595
		QSFP-40G-LR4-PSM1310	R7595
		QSFP-40G-LR4-WDM1300	R7595
		QSFP-40G-SR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-SR4-MM850-H	E7637P01

单板名称	端口	支持的光模块	版本适配及说明
LSXM1CGQ8TD2	1~7	LSWM1QSTK0	R7595
		LSWM1QSTK1	R7595
		LSWM1QSTK2	R7595
		LSWM1QSTK3	R7595
		LSWM1QSTK4	R7595
		LSWM1QSTK5	R7595
		QSFP-100G-4SFP-25G-CAB-1M	R7595
		QSFP-100G-4SFP-25G-CAB-3M	R7595
		QSFP-100G-4SFP-25G-CAB-5M	R7595
		QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.
		QSFP-100G-CWDM4-SM1300-A	R7595
		QSFP-100G-D-AOC-10M	R7595
		QSFP-100G-D-AOC-20M	R7595
		QSFP-100G-D-AOC-7M	R7595
		QSFP-100G-D-CAB-1M	R7595
		QSFP-100G-D-CAB-3M	R7595
		QSFP-100G-D-CAB-5M	R7595
		QSFP-100G-ER4L-WDM1300	R7595
		QSFP-100G-eSR4-MM850	R7595
		QSFP-100G-LR4L-WDM1300	R7595
		QSFP-100G-LR4-WDM1300	R7595
		QSFP-100G-PSM4-SM1310	R7595
		QSFP-100G-SR4-MM850	R7595
		QSFP-100G-SR4-MM850-A	R7595
QSFP-100G-SR4-MM850-H	E775303		
QSFP-100G-SWDM4-MM8	R7595		

单板名称	端口	支持的光模块	版本适配及说明
		50	
		QSFP-40G-BIDI-SR-MM850	R7595
		QSFP-40G-BIDI-WDM850	R7595
		QSFP-40G-CSR4-MM850	R7595
		QSFP-40G-CSR4-MM850-H	E7637P01
		QSFP-40G-D-AOC-10M	R7595
		QSFP-40G-D-AOC-10M-H	R7639P03
		QSFP-40G-D-AOC-20M	R7595
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7595
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7595
		QSFP-40G-LR4L-WDM1300	R7595
		QSFP-40G-LR4-PSM1310	R7595
		QSFP-40G-LR4-WDM1300	R7595
		QSFP-40G-SR4-MM850	R7595
		QSFP-40G-SR4-MM850-H	E7637P01
	8	LSWM1QSTK0	R7595
		LSWM1QSTK1	R7595
		LSWM1QSTK2	R7595
		QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.
		QSFP-100G-CWDM4-SM1300-A	R7595
		QSFP-100G-D-AOC-10M	R7595
		QSFP-100G-D-AOC-20M	R7595
		QSFP-100G-D-AOC-7M	R7595
		QSFP-100G-D-CAB-1M	R7595
		QSFP-100G-D-CAB-3M	R7595
		QSFP-100G-D-CAB-5M	R7595

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-ER4L-WDM1300	R7595
		QSFP-100G-eSR4-MM850	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-LR4L-WDM1300	R7595
		QSFP-100G-LR4-WDM1300	R7595
		QSFP-100G-PSM4-SM1310	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850-A	R7595, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850-H	E775303
		QSFP-100G-SWDM4-MM850	R7595
		QSFP-40G-BIDI-SR-MM850	R7595
		QSFP-40G-BIDI-WDM850	R7595
		QSFP-40G-CSR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-CSR4-MM850-H	E7637P01
		QSFP-40G-D-AOC-10M	R7595
		QSFP-40G-D-AOC-10M-H	R7639P03
		QSFP-40G-D-AOC-20M	R7595
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7595
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7595
		QSFP-40G-LR4L-WDM1300	R7595
		QSFP-40G-LR4-PSM1310	R7595
		QSFP-40G-LR4-WDM1300	R7595

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-SR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-SR4-MM850-H	E7637P01
LSXM1GT24GPSE2	25~48	SFP-GE-LH100-SM1550	R8043P06
		SFP-GE-LH40-SM1310	R8043P06
		SFP-GE-LH40-SM1310-BIDI	R8043P06
		SFP-GE-LH40-SM1310-D	R8043P06
		SFP-GE-LH40-SM1550	R8043P06
		SFP-GE-LH40-SM1550-BIDI	R8043P06
		SFP-GE-LH70-SM1490-BIDI	R8043P06
		SFP-GE-LH70-SM1550-BIDI	R8043P06
		SFP-GE-LH80-SM1550	R8043P06
		SFP-GE-LH80-SM1550-D	R8043P06
		SFP-GE-LX-SM1310-A	R8043P06
		SFP-GE-LX-SM1310-BIDI	R8043P06
		SFP-GE-LX-SM1310-D	R8043P06
		SFP-GE-LX-SM1490-BIDI	R8043P06
		SFP-GE-SX-MM850-A	R8043P06
		SFP-GE-SX-MM850-D	R8043P06
		SFP-GE-T	R8043P06
		SFP-GE-T-D	R8043P06
LSXM1QGS36TD2	1~36	LSWM1QSTK0	R7595
		LSWM1QSTK1	R7595
		LSWM1QSTK2	R7595
		QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.
		QSFP-40G-BIDI-SR-MM850	R7595
		QSFP-40G-BIDI-WDM850	R7595

单板名称	端口	支持的光模块	版本适配及说明		
		QSFP-40G-CSR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports		
		QSFP-40G-CSR4-MM850-H	E7637P01		
		QSFP-40G-D-AOC-10M	R7595		
		QSFP-40G-D-AOC-10M-H	R7639P03		
		QSFP-40G-D-AOC-20M	R7595		
		QSFP-40G-D-AOC-20M-H	R7639P03		
		QSFP-40G-D-AOC-7M	R7595		
		QSFP-40G-D-AOC-7M-H	R7639P03		
		QSFP-40G-ER4-WDM1300	R7595		
		QSFP-40G-LR4L-WDM1300	R7595		
		QSFP-40G-LR4-PSM1310	R7595		
		QSFP-40G-LR4-WDM1300	R7595		
		QSFP-40G-LX4-WDM1300	R7639P03		
		QSFP-40G-SR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports		
		QSFP-40G-SR4-MM850-H	E7637P01		
		LSXM1QGS36TE2	1~36	LSWM1QSTK0	R7595
				LSWM1QSTK1	R7595
LSWM1QSTK2	R7595				
QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.				
QSFP-40G-BIDI-SR-MM850	R7595				
QSFP-40G-BIDI-WDM850	R7595				
QSFP-40G-CSR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports				
QSFP-40G-D-AOC-10M	R7595				
QSFP-40G-D-AOC-10M-H	R7639P03				
QSFP-40G-D-AOC-20M	R7595				

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7595
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7595
		QSFP-40G-LR4L-WDM1300	R7595
		QSFP-40G-LR4-PSM1310	R7595
		QSFP-40G-LR4-WDM1300	R7595
		QSFP-40G-SR4-MM850	R7595, a QSFP+ port cannot be split into four 10G SFP+ ports
LSXM1SEERBA2	1~2,网口1~2	SFP-XG-SX-MM850-D	R7624P68
		SFP-XG-SX-MM850-E	R7624P68
		SFP-XG-SX-MM850-S	R7624P68
LSXM1SEERBG2	1~2,网口1~2	SFP-XG-SX-MM850-D	R7595
		SFP-XG-SX-MM850-E	R7595
		SFP-XG-SX-MM850-S	R7595
LSXM1SEERBXC2	1~2,网口1~2	SFP-XG-SX-MM850-D	R7595
		SFP-XG-SX-MM850-E	R7595
		SFP-XG-SX-MM850-S	R7595
LSXM1SEERBXD2	1~2,网口1~2	SFP-XG-SX-MM850-D	R7595
		SFP-XG-SX-MM850-E	R7595
		SFP-XG-SX-MM850-S	R7595
LSXM1SUP04T2	ALL	SFP-GE-LH100-SM1550	R7595
		SFP-GE-LH40-SM1310	R7595
		SFP-GE-LH40-SM1310-D	R7595
		SFP-GE-LH40-SM1550	R7595
		SFP-GE-LH80-SM1550	R7595
		SFP-GE-LH80-SM1550-D	R7595
		SFP-GE-LX-SM1310-A	R7595
		SFP-GE-LX-SM1310-BIDI	R7595
		SFP-GE-LX-SM1310-D	R7595
		SFP-GE-LX-SM1310-S	R7595

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LX-SM1490-BIDI	R7595
		SFP-GE-SX-MM850-A	R7595
		SFP-GE-SX-MM850-D	R7595
		SFP-GE-SX-MM850-S	R7595
		SFP-GE-T	R7595
		SFP-GE-T-D	R7595
LSXM1SUPS2	ALL	SFP-GE-LH100-SM1550	R8043P06
		SFP-GE-LH40-SM1310	R8043P06
		SFP-GE-LH40-SM1310-D	R8043P06
		SFP-GE-LH40-SM1550	R8043P06
		SFP-GE-LH80-SM1550	R8043P06
		SFP-GE-LH80-SM1550-D	R8043P06
		SFP-GE-LX-SM1310-A	R8043P06
		SFP-GE-LX-SM1310-BIDI	R8043P06
		SFP-GE-LX-SM1310-D	R8043P06
		SFP-GE-LX-SM1490-BIDI	R8043P06
		SFP-GE-SX-MM850-A	R8043P06
		SFP-GE-SX-MM850-D	R8043P06
LSXM1TGS24XT24C4Q2TE21~24		CAB-0.5M-SFP+	R7624P68
		CAB-1M-SFP+	R7624P68
		CAB-3M-SFP+	R7624P68
		LSTM1STK	R7624P68
		LSWM1STK	R7624P68
		LSWM2STK	R7624P68
		LSWM3STK	R7624P68
		SFP-10G-D-CAB-3M-Z	R7624P68
		SFP-XG-D-AOC-10M-H	R7639P03
		SFP-XG-D-AOC-20M-H	R7639P03
		SFP-XG-D-AOC-7M-H	R7639P03
		SFP-XG-LH40-SM1270-BIDI	R7624P68
		SFP-XG-LH40-SM1330-BIDI	R7624P68



单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LH40-SM1550	R7624P68
		SFP-XG-LH40-SM1550-D	R7624P68
		SFP-XG-LH80-SM1490-BIDI	R7624P68
		SFP-XG-LH80-SM1550	R7624P68
		SFP-XG-LH80-SM1550-BIDI	R7624P68
		SFP-XG-LH80-SM1550-D	R7624P68
		SFP-XG-LX-SM1270-BIDI	R7624P68
		SFP-XG-LX-SM1310-D	R7624P68
		SFP-XG-LX-SM1310-E	R7624P68
		SFP-XG-LX-SM1310-S	R7624P68
		SFP-XG-LX-SM1330-BIDI	R7624P68
		SFP-XG-SX-MM850-D	R7624P68
		SFP-XG-SX-MM850-E	R7624P68
		SFP-XG-SX-MM850-S	R7624P68
	25~28	QSFP-100G-BIDI-MM850	F7637P0301, You can use the speed command to modify the speed of this optical module to 40G.
		QSFP-100G-CWDM4-SM1300-A	R7624P68
		QSFP-100G-D-AOC-10M	R7624P68
		QSFP-100G-D-AOC-20M	R7624P68
		QSFP-100G-D-AOC-7M	R7624P68
		QSFP-100G-D-CAB-1M	R7624P68
		QSFP-100G-D-CAB-3M	R7624P68
		QSFP-100G-D-CAB-5M	R7624P68
		QSFP-100G-ER4L-WDM1300	R7624P68
		QSFP-100G-eSR4-MM850	R7624P68
		QSFP-100G-LR4L-WDM1300	R7624P68
		QSFP-100G-LR4-WDM1300	R7624P68
		QSFP-100G-LR4-WDM1300-A	R7624P68

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-PSM4-SM1310	R7624P68
		QSFP-100G-SR4-MM850	R7624P68
		QSFP-100G-SR4-MM850-A	R7624P68
		QSFP-100G-SWDM4-MM850	R7624P68
	53~54, 25~28	LSWM1QSTK0	R7624P68
		LSWM1QSTK1	R7624P68
		LSWM1QSTK2	R7624P68
		QSFP-40G-BIDI-SR-MM850	R7624P68
		QSFP-40G-BIDI-WDM850	R7624P68
		QSFP-40G-CSR4-MM850	R7624P68
		QSFP-40G-D-AOC-10M	R7624P68
		QSFP-40G-D-AOC-10M-H	R7639P03
		QSFP-40G-D-AOC-20M	R7624P68
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7624P68
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7624P68
		QSFP-40G-LR4L-WDM1300	R7624P68
		QSFP-40G-LR4-PSM1310	R7624P68
		QSFP-40G-LR4-WDM1300	R7624P68
QSFP-40G-LX4-WDM1300	F7639P51		
QSFP-40G-SR4-MM850	R7624P68		
LSXM1TGS48SE2	1~48	CAB-0.5M-SFP+	R8043P06, Can only be used for IRF/M-LAG setup connections.
		CAB-1M-SFP+	R8043P06, Can only be used for IRF/M-LAG setup connections.
		CAB-3M-SFP+	R8043P06, Can only be used for IRF/M-LAG setup connections.
		LSTM1STK	R8043P06, Can only be used for IRF/M-LAG setup

单板名称	端口	支持的光模块	版本适配及说明
			connections.
		LSWM1STK	R8043P06, Can only be used for IRF/M-LAG setup connections.
		LSWM2STK	R8043P06, Can only be used for IRF/M-LAG setup connections.
		LSWM3STK	R8043P06, Can only be used for IRF/M-LAG setup connections.
		SFP-10G-D-CAB-3M-Z	R8043P06, Can only be used for IRF/M-LAG setup connections.
		SFP-2.5G-LX10-SM1310-D R-I	R7755P01
		SFP-GE-LH100-SM1550	R8043P06
		SFP-GE-LH40-SM1310	R8043P06
		SFP-GE-LH40-SM1310-BIDI	R8043P06
		SFP-GE-LH40-SM1310-D	R8043P06
		SFP-GE-LH40-SM1550	R8043P06
		SFP-GE-LH40-SM1550-BIDI	R8043P06
		SFP-GE-LH70-SM1490-BIDI	R8043P06
		SFP-GE-LH70-SM1550-BIDI	R8043P06
		SFP-GE-LH80-SM1550	R8043P06
		SFP-GE-LH80-SM1550-D	R8043P06
		SFP-GE-LX-SM1310-A	R8043P06
		SFP-GE-LX-SM1310-BIDI	R8043P06
		SFP-GE-LX-SM1310-D	R8043P06
		SFP-GE-LX-SM1490-BIDI	R8043P06
		SFP-GE-SX-MM850-A	R8043P06
		SFP-GE-SX-MM850-D	R8043P06
		SFP-GE-T	R8043P06
		SFP-GE-T-D	R8043P06
		SFP-XG-LH40-SM1550	R8043P06

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LH40-SM1550-D	R8043P06
		SFP-XG-LH80-SM1550	R8043P06
		SFP-XG-LH80-SM1550-D	R8043P06
		SFP-XG-LX-SM1310	R8043P06
		SFP-XG-LX-SM1310-D	R8043P06
		SFP-XG-LX-SM1310-E	R8043P06
		SFP-XG-SX-MM850-A	R8043P06
		SFP-XG-SX-MM850-D	R8043P06
		SFP-XG-SX-MM850-E	R8043P06
		SFP-XG-SX-MM850-F1	R8043P06
		LSXM1TGS48TD2	1~48
CAB-1M-SFP+	R7595		
CAB-3M-SFP+	R7595		
LSTM1STK	R7595		
LSTM2STK	R7595		
LSWM1STK	R7595		
LSWM2STK	R7595		
LSWM3STK	R7595		
SFP-10GE-T	E7633P01, Up to eight interfaces are supported. For an interface inserted with a transceiver module, you cannot insert transceiver modules of the same model into the adjacent interfaces on the top, bottom, left, and right of the interface.		
SFP-GE-LH100-SM1550	R7595		
SFP-GE-LH40-SM1310	R7595		
SFP-GE-LH40-SM1310-D	R7595		
SFP-GE-LH40-SM1550	R7595		
SFP-GE-LH80-SM1550	R7595		
SFP-GE-LH80-SM1550-D	R7595		
SFP-GE-LX-SM1310-A	R7595		
SFP-GE-LX-SM1310-BIDI	R7595		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LX-SM1310-D	R7595
		SFP-GE-LX-SM1490-BIDI	R7595
		SFP-GE-SX-MM850-A	R7595
		SFP-GE-SX-MM850-D	R7595
		SFP-GE-T	R7595
		SFP-GE-T-D	R7595
		SFP-XG-D-AOC-10M	R7595
		SFP-XG-D-AOC-10M-H	R7639P03
		SFP-XG-D-AOC-20M	R7595
		SFP-XG-D-AOC-20M-H	R7639P03
		SFP-XG-D-AOC-7M	R7595
		SFP-XG-D-AOC-7M-H	R7639P03
		SFP-XG-LH40-SM1270-BIDI	R7595
		SFP-XG-LH40-SM1330-BIDI	R7595
		SFP-XG-LH40-SM1550	R7595
		SFP-XG-LH40-SM1550-D	R7595
		SFP-XG-LH80-SM1490-BIDI	R7595
		SFP-XG-LH80-SM1550	R7595
		SFP-XG-LH80-SM1550-BIDI	R7595
		SFP-XG-LH80-SM1550-D	R7595
		SFP-XG-LH80-Tunable	R7595
		SFP-XG-LX-SM1270-BIDI	R7595
		SFP-XG-LX-SM1310	R7595
		SFP-XG-LX-SM1310-D	R7595
		SFP-XG-LX-SM1310-E	R7595
		SFP-XG-LX-SM1330-BIDI	R7595
		SFP-XG-SX-MM850-A	R7595
		SFP-XG-SX-MM850-D	R7595
		SFP-XG-SX-MM850-E	R7595
		SFP-XG-SX-MM850-F1	R7595

单板名称	端口	支持的光模块	版本适配及说明
LSXM1TGS48TE2	1~48	CAB-0.5M-SFP+	R7595
		CAB-1M-SFP+	R7595
		CAB-3M-SFP+	R7595
		LSTM1STK	R7595
		LSTM2STK	R7595
		LSWM1STK	R7595
		LSWM2STK	R7595
		LSWM3STK	R7595
		SFP-10GE-T	E7633P01, Up to eight interfaces are supported. For an interface inserted with a transceiver module, you cannot insert transceiver modules of the same model into the adjacent interfaces on the top, bottom, left, and right of the interface.
		SFP-GE-LH100-SM1550	R7595
		SFP-GE-LH40-SM1310	R7595
		SFP-GE-LH40-SM1310-D	R7595
		SFP-GE-LH40-SM1550	R7595
		SFP-GE-LH80-SM1550	R7595
		SFP-GE-LH80-SM1550-D	R7595
		SFP-GE-LX-SM1310-A	R7595
		SFP-GE-LX-SM1310-BIDI	R7595
		SFP-GE-LX-SM1310-D	R7595
		SFP-GE-LX-SM1490-BIDI	R7595
		SFP-GE-SX-MM850-A	R7595
		SFP-GE-SX-MM850-D	R7595
		SFP-GE-T	R7595
		SFP-GE-T-D	R7595
SFP-XG-D-AOC-10M	R7595		
SFP-XG-D-AOC-10M-H	R7639P03		
SFP-XG-D-AOC-20M	R7595		
SFP-XG-D-AOC-20M-H	R7639P03		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-D-AOC-7M	R7595
		SFP-XG-D-AOC-7M-H	R7639P03
		SFP-XG-LH40-SM1270-BIDI	R7595
		SFP-XG-LH40-SM1330-BIDI	R7595
		SFP-XG-LH40-SM1550	R7595
		SFP-XG-LH40-SM1550-D	R7595
		SFP-XG-LH80-SM1490-BIDI	R7595
		SFP-XG-LH80-SM1550	R7595
		SFP-XG-LH80-SM1550-BIDI	R7595
		SFP-XG-LH80-SM1550-D	R7595
		SFP-XG-LH80-Tunable	R7595
		SFP-XG-LX-SM1270-BIDI	R7595
		SFP-XG-LX-SM1310	R7595
		SFP-XG-LX-SM1310-D	R7595
		SFP-XG-LX-SM1310-E	R7595
		SFP-XG-LX-SM1330-BIDI	R7595
		SFP-XG-SX-MM850-A	R7595
		SFP-XG-SX-MM850-D	R7595
		SFP-XG-SX-MM850-E	R7595
		SFP-XG-SX-MM850-F1	R7595
LSXM1YGS24CGMODTE2	1~24	CAB-0.5M-SFP+	E7634P04
		CAB-1M-SFP+	E7634P04
		CAB-3M-SFP+	E7634P04
		LSTM1STK	E7634P04
		LSTM2STK	E7634P04
		LSWM1STK	E7634P04
		LSWM2STK	E7634P04
		LSWM3STK	E7634P04

单板名称	端口	支持的光模块	版本适配及说明
		SFP-10GE-T	E7634P04, Up to eight interfaces are supported. For an interface inserted with a transceiver module, you cannot insert transceiver modules of the same model into the adjacent interfaces on the top, bottom, left, and right of the interface.
		SFP-25G-D-AOC-10M	R7624P07
		SFP-25G-D-AOC-20M	R7624P07
		SFP-25G-D-AOC-3M	R7624P07
		SFP-25G-D-AOC-5M	R7624P07
		SFP-25G-D-AOC-7M	R7624P07
		SFP-25G-D-CAB-1M	R7624P07
		SFP-25G-D-CAB-3M	R7624P07
		SFP-25G-D-CAB-5M	R7624P07
		SFP-25G-LR-SM1310	R7624P07
		SFP-25G-SR-MM850	R7624P07
		SFP-XG-D-AOC-10M	E7634P04
		SFP-XG-D-AOC-10M-H	R7639P03
		SFP-XG-D-AOC-20M	E7634P04
		SFP-XG-D-AOC-20M-H	R7639P03
		SFP-XG-D-AOC-7M	E7634P04
		SFP-XG-D-AOC-7M-H	R7639P03
		SFP-XG-LH40-SM1270-BIDI	E7634P04
		SFP-XG-LH40-SM1330-BIDI	E7634P04
		SFP-XG-LH40-SM1550	E7634P04
		SFP-XG-LH40-SM1550-D	E7634P04
		SFP-XG-LH80-SM1550	E7634P04
		SFP-XG-LH80-SM1550-D	E7634P04
		SFP-XG-LX-SM1270-BIDI	E7634P04
		SFP-XG-LX-SM1310	E7634P04
		SFP-XG-LX-SM1310-D	E7634P04



单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LX-SM1310-E	E7634P04
		SFP-XG-LX-SM1330-BIDI	E7634P04
		SFP-XG-SX-MM850-A	E7634P04
		SFP-XG-SX-MM850-D	E7634P04
		SFP-XG-SX-MM850-E	E7634P04
		SFP-XG-SX-MM850-F1	E7634P04
	25~28	LSWM1QSTK0	R7624P07
		LSWM1QSTK1	R7624P07
		LSWM1QSTK2	R7624P07
		QSFP-100G-CWDM4-SM1300-A	R7624P07
		QSFP-100G-D-AOC-10M	R7624P07
		QSFP-100G-D-AOC-20M	R7624P07
		QSFP-100G-D-AOC-7M	R7624P07
		QSFP-100G-D-CAB-1M	R7624P07
		QSFP-100G-D-CAB-3M	R7624P07
		QSFP-100G-D-CAB-5M	R7624P07
		QSFP-100G-ER4L-WDM1300	R7624P07
		QSFP-100G-ER4-WDM1300	E7634P03
		QSFP-100G-eSR4-MM850	R7624P07, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-LR4L-WDM1300	R7624P07
		QSFP-100G-LR4-WDM1300	R7624P07
		QSFP-100G-LR4-WDM1300-A	R7624P07
		QSFP-100G-PSM4-SM1310	R7624P07, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850	R7624P07, a QSFP28 port cannot be split into four 25G SFP28 ports
		QSFP-100G-SR4-MM850-A	R7624P07, a QSFP28 port cannot be split into four 25G

单板名称	端口	支持的光模块	版本适配及说明
			SFP28 ports
		QSFP-100G-SWDM4-MM850	R7624P07
		QSFP-100G-ZR4-WDM1300	E7634P03
		QSFP-40G-BIDI-SR-MM850	R7624P07
		QSFP-40G-BIDI-WDM850	R7624P07
		QSFP-40G-CSR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports
		QSFP-40G-D-AOC-10M	R7624P07
		QSFP-40G-D-AOC-10M-H	R7639P03
		QSFP-40G-D-AOC-20M	R7624P07
		QSFP-40G-D-AOC-20M-H	R7639P03
		QSFP-40G-D-AOC-7M	R7624P07
		QSFP-40G-D-AOC-7M-H	R7639P03
		QSFP-40G-ER4-WDM1300	R7624P07
		QSFP-40G-LR4L-WDM1300	R7624P07
		QSFP-40G-LR4-PSM1310	R7624P07
		QSFP-40G-LR4-WDM1300	R7624P07
		QSFP-40G-SR4-MM850	R7624P07, a QSFP+ port cannot be split into four 10G SFP+ ports
LSXM2SUPT2	ALL	SFP-GE-LH100-SM1550	R7595
		SFP-GE-LH40-SM1310	R7595
		SFP-GE-LH40-SM1310-D	R7595
		SFP-GE-LH40-SM1550	R7595
		SFP-GE-LH80-SM1550	R7595
		SFP-GE-LH80-SM1550-D	R7595
		SFP-GE-LX-SM1310-A	R7595
		SFP-GE-LX-SM1310-BIDI	R7595
		SFP-GE-LX-SM1310-D	R7595
		SFP-GE-LX-SM1490-BIDI	R7595

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-SX-MM850-A	R7595
		SFP-GE-SX-MM850-D	R7595
		SFP-GE-T	R7595
		SFP-GE-T-D	R7595
LSXM3CDQ16SF2	1~16	CAB-400G-QSFP-DD-2m	R8054
		LSWM1QSTK0	R8054
		LSWM1QSTK1	R8054
		LSWM1QSTK2	R8054
		QSFP-100G-CWDM4-SM1300-A	R8054
		QSFP-100G-D-AOC-10M	R8054
		QSFP-100G-D-AOC-20M	R8054
		QSFP-100G-D-AOC-7M	R8054
		QSFP-100G-D-CAB-1M	R8054
		QSFP-100G-D-CAB-3M	R8054
		QSFP-100G-D-CAB-5M	R8054
		QSFP-100G-ER4L-WDM1300	R8054
		QSFP-100G-LR4L-WDM1300	R8054
		QSFP-100G-LR4-WDM1300	R8054
		QSFP-100G-LR4-WDM1300-A	R8054
		QSFP-100G-PSM4-SM1310	R8054
		QSFP-100G-SR4-MM850	R8054
		QSFP-100G-SR4-MM850-A	R8054
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	R8054
		QSFP-40G-BIDI-SR-MM850	R8054
		QSFP-40G-BIDI-WDM850	R8054
		QSFP-40G-CSR4-MM850	R8054
		QSFP-40G-D-AOC-10M	R8054

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-D-AOC-20M	R8054
		QSFP-40G-D-AOC-7M	R8054
		QSFP-40G-ER4-WDM1300	R8054
		QSFP-40G-LR4L-WDM1300	R8054
		QSFP-40G-LR4-PSM1310	R8054
		QSFP-40G-LR4-WDM1300	R8054
		QSFP-40G-LX4-WDM1300	R8054P10
		QSFP-40G-SR4-MM850	R8054
		QSFP56-200G-D-DAC-1m	R8053P09
		QSFP56-200G-D-DAC-2m	R8053P09
		QSFP56-200G-D-DAC-3m	R8053P09
		QSFP56-200G-FR4-WDM1300	R8053P09
		QSFP56-200G-SR4-MM850	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-10m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-20m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-30m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-50m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-5m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-7m	R8053P09
		QSFPDD-400G-FR4-WDM1300	R8054
		QSFPDD-400G-LR4-WDM1300-DC	R8053P09
		QSFPDD-400G-LR8-WDM1300	R8053P09
		QSFPDD-400G-SR8-MM850	R8054
		QSFPDD-400G-ZR-B	R8053P09
LSXM3CDQ8SF2	1~8	CAB-400G-QSFP-DD-2m	R8054

单板名称	端口	支持的光模块	版本适配及说明
		LSWM1QSTK0	R8054
		LSWM1QSTK1	R8054
		LSWM1QSTK2	R8054
		QSFP-100G-CWDM4-SM1300-A	R8054
		QSFP-100G-D-AOC-10M	R8054
		QSFP-100G-D-AOC-20M	R8054
		QSFP-100G-D-AOC-7M	R8054
		QSFP-100G-D-CAB-1M	R8054
		QSFP-100G-D-CAB-3M	R8054
		QSFP-100G-D-CAB-5M	R8054
		QSFP-100G-ER4L-WDM1300	R8054
		QSFP-100G-LR4L-WDM1300	R8054
		QSFP-100G-LR4-WDM1300	R8054
		QSFP-100G-LR4-WDM1300-A	R8054
		QSFP-100G-PSM4-SM1310	R8054
		QSFP-100G-SR4-MM850	R8054
		QSFP-100G-SR4-MM850-A	R8054
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	R8054
		QSFP-40G-BIDI-SR-MM850	R8054
		QSFP-40G-BIDI-WDM850	R8054
		QSFP-40G-CSR4-MM850	R8054
		QSFP-40G-D-AOC-10M	R8054
		QSFP-40G-D-AOC-20M	R8054
		QSFP-40G-D-AOC-7M	R8054
		QSFP-40G-ER4-WDM1300	R8054
		QSFP-40G-LR4L-WDM1300	R8054

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-LR4-PSM1310	R8054
		QSFP-40G-LR4-WDM1300	R8054
		QSFP-40G-LX4-WDM1300	R8054P10
		QSFP-40G-SR4-MM850	R8054
		QSFP56-200G-D-DAC-1m	R8053P09
		QSFP56-200G-D-DAC-2m	R8053P09
		QSFP56-200G-D-DAC-3m	R8053P09
		QSFP56-200G-FR4-WDM1300	R8053P09
		QSFP56-200G-SR4-MM850	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-10m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-20m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-30m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-50m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-5m	R8053P09
		QSFPDD-400G-2QSFP56-200G-AOC-7m	R8053P09
		QSFPDD-400G-FR4-WDM1300	R8054
		QSFPDD-400G-LR4-WDM1300-DC	R8053P09
		QSFPDD-400G-LR8-WDM1300	R8053P09
		QSFPDD-400G-SR8-MM850	R8054
		QSFPDD-400G-ZR-B	R8053P09
LSXM3CGQ18SF2	1~18	LSWM1QSTK0	E8051P02
		LSWM1QSTK1	E8051P02
		LSWM1QSTK2	E8051P02
		LSWM1QSTK3	E8051P02
		LSWM1QSTK4	E8051P02
		LSWM1QSTK5	E8051P02

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-4SFP-25G-CAB-3M	E8051P02
		QSFP-100G-4SFP-25G-CAB-5M	E8051P02
		QSFP-100G-BIDI-MM850	E8054
		QSFP-100G-CWDM4-SM1300-A	E8051P02
		QSFP-100G-D-AOC-10M	E8051P02
		QSFP-100G-D-AOC-20M	E8051P02
		QSFP-100G-D-AOC-7M	E8051P02
		QSFP-100G-D-CAB-1M	E8051P02
		QSFP-100G-D-CAB-3M	E8051P02
		QSFP-100G-D-CAB-5M	E8051P02
		QSFP-100G-ER4L-WDM1300	E8051P02
		QSFP-100G-eSR4-MM850	E8051P02
		QSFP-100G-LR4L-WDM1300	E8051P02
		QSFP-100G-LR4-WDM1300	E8051P02
		QSFP-100G-LR4-WDM1300-A	E8051P02
		QSFP-100G-PSM4-SM1310	E8051P02
		QSFP-100G-SR4-MM850	E8051P02
		QSFP-100G-SR4-MM850-A	E8051P02
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	E8051P02
		QSFP-40G-BIDI-SR-MM850	E8051P02
		QSFP-40G-BIDI-WDM850	E8051P02
		QSFP-40G-CSR4-MM850	E8051P02
		QSFP-40G-D-AOC-10M	E8051P02
		QSFP-40G-D-AOC-20M	E8051P02
		QSFP-40G-D-AOC-7M	E8051P02
		QSFP-40G-ER4-WDM1300	E8051P02

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-LR4L-WDM1300	E8051P02
		QSFP-40G-LR4-PSM1310	E8051P02
		QSFP-40G-LR4-WDM1300	E8051P02
		QSFP-40G-LX4-WDM1300	R8054P10
		QSFP-40G-SR4-MM850	E8051P02
LSXM3CGQ36SF2	1~36	LSWM1QSTK0	E8045P10
		LSWM1QSTK1	E8045P10
		LSWM1QSTK2	E8045P10
		LSWM1QSTK3	E8045P10
		LSWM1QSTK4	E8045P10
		LSWM1QSTK5	E8045P10
		QSFP-100G-4SFP-25G-CAB-1M	E8045P10
		QSFP-100G-4SFP-25G-CAB-3M	E8045P10
		QSFP-100G-4SFP-25G-CAB-5M	E8045P10
		QSFP-100G-BIDI-MM850	R8055P01
		QSFP-100G-CWDM4-SM1300-A	E8045P10
		QSFP-100G-D-AOC-10M	E8045P10
		QSFP-100G-D-AOC-20M	E8045P10
		QSFP-100G-D-AOC-7M	E8045P10
		QSFP-100G-D-CAB-1M	E8045P10
		QSFP-100G-D-CAB-3M	E8045P10
		QSFP-100G-D-CAB-5M	E8045P10
		QSFP-100G-ER4L-WDM1300	E8045P10
		QSFP-100G-eSR4-MM850	E8045P10
		QSFP-100G-LR4L-WDM1300	E8045P10
		QSFP-100G-LR4-WDM1300	E8045P10
QSFP-100G-LR4-WDM1300-A	E8045P10		



单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-PSM4-SM1310	E8045P10
		QSFP-100G-SR4-MM850	E8045P10
		QSFP-100G-SR4-MM850-A	E8045P10
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	E8045P10
		QSFP-40G-BIDI-SR-MM850	E8045P10
		QSFP-40G-BIDI-WDM850	E8045P10
		QSFP-40G-CSR4-MM850	E8045P10
		QSFP-40G-D-AOC-10M	E8045P10
		QSFP-40G-D-AOC-20M	E8045P10
		QSFP-40G-D-AOC-7M	E8045P10
		QSFP-40G-ER4-WDM1300	E8045P10
		QSFP-40G-LR4L-WDM1300	E8045P10
		QSFP-40G-LR4-PSM1310	E8045P10
		QSFP-40G-LR4-WDM1300	E8045P10
		QSFP-40G-LX4-WDM1300	R8053P07
		QSFP-40G-SR4-MM850	E8045P10
		LSXM3GP48SE2	1~48
SFP-GE-LH40-SM1310	R7743P06		
SFP-GE-LH40-SM1310-BIDI	R7743P06		
SFP-GE-LH40-SM1310-D	R7743P06		
SFP-GE-LH40-SM1550	R7743P06		
SFP-GE-LH40-SM1550-BIDI	R7743P06		
SFP-GE-LH70-SM1490-BIDI	R7743P06		
SFP-GE-LH70-SM1550-BIDI	R7743P06		
SFP-GE-LH80-SM1550	R7743P06		
SFP-GE-LH80-SM1550-D	R7743P06		
SFP-GE-LX-SM1310-A	R7743P06		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LX-SM1310-BIDI	R7743P06
		SFP-GE-LX-SM1310-D	R7743P06
		SFP-GE-LX-SM1490-BIDI	R7743P06
		SFP-GE-SX-MM850-A	R7743P06
		SFP-GE-SX-MM850-D	R7743P06
		SFP-GE-T	R7743P06
		SFP-GE-T-D	R7743P06
LSXM3GT24GPSE2	25~48	SFP-GE-LH100-SM1550	R7743P06
		SFP-GE-LH40-SM1310	R7743P06
		SFP-GE-LH40-SM1310-BIDI	R7743P06
		SFP-GE-LH40-SM1310-D	R7743P06
		SFP-GE-LH40-SM1550	R7743P06
		SFP-GE-LH40-SM1550-BIDI	R7743P06
		SFP-GE-LH70-SM1490-BIDI	R7743P06
		SFP-GE-LH70-SM1550-BIDI	R7743P06
		SFP-GE-LH80-SM1550	R7743P06
		SFP-GE-LH80-SM1550-D	R7743P06
		SFP-GE-LX-SM1310-A	R7743P06
		SFP-GE-LX-SM1310-BIDI	R7743P06
		SFP-GE-LX-SM1310-D	R7743P06
		SFP-GE-LX-SM1490-BIDI	R7743P06
		SFP-GE-SX-MM850-A	R7743P06
		SFP-GE-SX-MM850-D	R7743P06
		SFP-GE-T	R7743P06
		SFP-GE-T-D	R7743P06
LSXM3QGS36SF1	1~36	LSWM1QSTK0	R8053P09
		LSWM1QSTK1	R8053P09
		LSWM1QSTK2	R8053P09
		LSWM1QSTK3	R8053P09
		LSWM1QSTK4	R8053P09

单板名称	端口	支持的光模块	版本适配及说明
		LSWM1QSTK5	R8053P09
		QSFP-40G-BIDI-SR-MM850	R8053P09
		QSFP-40G-BIDI-WDM850	R8053P09
		QSFP-40G-CSR4-MM850	R8053P09
		QSFP-40G-D-AOC-10M	R8053P09
		QSFP-40G-D-AOC-20M	R8053P09
		QSFP-40G-D-AOC-7M	R8053P09
		QSFP-40G-ER4-WDM1300	R8053P09
		QSFP-40G-LR4L-WDM1300	R8053P09
		QSFP-40G-LR4-PSM1310	R8053P09
		QSFP-40G-LR4-WDM1300	R8053P09
		QSFP-40G-LX4-WDM1300	R8053P09
		QSFP-40G-SR4-MM850	R8053P09
		LSXM3QGS36SF2	1~36
LSWM1QSTK1	E8051P02		
LSWM1QSTK2	E8051P02		
LSWM1QSTK3	E8051P02		
LSWM1QSTK4	E8051P02		
LSWM1QSTK5	E8051P02		
QSFP-40G-BIDI-SR-MM850	E8051P02		
QSFP-40G-BIDI-WDM850	E8051P02		
QSFP-40G-CSR4-MM850	E8051P02		
QSFP-40G-D-AOC-10M	E8051P02		
QSFP-40G-D-AOC-20M	E8051P02		
QSFP-40G-D-AOC-7M	E8051P02		
QSFP-40G-ER4-WDM1300	E8051P02		
QSFP-40G-LR4L-WDM1300	E8051P02		
QSFP-40G-LR4-PSM1310	E8051P02		
QSFP-40G-LR4-WDM1300	E8051P02		
QSFP-40G-LX4-WDM1300	R7753P07		

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-SR4-MM850	E8051P02
LSXM3SUP04S2	ALL	SFP-GE-LH100-SM1550	E8045P10
		SFP-GE-LH40-SM1310	E8045P10
		SFP-GE-LH40-SM1310-D	E8045P10
		SFP-GE-LH40-SM1550	E8045P10
		SFP-GE-LH80-SM1550	E8045P10
		SFP-GE-LH80-SM1550-D	E8045P10
		SFP-GE-LX-SM1310-A	E8045P10
		SFP-GE-LX-SM1310-BIDI	E8045P10
		SFP-GE-LX-SM1310-D	E8045P10
		SFP-GE-LX-SM1310-S	E8045P10
		SFP-GE-LX-SM1490-BIDI	E8045P10
		SFP-GE-SX-MM850-A	E8045P10
		SFP-GE-SX-MM850-D	E8045P10
		SFP-GE-SX-MM850-S	E8045P10
LSXM3SUPS2	ALL	SFP-GE-LH100-SM1550	R7743P06
		SFP-GE-LH40-SM1310	R7743P06
		SFP-GE-LH40-SM1310-D	R7743P06
		SFP-GE-LH40-SM1550	R7743P06
		SFP-GE-LH80-SM1550	R7743P06
		SFP-GE-LH80-SM1550-D	R7743P06
		SFP-GE-LX-SM1310-A	R7743P06
		SFP-GE-LX-SM1310-BIDI	R7743P06
		SFP-GE-LX-SM1310-D	R7743P06
		SFP-GE-LX-SM1490-BIDI	R7743P06
		SFP-GE-SX-MM850-A	R7743P06
		SFP-GE-SX-MM850-D	R7743P06
LSXM3TGS48SF1	1~48	CAB-0.5M-SFP+	R8053P09
		CAB-1M-SFP+	R8053P09
		CAB-3M-SFP+	R8053P09
		LSTM1STK	R8053P09
		LSWM1STK	R8053P09

单板名称	端口	支持的光模块	版本适配及说明
		LSWM2STK	R8053P09
		LSWM3STK	R8053P09
		SFP-10G-D-CAB-3M-Z	R8053P09
		SFP-2.5G-LX10-SM1310-D R-I	R8055P01
		SFP-GE-LH100-SM1550	R8053P09
		SFP-GE-LH40-SM1310	R8053P09
		SFP-GE-LH40-SM1310-BID I	R8053P09
		SFP-GE-LH40-SM1310-D	R8053P09
		SFP-GE-LH40-SM1550	R8053P09
		SFP-GE-LH40-SM1550-BID I	R8053P09
		SFP-GE-LH70-SM1490-BID I	R8053P09
		SFP-GE-LH70-SM1550-BID I	R8053P09
		SFP-GE-LH80-SM1550	R8053P09
		SFP-GE-LH80-SM1550-D	R8053P09
		SFP-GE-LX-SM1310-A	R8053P09
		SFP-GE-LX-SM1310-BIDI	R8053P09
		SFP-GE-LX-SM1310-D	R8053P09
		SFP-GE-LX-SM1310-S	R8053P09
		SFP-GE-LX-SM1490-BIDI	R8053P09
		SFP-GE-SX-MM850-A	R8053P09
		SFP-GE-SX-MM850-D	R8053P09
		SFP-GE-SX-MM850-S	R8053P09
		SFP-GE-T	R8053P09
		SFP-GE-T-D	R8053P09
		SFP-XG-LH40-SM1270-BID I	R8053P09
		SFP-XG-LH40-SM1330-BID I	R8053P09
		SFP-XG-LH40-SM1550	R8053P09
		SFP-XG-LH40-SM1550-D	R8053P09

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LH80-SM1490-BIDI	R8053P09
		SFP-XG-LH80-SM1550	R8053P09
		SFP-XG-LH80-SM1550-BIDI	R8053P09
		SFP-XG-LH80-SM1550-D	R8053P09
		SFP-XG-LX-SM1270-BIDI	R8053P09
		SFP-XG-LX-SM1310	R8053P09
		SFP-XG-LX-SM1310-D	R8053P09
		SFP-XG-LX-SM1310-E	R8053P09
		SFP-XG-LX-SM1310-S	R8053P09
		SFP-XG-LX-SM1330-BIDI	R8053P09
		SFP-XG-SX-MM850-A	R8053P09
		SFP-XG-SX-MM850-D	R8053P09
		SFP-XG-SX-MM850-E	R8053P09
		SFP-XG-SX-MM850-S	R8053P09
		LSXM3TGS48SF2	1~48
CAB-1M-SFP+	E8045P10		
CAB-3M-SFP+	E8045P10		
LSTM1STK	E8045P10		
LSWM1STK	E8045P10		
LSWM2STK	E8045P10		
LSWM3STK	E8045P10		
SFP-10G-D-CAB-3M-Z	E8045P10		
SFP-2.5G-LX10-SM1310-D R-I	R8055P01		
SFP-GE-LH100-SM1550	E8045P10		
SFP-GE-LH40-SM1310	E8045P10		
SFP-GE-LH40-SM1310-BIDI	E8045P10		
SFP-GE-LH40-SM1310-D	E8045P10		
SFP-GE-LH40-SM1550	E8045P10		
SFP-GE-LH40-SM1550-BIDI	E8045P10		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LH70-SM1490-BIDI	E8045P10
		SFP-GE-LH70-SM1550-BIDI	E8045P10
		SFP-GE-LH80-SM1550	E8045P10
		SFP-GE-LH80-SM1550-D	E8045P10
		SFP-GE-LX-SM1310-A	E8045P10
		SFP-GE-LX-SM1310-BIDI	E8045P10
		SFP-GE-LX-SM1310-D	E8045P10
		SFP-GE-LX-SM1310-S	E8045P10
		SFP-GE-LX-SM1490-BIDI	E8045P10
		SFP-GE-SX-MM850-A	E8045P10
		SFP-GE-SX-MM850-D	E8045P10
		SFP-GE-SX-MM850-S	E8045P10
		SFP-GE-T	E8045P10
		SFP-GE-T-D	E8045P10
		SFP-XG-LH40-SM1270-BIDI	E8045P10
		SFP-XG-LH40-SM1330-BIDI	E7745P10
		SFP-XG-LH40-SM1550	E8045P10
		SFP-XG-LH40-SM1550-D	E8045P10
		SFP-XG-LH80-SM1490-BIDI	E7745P10
		SFP-XG-LH80-SM1550	E8045P10
		SFP-XG-LH80-SM1550-BIDI	E7745P10
		SFP-XG-LH80-SM1550-D	E8045P10
		SFP-XG-LX-SM1270-BIDI	E8045P10
		SFP-XG-LX-SM1310	E8045P10
		SFP-XG-LX-SM1310-D	E8045P10
		SFP-XG-LX-SM1310-E	E8045P10
		SFP-XG-LX-SM1310-S	E8045P10
		SFP-XG-LX-SM1330-BIDI	E8045P10
		SFP-XG-SX-MM850-A	E8045P10

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-SX-MM850-D	E8045P10
		SFP-XG-SX-MM850-E	E8045P10
		SFP-XG-SX-MM850-S	E8045P10
LSXM3TGT48CQSF2	49~50	LSWM1QSTK0	E8054P03
		LSWM1QSTK1	E8054P03
		LSWM1QSTK2	E8054P03
		LSWM1QSTK3	E8054P03
		LSWM1QSTK4	E8054P03
		LSWM1QSTK5	E8054P03
		QSFP-100G-4SFP-25G-CAB-1M	E8054P03
		QSFP-100G-4SFP-25G-CAB-3M	E8054P03
		QSFP-100G-4SFP-25G-CAB-5M	E8054P03
		QSFP-100G-CWDM4-SM1300-A	E8054P03
		QSFP-100G-D-AOC-10M	E8054P03
		QSFP-100G-D-AOC-20M	E8054P03
		QSFP-100G-D-AOC-7M	E8054P03
		QSFP-100G-D-CAB-1M	E8054P03
		QSFP-100G-D-CAB-3M	E8054P03
		QSFP-100G-D-CAB-5M	E8054P03
		QSFP-100G-ER4L-WDM1300	E8054P03
		QSFP-100G-eSR4-MM850	E8054P03
		QSFP-100G-LR4L-WDM1300	E8054P03
		QSFP-100G-LR4-WDM1300	E8054P03
		QSFP-100G-PSM4-SM1310	E8054P03
		QSFP-100G-SR4-MM850	E8054P03
		QSFP-100G-SR4-MM850-A	E8054P03
QSFP-100G-SR4-MM850-H	E8054P03		
QSFP-100G-SWDM4-MM8	E8054P03		



单板名称	端口	支持的光模块	版本适配及说明
		50	
		QSFP-40G-BIDI-SR-MM850	E8054P03
		QSFP-40G-BIDI-WDM850	E8054P03
		QSFP-40G-CSR4-MM850	E8054P03
		QSFP-40G-D-AOC-10M	E8054P03
		QSFP-40G-D-AOC-20M	E8054P03
		QSFP-40G-D-AOC-7M	E8054P03
		QSFP-40G-ER4-WDM1300	E8054P03
		QSFP-40G-LR4L-WDM1300	E8054P03
		QSFP-40G-LR4-PSM1310	E8054P03
		QSFP-40G-LR4-PSM1310-A	E8054P03
		QSFP-40G-LR4-WDM1300	E8054P03
		QSFP-40G-LX4-WDM1300	R8054P10
		QSFP-40G-SR4-MM850	E8054P03
		LSXM3YGS48SF2	1~48
CAB-1M-SFP+	E8045P10		
CAB-3M-SFP+	E8045P10		
LSTM1STK	E8045P10		
LSWM1STK	E8045P10		
LSWM2STK	E8045P10		
LSWM3STK	E8045P10		
SFP-10G-D-CAB-3M-Z	E8045P10		
SFP-25G-D-AOC-10M	E8045P10		
SFP-25G-D-AOC-20M	E8045P10		
SFP-25G-D-AOC-3M	E8045P10		
SFP-25G-D-AOC-5M	E8045P10		
SFP-25G-D-AOC-7M	E8045P10		
SFP-25G-D-CAB-1M	E8045P10		
SFP-25G-D-CAB-3M	E8045P10		
SFP-25G-D-CAB-5M	E8045P10		
SFP-25G-LR-SM1310	E8045P10		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-25G-SR-MM850	E8045P10
		SFP-25G-SR-MM850-H	E805303
		SFP-GE-LH100-SM1550	E8045P10
		SFP-GE-LH40-SM1310	E8045P10
		SFP-GE-LH40-SM1310-BIDI	E8045P10
		SFP-GE-LH40-SM1310-D	E8045P10
		SFP-GE-LH40-SM1550	E8045P10
		SFP-GE-LH40-SM1550-BIDI	E8045P10
		SFP-GE-LH70-SM1490-BIDI	E8045P10
		SFP-GE-LH70-SM1550-BIDI	E8045P10
		SFP-GE-LH80-SM1550	E8045P10
		SFP-GE-LH80-SM1550-D	E8045P10
		SFP-GE-LX-SM1310-A	E8045P10
		SFP-GE-LX-SM1310-BIDI	E8045P10
		SFP-GE-LX-SM1310-D	E8045P10
		SFP-GE-LX-SM1310-S	E8045P10
		SFP-GE-LX-SM1490-BIDI	E8045P10
		SFP-GE-SX-MM850-A	E8045P10
		SFP-GE-SX-MM850-D	E8045P10
		SFP-GE-SX-MM850-S	E8045P10
		SFP-GE-T	E8045P10
		SFP-GE-T-D	E8045P10
		SFP-XG-LH40-SM1270-BIDI	E8045P10
		SFP-XG-LH40-SM1330-BIDI	E8045P10
		SFP-XG-LH40-SM1550	E8045P10
		SFP-XG-LH40-SM1550-D	E8045P10
		SFP-XG-LH80-SM1490-BIDI	E8045P10
		SFP-XG-LH80-SM1550	E8045P10

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LH80-SM1550-BIDI	E8045P10
		SFP-XG-LH80-SM1550-D	E8045P10
		SFP-XG-LX-SM1270-BIDI	E8045P10
		SFP-XG-LX-SM1310	E8045P10
		SFP-XG-LX-SM1310-D	E8045P10
		SFP-XG-LX-SM1310-E	E8045P10
		SFP-XG-LX-SM1310-S	E8045P10
		SFP-XG-LX-SM1330-BIDI	E8045P10
		SFP-XG-SX-MM850-A	E8045P10
		SFP-XG-SX-MM850-D	E8045P10
		SFP-XG-SX-MM850-E	E8045P10
		SFP-XG-SX-MM850-S	E8045P10
		LSXM4CGQ36SF2	1~36
LSWM1QSTK1	E8054P01		
LSWM1QSTK2	E8054P01		
LSWM1QSTK3	E8054P01		
LSWM1QSTK4	E8054P01		
LSWM1QSTK5	E8054P01		
QSFP-100G-4SFP-25G-CAB-1M	E8054P01		
QSFP-100G-4SFP-25G-CAB-1M-Z	E8054P01		
QSFP-100G-4SFP-25G-CAB-3M	E8054P01		
QSFP-100G-4SFP-25G-CAB-3M-Z	E8054P01		
QSFP-100G-4SFP-25G-CAB-5M	E8054P01		
QSFP-100G-4SFP-25G-CAB-5M-Z	E8054P01		
QSFP-100G-BIDI-MM850	R8055P01		
QSFP-100G-CWDM4-SM1300-A	E8054P01		
QSFP-100G-D-AOC-10M	E8054P01		
QSFP-100G-D-AOC-20M	E8054P01		

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-D-AOC-7M	E8054P01
		QSFP-100G-D-CAB-1M	E8054P01
		QSFP-100G-D-CAB-1M-Z	E8054P01
		QSFP-100G-D-CAB-3M	E8054P01
		QSFP-100G-D-CAB-3M-Z	E8054P01
		QSFP-100G-D-CAB-5M	E8054P01
		QSFP-100G-D-CAB-5M-Z	E8054P01
		QSFP-100G-ER4L-WDM1300	E8054P01
		QSFP-100G-ER4L-WDM1300-Z	E8054P01
		QSFP-100G-eSR4-MM850	E8054P01
		QSFP-100G-LR4L-WDM1300	E8054P01
		QSFP-100G-LR4L-WDM1300-Z	E8054P01
		QSFP-100G-LR4-WDM1300	E8054P01
		QSFP-100G-LR4-WDM1300-A	E8054P01
		QSFP-100G-LR4-WDM1300-Z	E8054P01
		QSFP-100G-PSM4-SM1310	E8054P01
		QSFP-100G-SR4-MM850	E8054P01
		QSFP-100G-SR4-MM850-A	E8054P01
		QSFP-100G-SR4-MM850-Z	E8054P01
		QSFP-100G-SWDM4-MM850	E8054P01
		QSFP-100G-SWDM4-MM850-Z	E8054P01
		QSFP-40G-BIDI-SR-MM850	E8054P01
		QSFP-40G-BIDI-SR-MM850-Z	E8054P01
		QSFP-40G-BIDI-WDM850	E8054P01
		QSFP-40G-CSR4-MM850	E8054P01

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-CSR4-MM850-Z	E8054P01
		QSFP-40G-D-AOC-10M	E8054P01
		QSFP-40G-D-AOC-20M	E8054P01
		QSFP-40G-D-AOC-7M	E8054P01
		QSFP-40G-D-CAB-1M-Z	E8054P01
		QSFP-40G-D-CAB-3M-Z	E8054P01
		QSFP-40G-D-CAB-5M-Z	E8054P01
		QSFP-40G-ER4-WDM1300	E8054P01
		QSFP-40G-ER4-WDM1300-Z	E8054P01
		QSFP-40G-LR4L-WDM1300	E8054P01
		QSFP-40G-LR4L-WDM1300-Z	E8054P01
		QSFP-40G-LR4-PSM1310	E8054P01
		QSFP-40G-LR4-WDM1300	E8054P01
		QSFP-40G-LR4-WDM1300-Z	E8054P01
		QSFP-40G-LX4-WDM1300	R8054P10
		QSFP-40G-SR4-MM850	E8054P01
		QSFP-40G-SR4-MM850-Z	E8054P01