

知 F5030防火墙定期保存配置的方法

其他 韦家宁 2020-04-07 发表

组网及说明

本案例使用F5030防火墙每天0:00定时保存设备配置。

F5030版本信息：

H3C Comware Software, Version 7.1.064, Release 9606P1801

Copyright (c) 2004-2018 New H3C Technologies Co., Ltd. All rights reserved.

H3C SecPath F5030 uptime is 84 weeks, 6 days, 5 hours, 21 minutes

Boot image: sda0:/F5080FW-CMW710-BOOT-R9606P1801.bin

Boot image version: 7.1.064, Release 9606P1801

Compiled Jun 20 2018 16:00:00

System image: sda0:/F5080FW-CMW710-SYSTEM-R9606P1801.bin

System image version: 7.1.064, Release 9606P1801

Compiled Jun 20 2018 16:00:00

SLOT 1

CPU type: Multi-core CPU

DDR3 SDRAM Memory: 16368M bytes

SD0: 3728M bytes

NSQ1MPBHA PCB Version: Ver.B

NSQ1MPBBHB PCB Version: Ver.A

NSQ1MPHDBHA PCB Version: Ver.A

NSQ1MPGC4BHA PCB Version: Ver.A

NSQ1MPLEDBHA PCB Version: Ver.A

CPLD_A Version: 2.0

CPLD_B Version: 2.0

Release Version:SecPath F5030-9606P1801

Basic BootWare Version:1.05

Extend BootWare Version:1.05

[SUBCARD 0] NSQ1MPBHA(Hardware)Ver.B, (Driver)1.0, (Cpld)2.0

[SUBCARD 2] NSQM1TG8A(Hardware)Ver.A, (Driver)1.0, (Cpld)1.0

[SUBCARD 4] NSQM1GT8A(Hardware)Ver.B, (Driver)1.0, (Cpld)1.0

配置步骤

1、配置调度工作

[H3C]scheduler job save //创建调度工作

[H3C-job-save]command 1 save //配置调度工作的第一条命令为save

[H3C-job-save]command 2 y //配置调度工作的第二条命令为y，因为在执行save命令时，设备会确认是否要保存

[H3C-job-save]command 3 y //配置调度工作的第三条命令为y，设备会确认是否写入当前启动配置文件中

[H3C-job-save]quit

2、配置调度策略

[H3C]scheduler schedule save //创建调度策略

[H3C-schedule-save]job save //调用调度工作

[H3C-schedule-save]time repeating at 0:00 //指定调度策略执行的时间是每天的0:00

[H3C-schedule-save]quit

注意事项：

1、完成scheduler配置后记得使用save命令保存配置。

2、F5030的系统时间最好和现实时间一致，如果不一致，会导致设备保存配置的时间与现实的时间出现偏差。

配置关键点