🗯 S12508与思科3750对接NTP典型组网配置案例

NTP **韦家宁** 2020-06-06 发表

组网及说明

S12508与思科3750对接NTP典型组网配置,其中S12508为时钟源,思科3750为客户端 S12508版本信息如下:

H3C Comware Platform Software

Comware Software, Version 5.20, Release 1828P05

Copyright (c) 2004-2014 Hangzhou H3C Tech. Co., Ltd. All rights reserved.

H3C S12508 uptime is 58 weeks, 4 days, 15 hours, 32 minutes

Last reboot reason: User reboot

思科3750信息如下:

Cisco IOS Software, C3750 Software (C3750-IPSERVICESK9-M), Version 12.2(52)SE, RELEASE S OFTWARE (fc3)

Copyright (c) 1986-2009 by Cisco Systems, Inc.

Compiled Fri 25-Sep-09 08:32 by sasyamal

Image text-base: 0x01000000, data-base: 0x02E00000

ROM: Bootstrap program is C3750 boot loader

BOOTLDR: C3750 Boot Loader (C3750-HBOOT-M) Version 12.2(44)SE5, RELEASE SOFTWARE (f c1)

JCW_C3750_A uptime is 1 year, 18 weeks, 1 day, 9 hours, 34 minutes

System returned to ROM by address error at PC 0x1765528, address 0x0

System restarted at 05:21:37 GX Thu Jan 24 2019

System image file is "flash:/c3750-ipservicesk9-mz.122-52.SE.bin"

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute or use encryption. Importers, exporters, distributors and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

A summary of U.S. laws governing Cisco cryptographic products may be found at: http://www.cisco.com/wwl/export/crypto/tool/stqrg.html

If you require further assistance please contact us by sending email to export@cisco.com.

cisco WS-C3750G-48TS (PowerPC405) processor (revision H0) with 131072K bytes of memory.

Processor board ID FOC1446Y0A6

Last reset from address error

7 Virtual Ethernet interfaces

52 Gigabit Ethernet interfaces

The password-recovery mechanism is enabled.

512K bytes of flash-simulated non-volatile configuration memory.

Base ethernet MAC Address : F0:25:72:81:E7:80 Motherboard assembly number : 73-10218-10 Power supply part number : 341-0107-01 Motherboard serial number : FOC14434ZZ4 Power supply serial number : AZS143207C1

Model revision number Motherboard revision number : A0

Model number : WS-C3750G-48TS-E System serial number : FOC1446Y0A6

Top Assembly Part Number : 800-27483-05

Top Assembly Revision Number : D0

Version ID : V07

CLEI Code Number : CMMAN00ARA Hardware Board Revision Number : 0x09

Switch Ports Model SW Version SW Image

* 1 52 WS-C3750G-48TS 12.2(52)SE C3750-IPSERVICESK9-M

Configuration register is 0xF

配置步骤

S12508 NTP时钟源配置信息如下:

clock protocol none ntp-service enable

ntp-service refclock-master 2

interface Vlan-interface4

ip address 10.190.4.254 255.255.255.0

vrrp vrid 4 virtual-ip 10.190.4.1

vrrp vrid 4 priority 105

packet-filter 3002 inbound

packet-filter 3002 outbound

思科3750 NTP配置如下:

ntp server 10.190.4.1 source Loopback0

S12508查看NTP显示信息:

dis ntp sessions

source reference stra reach poll now offset delay disper

[25]10.190.8.252 LOCL 1 255 64 51 -28825 0.9002 18.218 [12345]LOCAL(0) LOCL 1 255 64 42 0.0000 0.0000 0.9155

 $Notes: 1\ source(master),\ 2\ source(peer),\ 3\ selected,\ 4\ candidate,\ 5\ configured.$

Total sessions: 2

dis ntp status

Clock status: synchronized

Clock stratum: 2 System peer: LOCAL(0) Local mode: client

Reference clock ID: 127.127.1.0

Leap indicator: 00 Clock jitter: 0.000000 s Stability: 0.000 pps Clock precision: 2^-21 Root delay: 0.00000 ms Root dispersion: 10.98633 ms

Reference time: e27ced67.56daf74f Sat, May 30 2020 14:34:15.339

System poll interval: 64 s

思科3750查看NTP显示信息:

sh ntp status

Clock is synchronized, stratum 3, reference is 10.190.4.1

nominal freq is 119.2092 Hz, actual freq is 119.2110 Hz, precision is $2^{**}18$

reference time is E27CEE35.8C7EDE85 (14:37:41.548 GX Sat May 30 2020)

clock offset is 0.5777 msec, root delay is 1.36 msec

root dispersion is 12.39 msec, peer dispersion is 0.70 msec

address ref clock st when poll reach delay offset disp

*~10.190.4.1 127.127.1.0 2 544 1024 377 1.4 0.58 0.7

 * master (synced), # master (unsynced), + selected, - candidate, ~ configured

配置关键占

- 1、 确保时钟源和时钟客户端路由可达。
- 2、 时钟源及时钟客户端都需要开启NTP功能。
- 3、 时钟客户端指定时钟源为NTP服务器。
- 4、 时钟源所在的设备配置为时钟源。