

display version to check the version of the device.
 [MSR810]dis version
 H3C Comware Software, Version 7.1.064, Release 0707P24
 Copyright (c) 2004-2020 New H3C Technologies Co., Ltd. All rights reserved.
 H3C MSR810 uptime is 0 weeks, 0 days, 0 hours, 4 minutes

4. Restart the device, and long press Ctrl+B when restarting the device to enter the bootrom.

reboot

Start to check configuration with next startup configuration file, please wait......DONE! This command will reboot the device. Continue? [Y/N]:Y Now rebooting, please wait... %Jan 1 00:09:47:099 2011 MSR810 DEV/5/SYSTEM_REBOOT: System is rebooting now. @ System is starting... Press Ctrl+D to access BASIC-BOOTWARE MENU Booting Normal Extended BootWare

* H3C MSR810 BootWare, Version 1.61 *

Copyright (c) 2004-2019 New H3C Technologies Co., Ltd.

Compiled Date : May 5 2019 CPU ID : 0xa CPU L1 Cache : 32KB CPU L2 Cache : 256KB Memory Type : DDR3 SDRAM Memory Size : 1024MB Flash Size : 256MB PCB Version : 2.0

BootWare Validating... Press Ctrl+B to access EXTENDED-BOOTWARE MENU...

Password recovery capability is enabled. Note: The current operating device is flash Enter < Storage Device Operation > to select device.

	===
<1> Boot System <2> Enter Serial SubMenu <3> Enter Ethernet SubMenu <4> File Control <5> Restore to Factory Default Configuration <6> Skip Current System Configuration <7> BootWare Operation Menu <8> Skip Authentication for Console Login <9> Storage Device Operation <0> Reboot	
Ctrl+Z: Access EXTENDED ASSISTANT MENU Ctrl+C: Display Copyright Ctrl+F: Format File System Enter your choice(0-9): 3	
INote:the operating device is flash <1> Download Image Program To SDRAM And Run <2> Update Main Image File <3> Update Backup Image File <4> Download Files(*.*) <5> Modify Ethernet Parameter <0> Exit To Main Menu	I
Enter your choice(0-5): 5	
INote: "." = Clear field. "-" = Go to previous field. Ctrl+D = Quit.	
Protocol (FTP or TFTP) :tftp Load File Name :MSR810-CMW710-R0809P25.ipe Target File Name :MSR810-CMW710-R0809P25.ipe Server IP Address :1.1.1.2 Local IP Address :1.1.1.1 Subnet Mask :255.255.255.0 Gateway IP Address :1.1.1.2	: :

Note:the operating device is flash||<1> Download Image Program To SDRAM And Run||<2> Update Main Image File||<3> Update Backup Image File||<4> Download Files(*.*)|

- |<5> Modify Ethernet Parameter
- |<0> Exit To Main Menu

•			

Enter	vour	choice	(0-5):	2
Lincor	your	0110100	(0,0).	_

Loading.....

.....Done.

79714304 bytes downloaded!

Image file msr810-cmw710-boot-r0809p25.bin is self-decompressing... Saving file flash:/msr810-cmw710-boot-r0809p25.binDone. Image file msr810-cmw710-system-r0809p25.bin is self-decompressing...

Saving file flash:/msr810-cmw710-system-r0809p25.bin

 Note:the operating device is flash
 |

 |<1> Download Image Program To SDRAM And Run

 |<2> Update Main Image File
 |

 |<3> Update Backup Image File
 |

 |<4> Download Files(*.*)
 |

 |<5> Modify Ethernet Parameter
 |

|<0> Exit To Main Menu | |

Enter your choice(0-5): 0

<1> Boot System		
<2> Enter Serial SubMenu		
<3> Enter Ethernet SubMenu		
<4> File Control		
<5> Restore to Factory Default Configuration		
<6> Skip Current System Configuration		
<7> BootWare Operation Menu		
<8> Skip Authentication for Console Login		
<9> Storage Device Operation		
<pre> <0> Reboot</pre>	I	
Ctrl+Z: Access EXTENDED ASSISTANT MENU		

Ctrl+C: Display Copyright

Ctrl+F: Format File System

Enter your choice(0-9): 1

Loading the main image files...

Loading file flash:/msr810-cmw710-system-r0809p25.bin.....

.....Done.

Loading file flash:/msr810-cmw710-security-r0809p25.bin....Done.

Loading file flash:/msr810-cmw710-voice-r0809p25.bin...Done.

Loading file flash:/msr810-cmw710-data-r0809p25.bin.....Done.

Loading file flash:/msr810-cmw710-wifidog-r0809p25.bin...Done.

Loading file flash:/msr810-cmw710-wwd-r0809p25.bin...Done.

Loading file flash:/msr810-cmw710-boot-r0809p25.bin......Done.

Image file flash:/msr810-cmw710-boot-r0809p25.bin is self-decompressing.....

Done.

System image is starting...

Cryptographic algorithms tests passed.

Line con0 is available.

Press ENTER to get started.

%Jan 1 00:03:24:378 2011 MSR810 SHELL/5/SHELL_LOGIN: Console logged in from con0.

display version

H3C Comware Software, Version 7.1.064, Release 0809P25 Copyright (c) 2004-2020 New H3C Technologies Co., Ltd. All rights reserved. H3C MSR810 uptime is 0 weeks, 0 days, 0 hours, 3 minutes

Solutio

NULL

附件下载: boot.rar