

知 在原有端口镜像的基础上配置qos流镜像，删除端口镜像后无法恢复

镜像 zhiliao_aSlje5 2022-04-11 发表

组网及说明

```
H3C Comware Software, Version 7.1.070, Feature 2802P01
Copyright (c) 2004-2020 New H3C Technologies Co., Ltd. All rights reserved.
H3C S12508F-AF uptime is 66 weeks, 1 day, 8 hours, 28 minutes
Last reboot reason : User reboot

Boot image: flash:/S12500F-CMW710-BOOT-F2802P01.bin
Boot image version: 7.1.070P4216, Feature 2802P01
  Compiled Oct 19 2020 11:00:00
System image: flash:/S12500F-CMW710-SYSTEM-F2802P01.bin
System image version: 7.1.070, Feature 2802P01
  Compiled Oct 19 2020 11:00:00
Patch image(s) list:
  flash:/S12500F-CMW710-SYSTEM-F2802P01H13.bin, version: F2802P01H13
    Compiled Oct 19 2020 11:00:00
```

告警信息

mirroring setting fail

问题描述

删除端口镜像后只保留qos流镜像，仍然没有流量，然后想加回原有的端口镜像，发现添加后报错。

过程分析

已在F2802P01H07补丁中解决，现网设备虽然已经打了H13补丁，但是根据设备运行时间和进程启动时间看镜像组是在2020-12-18日设备启动时就配置了（当时触发该问题,镜像在备框2和3槽位是下失败的），后来打补丁并没有进行恢复。

解决方法

对于已有问题的环境，需要先把所有镜像目的口删除，如果未安装补丁，可以通过一个命令配置一个镜像目的口的方式恢复；如果已安装补丁，可以通过单条命令配置多个镜像目的口的方式恢复。

