

知 堆叠之后的MSR56系列路由器做本地端口镜像，目的端口不支持跨框

镜像

谢晖

2023-05-31 发表

问题描述

MSR路由做了IRF2堆叠之后，配置本地端口镜像，发现目的端口无法配置，报错提示如下：

```
[H3C]mirroring-group 1 monitor-port gi 1/2/6/3
```

The type of the monitor port in the mirroring group is not supported.

本地端口镜像配置正常，但是目的端口无法配置

```
[H3C]dis mirroring-group all
```

Mirroring group 1:

Type: Local

Status: Incomplete

Mirroring port:

GigabitEthernet1/2/6/5 Both

GigabitEthernet1/2/6/6 Both

GigabitEthernet1/2/6/7 Both

GigabitEthernet2/2/6/5 Both

GigabitEthernet2/2/6/6 Both

GigabitEthernet2/2/6/7 Both

解决方法

本地端口镜像不支持源端口和目的端口是处于不同框的情况。

举例说明：配置本地端口镜像后，只能将Slot1机框上的源端口镜像到Slot1机框上的目的端口，不能将Slot2机框上的源端口镜像到Slot1机框上的目的端口。

