

【MVS】F5配置HA报错“01070661:3: Attempt to enable both Failover.ForceActive and Failover.ForceStandby.”

设备管理 胡伟 2024-09-30 发表

问题描述

【MVS】F5配置HA报错“01070661:3: Attempt to enable both Failover.ForceActive and Failover.ForceStandby.”

解决方法

Known Issue

This is the result of a known issue. In BIG-IP version 10.1.0 and later, changes to the **Redundancy State Preference** setting on the High Availability > Redundancy screen may fail, and an error message similar to the following example will display in the Configuration utility:

01070661:3: Attempt to enable both Failover.ForceActive and Failover.ForceStandby.

This condition is only known to occur if the Active and Standby members of a high-availability pair previously had their redundancy state preferences changed from **None** to **Active** or **Standby**. Once the devices have had their settings set to prefer a specific role, an attempt to change the **Redundancy State Preference** from **Active** to **Standby** may result in the error condition and error message described previously.

F5 Product Development is tracking this issue as ID 252045 (formerly CR48012).

Note: This issue does not affect BIG-IP version 11.x and later.

Workaround

You can work around this issue by clearing and resetting the **Redundancy State Preference** setting.

To do so, perform one of the following two procedures:

Clearing and Resetting the Redundancy State Preference setting from the Configuration utility

1. Log in to the BIG-IP Configuration utility.
2. Click **System**.
3. Click **High Availability**.
4. Change the **Redundancy State Preference** setting on both devices to **None**.
5. Commit the changes by clicking **Update**.
6. Change each device to the desired **Redundancy State Preference** of **Active** or **Standby**.
7. Commit the changes by clicking **Update**.