

知 WA4320-ACN如何从V5胖模式转换为V7的瘦模式

软件升级 徐猛 2018-01-27 发表

问: WA4320-ACN如何从V5胖模式转换为V7的瘦模式

答: AP重启的过程中按下Ctrl+B进入BootMenu扩展段

```
=====<EXTEND-BOOTWARE MENU>=====
===
|<1> Boot System                |
|<2> Enter Serial SubMenu      |
|<3> Enter Ethernet SubMenu    |
|<4> File Control              |
|<5> Restore to Factory Default Configuration |
|<6> Skip Current System Configuration |
|<7> BootWare Operation Menu   |
|<8> Clear Super Password      |
|<9> Storage Device Operation  |
|<0> Reboot                    |
=====

Ctrl+C: Display Copyright
Ctrl+Y: Change AP Mode
Ctrl+F: Format File System
Enter your choice(0-9): //此处按下Ctrl+Y
Please select the new mode
Current mode is Fat
=====
|NO. Mode                |
|1 Fat Mode              |
|2 Fit Mode              |
|0 Exit                  |
=====

Enter your choice(0-2):2
Warning:Change from fat mode to fit mode formats the storage meduim! Are you
sure to continue ? [Y/N]Y.....
.....
Formatted the storage medium successfully!
Changed to fit mode successfully!
//AP更改为瘦模式后,会对设备的flash进行格式化,格式化成功后,将该AP注册到适配的V7版本的A
C上即可完成AP系统版本由V5胖版本转换为V7瘦版本的过程。
```