

如何解决忘记6125Web页面默认密码的问题

6125Web页面默认密码:

admin/admin

如果不能登陆, 可以尝试用以下步骤进行修改

在开始—运行---cmd下telnet到oa的ip上, 用oa的Administrator和密码登陆后继续

C7000-Rank1-24U-33U-OA1> show interconnect list

Bay Interconnect Type Manufacturer Power Health UID Management

```
-----  
1 Ethernet HP On OK Off 1.1.32.73  
2 [Absent]  
3 [Absent]  
4 Ethernet HP On OK Off 1.1.32.76  
5 [Absent]  
6 [Absent]  
7 Ethernet HP On OK Off 1.1.32.79  
8 [Absent]
```

Totals: 3 interconnect modules installed, 3 powered on.

C7000-Rank1-24U-33U-OA1> connect interconnect 4 (连接到6125上, 回车后不需要6125的密码验证, 直接登陆到6125命令行下)

NOTICE: This pass-thru connection to the integrated I/O console is provided for convenience and does not supply additional access control. For security reasons, use the password features of the integrated switch.

Connecting to integrated switch 4 at 9600,N81...

Escape character is & # 39;<Ctrl>_& # 39; (Control + Shift + Underscore)

Press [Enter] to display the switch console:

<6125G/XG Blade Switch>

#Jun 3 19:24:49:342 2000 6125G/XG Blade Switch SHELL/4/LOGIN:

Trap 1.3.6.1.4.1.25506.2.2.1.1.3.0.1: login from Console

%Jun 3 19:24:49:467 2000 6125G/XG Blade Switch SHELL/5/SHELL_LOGIN: Console logged in from aux0.

<6125G/XG Blade Switch>

<6125G/XG Blade Switch>

开始修改

[Sysname] local-user admin

[Sysname-luser-admin] service-type web

[Sysname-luser-admin] authorization-attribute level 3

[Sysname-luser-admin] password simple admin