

组网及说明

1 配置需求或说明

1.1 适用产品系列

本案例适用于如S7006、S7503E、S7506E、S7606、S10510、S10508等S7000、S7500E、S10500系列，且软件版本是V7的交换机。

1.2 需要的工具环境及注意事项

恢复出厂配置模块提供将设备中的所有配置恢复到出厂时的缺省配置，删除当前的配置文件，并重新启动设备的功能。

2 组网图

无

配置步骤

3 配置步骤

3.1 命令恢复方式

3.1.1 删除配置文件，重启设备方式恢复

#查看设备当前已存在的配置文件

```
<H3C>dir
Directory of flash:
 0 -rw-   6244 Jan 08 2013 07:26:03  startup.cfg
 1 -rw-  136628 Jan 08 2013 07:26:03  startup.mdb
 2 -rw-   58704 Jan 03 2013 07:56:22  diag_H3C_20130103-005605.tar.gz
```

#删除配置文件

```
<H3C>delete /unreserved startup.cfg
The contents cannot be restored!!! Delete flash:/startup.cfg?[Y/N]:y
Deleting a file permanently will take a long time. Please wait...
.
%Delete file flash:/startup.cfg...Done.
```

#重启设备

```
<H3C>reboot
Start to check configuration with next startup configuration file, please wait.....DONE!
This command will reboot the device. Current configuration will be lost, save current configuration? [Y/N]:n
This command will reboot the device. Continue? [Y/N]:y
当设备重新完成，那么设备就在出厂设置的状态
```

3.1.2 清除保存的配置，重启设备方式恢复

#清除已保存的配置

```
<H3C>reset save
The saved configuration file will be erased. Are you sure? [Y/N]:Y
```

#重启设备

```
<H3C>reboot
Start to check configuration with next startup configuration file, please wait.....DONE!
This command will reboot the device. Current configuration will be lost, save current configuration? [Y/N]:n
This command will reboot the device. Continue? [Y/N]:y
```

配置关键点

