

无线设备的胖瘦切换实验



1. 胖切瘦

a) 命令行切换

<WAP621>ap-mode fit

Change working mode will reboot system, do you want to continue? [Y/N]y

Change working mode to FIT now? [Y/N]y.....

切换完成后设备重启，如果跟AC连接正确可以自动注册，版本也会自动更新。

%Mar 19 16:41:41:635 2009 WAP621 IFNET/3/LINK_UPDOWN: GigabitEthernet1/0/1 link status is DOWN.

System is starting...

Press Ctrl+D to access BASIC-BOOTWARE MENU

Booting Normal Extend BootWare....

The Extend BootWare is self-decompressing.....Done!

```

*****
*                                     *
*           H3C WAP621 BootWare, Version 3.03           *
*                                     *
*****
  
```

Copyright (c) 2004-2014 Hangzhou H3C Technologies Co., Ltd.

```

Compiled Date   : Sep 1 2014
CPU Type       : AR9344
CPU L1 Cache   : 32KB
CPU Clock Speed : 560MHz
Memory Type    : SDRAM
Memory Size    : 128MB
Memory Speed   : 480MHz
BootWare Size  : 512KB
Flash Size     : 16MB
PCB Version    : Ver.A
  
```

BootWare Validating...

Press Ctrl+B to enter extended boot menu...

Starting to get the main application file--flash:/wa2600a_fit.bin!

The main application file does not exist--flash:/wa2600a_fit.bin!

Starting to get the backup application file--flash:/backup.bin!

The backup application file does not exist--flash:/backup.bin!

Starting to get the secure application file--flash:/secure.bin!

The secure application file does not exist--flash:/secure.bin!

Booting App fails!

Trying to get the IP address from the DHCP server.....

DHCP server's IP address is 192.168.0.100

Client's assigned address is 192.168.0.3

DNS domain name got from DHCP server is

DNS server's IP address is 0.0.0.0

Default Gateway's IP address is 192.168.0.100

This client's subnet mask is 255.255.255.0

The length of option 43 is: 0

Change State : Idle to Broadcast Discovery
Change State : Broadcast Discovery to Join
Change State : Join to JoinAck
Change State : JoinCfm to Image Download.....

.....
[State : ImageLoad] Image download successful
[State : Idle] Reset request, rebooting the AP
Rebooting.....

System is starting...
Press Ctrl+D to access BASIC-BOOTWARE MENU
Booting Normal Extend BootWare...
The Extend BootWare is self-decompressing.....Done!

```
*****  
*                                     *  
*          H3C WAP621 BootWare, Version 3.03          *  
*                                     *  
*****
```

Copyright (c) 2004-2014 Hangzhou H3C Technologies Co., Ltd.

Compiled Date : Sep 1 2014
CPU Type : AR9344
CPU L1 Cache : 32KB
CPU Clock Speed : 560MHz
Memory Type : SDRAM
Memory Size : 128MB
Memory Speed : 480MHz
BootWare Size : 512KB
Flash Size : 16MB
PCB Version : Ver.A

BootWare Validating...
Press Ctrl+B to enter extended boot menu...
Starting to get the main application file--flash:/wa2600a_fit.bin!.....

.....
.....
The main application file is self-decompressing.....
.....
.....
.....
.....Done!

Extend BootWare Version is not equal,updating? [Y/N]
Updating Extend BootWare.....Done!
Basic BootWare Version is not equal,updating? [Y/N]
Updating Basic BootWare.....Done!
BootWare updated,System is rebooting now.
System is starting...
Press Ctrl+D to access BASIC-BOOTWARE MENU
Booting Normal Extend BootWare...
The Extend BootWare is self-decompressing.....Done!

```
*****  
*                                     *  
*          H3C WAP621 BootWare, Version 3.05          *  
*                                     *  
*****
```

Copyright (c) 2004-2014 Hangzhou H3C Technologies Co., Ltd.

Compiled Date : Nov 20 2014
CPU Type : AR9344
CPU L1 Cache : 32KB

CPU Clock Speed : 560MHz
Memory Type : SDRAM
Memory Size : 128MB
Memory Speed : 480MHz
BootWare Size : 512KB
Flash Size : 16MB
PCB Version : Ver.A

BootWare Validating...

Press Ctrl+B to enter extended boot menu...

Starting to get the main application file--flash:/wa2600a_fit.bin!.....

The main application file is self-decompressing.....

.....Done!

System application is starting...

Startup configuration file does not exist.

User interface con0 is available.

进入AC查看，AP已经注册成功

<H3C>dis wlan ap all

Total Number of APs configured : 1
Total Number of configured APs connected : 1
Total Number of auto APs connected : 0
Total Number of APs connected : 1
Maximum AP capacity : 32
Remaining AP capacity : 31

AP Profiles

State : I = Idle, J = Join, JA = JoinAck, IL = ImageLoad
C = Config, R = Run, KU = KeyUpdate, KC = KeyCfm
M = Master, B = Backup

AP Name	State Model	Serial-ID
3c8c-403c-88d0	R/M WAP621	219801A0Q59153Q00000

b) Web切换

页面向导: 高级设置——形态切换——切换

2. 命令行瘦切胖

命令行升级需在PC上搭建TFTPServer (推荐用户使用3CDaemon搭建TFTP服务器, 百度可下) 将软件版本下载到设备FLASH内, 然后通过命令行首先加载BOOTROM, 第二步再加载主机软件版本, 加载时敲得文件名一定要一致, 建议复制黏贴不要手打, 然后升级过程中避免断电重启操作。

下载到PC后需修改文件名, AP本地后对应的启动文件名均为WA2600a_fat.bin, 需要注意文件名称修改正确。

a) 设备有console口

1) 断开AC连接, 设备启动完毕后修改设备管理地址

<WAP621>sys

System View: return to User View with Ctrl+Z.

[WAP621]int vlan 1

[WAP621-Vlan-interface1]ip add 192.168.0.3 24

[WAP621-Vlan-interface1]qu

2) 搭建TFTP服务器

在计算机上的3CD软件上选择存放版本的路径, 点应用。

3) 上传版本

<WAP621>tftp 192.168.0.1 get apwa26xx_v3.03.btw

.

File will be transferred in binary mode

Downloading file from remote TFTP server, please wait.....

TFTP: 408332 bytes received in 3 second(s)

File downloaded successfully.

<WAP621>tftp 192.168.0.1 get wa2600a_fat.bin

..

File will be transferred in binary mode
Downloading file from remote TFTP server, please wait...../

.....
TFTP: 9091072 bytes received in 63 second(s)
File downloaded successfully.

PS: 如果提示FLASH空间不足已放下新版本请将老版本删除, 删除后请勿重启, 否则设备已无系统, 只能通过bootrom升级。

<WAP621>delete /unreserved wa2600a_fit.bin
The contents cannot be restored!!! Delete flash:/wa2600a_fit.bin?[Y/N]:y
Deleting a file permanently will take a long time. Please wait...

.....
%Delete file flash:/wa2600a_fit.bin...Done.

//如果空间不够, 可以删除原有的软件版本释放存储空间

4) 加载版本

<WAP621>**bootrom update file apwa26xx_v3.03.btw**
This command will update bootrom file, Continue? [Y/N]:y
Now updating bootrom, please wait...
Updating basic bootrom!

Update basic bootrom success!
Updating extended bootrom!

Update extended bootrom success!
Update bootrom success!

<WAP621>**boot-loader file wa2600a_fat.bin**

Verifying boot file
This command will set the boot file. Continue? [Y/N]:y
System is starting...

Press Ctrl+D to access BASIC-BOOTWARE MENU

Booting Normal Extend BootWare....

The Extend BootWare is self-decompressing.....Done!

* * * * *
* H3C WAP621 BootWare, Version 3.03 *
* * * * *

Copyright (c) 2004-2014 Hangzhou H3C Technologies Co., Ltd.

Compiled Date : Sep 1 2014
CPU Type : AR9344
CPU L1 Cache : 32KB
CPU Clock Speed : 560MHz
Memory Type : SDRAM
Memory Size : 128MB
Memory Speed : 480MHz
BootWare Size : 512KB
Flash Size : 16MB
PCB Version : Ver.A

BootWare Validating...

Press Ctrl+B to enter extended boot menu...

Starting to get the main application file--flash:/wa2600a_fat.bin!.....

.....
.....

The main application file is self-decompressing.....

.....
.....
.....
.....
.....
.....
.....
.....
.....
.....

Done!

System application is starting...

Startup configuration file does not exist.

User interface con0 is available.

Press ENTER to get started.

b) 设备无console口

1) 查看AP name

[H3C]dis wlan ap all

Total Number of APs configured : 0

Total Number of configured APs connected : 0

Total Number of auto APs connected : 1

Total Number of APs connected : 1

Maximum AP capacity : 32

Remaining AP capacity : 31

AP Profiles

State : I = Idle, J = Join, JA = JoinAck, IL = ImageLoad

C = Config, R = Run, KU = KeyUpdate, KC = KeyCfm

M = Master, B = Backup

```
-----  
AP Name                State Model          Serial-ID  
-----  
3c8c-403c-88d0        R/M WAP621         219801A0Q59153Q00000
```

2) 进入AC的隐藏模式

[H3C]_h

Now you enter a hidden command view for developer's testing, some commands may affect operation by wrong use, please carefully use it with our engineer's direction.

3) 开启AP的telnet功能:

[H3C-hidecmd]wlan ap-execute 3c8c-403c-88d0 exec-control enable

[H3C-hidecmd]wlan ap-execute 3c8c-403c-88d0 telnet enable

[H3C-hidecmd]qui

4) Telnet进入AP导入版本

<H3C>telnet 192.168.0.3

Trying 192.168.0.3 ...

Press CTRL+K to abort

Connected to 192.168.0.3 ...

* Copyright (c) 2004-2015 Hangzhou H3C Tech. Co., Ltd. All rights reserved. *

* Without the owner's prior written consent, *

* no decompiling or reverse-engineering shall be allowed. *

<3c8c-403c-88d0>

之后导入和加载步骤同上

命令行升级需在PC上搭建TFTPServer (推荐用户使用3CDaemon搭建TFTP服务器, 百度可下) 将软件版本下载到设备FLASH内, 然后通过命令行首先加载BOOTROM, 第二步再加载主机软件版本, 加载时敲得文件名一定要一致, 建议复制黏贴不要手打, 然后升级过程中避免断电重启操作。

下载到PC后需修改文件名, AP本地后对应的启动文件名均为WA2600a_fat.bin, 需要注意文件名称修改正确。