

NE40/NE80/S8016 Console口密码恢复方法

NE40/NE80/S8016的Console口密码一般不建议配置，但是如果配置后不小心遗失，而且也不能通过其它设备Telnet上来修改Console密码，则只能删除配置文件再重启，然后通过删除原先备份的配置文件中Console口密码的相关配置后导入系统(如果是VR P3.10用vrpcfg.zip直接覆盖原配置文件，如果是VRP5.10或VRP5.30，可以设定启动文件为刚导入的配置文件)，重启后才能恢复。

其中删除配置文件的操作如下：

```
ZBB_TEST
Starting...
*****
*                               *
* Switching Routing Platform 80 Bootrom, Ver128 *
*                               *
*****

Copyright(C) 2001-2005 by HUAWEI TECHNOLOGIES CO.,LTD.
Creation date: Jul 25 2002, 21:50:11
CPU type      : MPC750
CPU L2 Cache  : 1024KB
CPU Clock Speed : 350MHz
BUS Clock Speed : 100MHz
Memory Size   : 512MB

Initialize HardDisk will take long time if needed.
Initialize HardDisk...ok!
Press Ctrl+B to enter Boot Menu... 4
//此时键入Ctrl+B，进入bootroom菜单
password:
  MAIN MENU
  1. Boot with default mode
  2. Boot from Flash
  3. Boot from HardDisk
  4. Enter serial submenu
  5. Enter ethernet submenu
  6. Modify Flash description area
  7. Modify bootrom password
  8. Reboot
Enter your choice(1-8):
//此时键入Ctrl+Z进入隐藏菜单
  HIDDEN MENU
  1. Enter to debugging environment
  2. Erase Flash
  3. Delete file from Flash
  4. Disable Config Password
  5. Fdisk HardDisk
  6. Format HardDisk
  7. Chkdsk HardDisk
  8. Return to main menu
Enter your choice(1-8): 3
//选择3，删除flash上的文件
BE CAREFUL!
This may cause your system fail to start!
Please input the file name you want to delete, e.g.: rps.bin vrpcfg.zip
//删除配置文件
delete it? Yes or No(Y/N)y
//确定
Deleting file...done
  HIDDEN MENU
  1. Enter to debugging environment
  2. Erase Flash
```

3. Delete file from Flash
4. Disable Config Password
5. Fdisk HardDisk
6. Format HardDisk
7. Chkdsk HardDisk
8. Return to main menu

Enter your choice(1-8): 8

//**返回到bootroom菜单**

MAIN MENU

1. Boot with default mode
2. Boot from Flash
3. Boot from HardDisk
4. Enter serial submenu
5. Enter ethernet submenu
6. Modify Flash description area
7. Modify bootrom password
8. Reboot

Enter your choice(1-8): 8

//**重新reboot**

Rebooting...