

WA1208E的WEP加密功能的配置

一、配置步骤

1、建立SSID

```
[H3C]ssid wa1208
```

```
New ssid!
```

2、配置SSID的加密算法为WEP

```
[H3C-ssid-wa1208e] encryption suite wep
```

3、配置WEP加密所用的密钥索引

```
[H3C-ssid-wa1208e] encryption wep-default-key-id 1
```

```
[H3C-ssid-wa1208e] quit
```

4、进入射频模块视图

```
[H3C] radio module 1
```

5、配置WEP加密所用的密钥索引对应的密码

```
[H3C-radio-module1] encryption wep 1 wep40 ascii aaaaa
```

6、将SSID绑定到接口

```
[H3C] interface Wireless-access 1/2
```

```
[H3C-Wireless-access1/2] bind ssid wa1208
```

```
bind the ssid sucessfully!
```

```
[H3C-Wireless-access1/2] access uplayer
```

二、配置关键点

密钥可以以十六进制数或字符串形式输入，密钥长度由采用WEP40协议还是WEP104协议决定。本例中的配置命令采用了WEP40协议，密钥为ASCII码形式的字符aaaaa

。有关密钥长度可以参考如下表格：

密钥长度	ASCII形式	十六进制数形式
40位	5个字符	10个字符
104位	13个字符	26个字符

注意：一旦配置了WEP加密，所有进出设备的报文将被进行加解密处理。