

知 VG2000/3000系列修改自带的MAC地址的方法

李丹【技术大咖】 2008-09-22 发表

在启动过程中（提示ctrl+b之前），按下ctrl+t，即可进入修改MAC地址菜单。完整的过程如下：

```
*****
*
*   H3C Voice Gateway BOOTROM, Version 1.12   *
*
*****

Copyright(c) 2004-2007 Hangzhou H3C Technologies Co., Ltd.
Creation date   : Apr 18 2007, 18:22:11.
Testing memory...OK!
64M  bytes SDRAM
8192k bytes Flash Memory
Hardware Version is MTR 4.0
CPLD   Version is CPLD 3.0
Bootrom Version is 1.12
  J: mac address set
  K: mac address get
  0: exit and reboot

Please Select Item To Test:
  Please input a legal command
Please Select Item To Test: K
  the mac address in bootrom is not exist, test fail
  the mac address in flash is not exist, test fail
Please Select Item To Test: J
  please input mac address(in HEX):00-e0-fc-00-00-05
  writting mac address, please wait...
  mac address write bootrom success
  mac address write flash success
Please Select Item To Test: K
  the mac address in bootrom is: 00-E0-FC-00-00-05
  the mac address in flash is: 00-E0-FC-00-00-05
Please Select Item To Test: 0
  You have chosen to quit the test.
  The system will reboot!
```