

知 在S5500-52C-EI使用LSPM2GP2P插卡注意事项

其他硬件相关 夏威 2019-11-24 发表

问题描述

在S5500-52C-EI使用LSPM2GP2P插卡需要注意什么?

解决方法

1) LSPM2GP2P插卡带有两个千兆光口，但是在命令行显示是两个万兆接口。这种情况是正常的。由于交换机同时支持千兆和万兆子卡，在内部硬件上和普通万兆卡一样，均连接在了万兆芯片，因此会导致千兆子卡显示为万兆接口，如果插入线缆不亮，可以通过speed 1000解决

2) 在设备上display device 显示状态是正常的，但是display device ma。提示：不支持。这种情况也是正常的。

因为2GE子卡不支持电子标签，故通过dis device manu无法获取信息；dis device manu是通过硬件获取电子标签信息的，display device是我们自己定义的，获取方式不一样；

```
=====
=====display device verbose=====
=====
%Jan 16 07:37:41:387 2016 HG-CORE-SW-2 OSPF/5/OSPF_NBR_CHG: OSPF 202 Neighbor 125.2
02.240.250(Vlan-interface4001) from Full to Down.
Slot 1
SubSNo PortNum PCBVer FPGAVer CPLDVer BootRomVer AddrLM Type State
0 52 REV.C NULL 002 721 IVL MAIN Normal
1 2 REV.B NULL NULL NULL IVL 2*GE Normal
2 2 REV.B NULL NULL NULL IVL 2*GE Normal

slot 1 info:
Up Time : 0 weeks, 0 days, 0 hours, 43 minutes
Brd Type : H3C S5500-52C-EI
Brd Status : Master
Sft Ver : Release 2221P15
Patch Ver : None
PCB Ver : REV.C
BootRom Ver : 721
CPLD Ver : 002
SubCard : 1
  Status : Normal
  Name : LSPM2GP2P
  PCB Ver : REV.B
  CPLD Ver : NULL
  PortNum : 2
SubCard : 2
  Status : Normal
  Name : LSPM2GP2P
  PCB Ver : REV.B
  CPLD Ver : NULL
  PortNum : 2=====
==
=====display device manuinfo slot 1=====
=====
Slot 1:
DEVICE_NAME : S5500-52C-EI
DEVICE_SERIAL_NUMBER : 210235A24WH157000027
MAC_ADDRESS : 741F-4A8C-3108
MANUFACTURING_DATE : 2015-07-23
VENDOR_NAME : H3C
Subslot 1:
The card does not support manufacture information.
Subslot 2:
The card does not support manufacture information.
```

