

# 知 BootRom菜单升级过程中可能会遇到此提示操作不支持

其他硬件相关 软件问题 夏威夷 2019-11-24 发表

## 问题描述

BootRom菜单升级过程中可能会遇到此提示操作不支持该怎么办?

## 解决方法

在V7交换机升级的过程中不知道大家是否遇到此种情况, 即提示情况如下:

```
EXTENDED BOOT MENU
```

1. Download image to flash
2. Select image to boot
3. Display all files in flash
4. Delete file from flash
5. Restore to factory default configuration
6. Enter BootRom upgrade menu
7. Skip current system configuration
8. Set switch startup mode
0. Reboot

```
Ctrl+Z: Access EXTENDED ASSISTANT MENU
```

```
Ctrl+F: Format file system
```

```
Ctrl+P: Change authentication for console login
```

```
Ctrl+R: Download image to SDRAM and run
```

```
Ctrl+Y: Change Work Mode
```

```
Ctrl+C: Display Copyright
```

```
Enter your choice(0-8): 1
```

1. Set TFTP protocol parameters
2. Set FTP protocol parameters
3. Set XMODEM protocol parameters
0. Return to boot menu

```
Enter your choice(0-3): 1
```

**This operation is not supported in PEX mode**

大家看到此处可能有懵了, 其实这是支持irf3堆叠设备新添加了Ctrl+Y: Change Work Mode, 更改工作模式选项, 出现上面情况可能是客户误操作了按了ctrl+Y或是客户的网络中配置了irf3, 其中此设备是做为PEX设备导致。解决的方式其实特别简单就在按一下ctrl+Y把模式更改回来就ok了。

测试情况如下:

```
EXTENDED BOOT MENU
```

1. Download image to flash
2. Select image to boot
3. Display all files in flash
4. Delete file from flash
5. Restore to factory default configuration
6. Enter BootRom upgrade menu
7. Skip current system configuration
8. Set switch startup mode
0. Reboot

```
Ctrl+Z: Access EXTENDED ASSISTANT MENU
```

```
Ctrl+F: Format file system
```

```
Ctrl+P: Change authentication for console login
```

```
Ctrl+R: Download image to SDRAM and run
```

```
Ctrl+Y: Change Work Mode
```

```
Ctrl+C: Display Copyright
```

```
Enter your choice(0-8): //按ctrl+Y就ok了
```

```
PEX mode is enabled. Are you sure you want to disable PEX mode? [Y/N]Y
```

```
Mode changed successfully
```

```
EXTENDED BOOT MENU
```

1. Download image to flash
2. Select image to boot
3. Display all files in flash
4. Delete file from flash
5. Restore to factory default configuration
6. Enter BootRom upgrade menu
7. Skip current system configuration
8. Set switch startup mode
0. Reboot

Ctrl+Z: Access EXTENDED ASSISTANT MENU

Ctrl+F: Format file system

Ctrl+P: Change authentication for console login

Ctrl+R: Download image to SDRAM and run

Ctrl+Y: Change Work Mode

Ctrl+C: Display Copyright

Enter your choice(0-8): 1

1. Set TFTP protocol parameters
2. Set FTP protocol parameters
3. Set XMODEM protocol parameters
0. Return to boot menu

Enter your choice(0-3): 1

Load File Name :S5130EI\_E-CMW710-R3115P05.ipe

:

Server IP Address :3.3.3.3

Local IP Address :3.3.3.10

Subnet Mask :0.0.0.0

Gateway IP Address :0.0.0.0

拓展一下目前V7交换机支持irf3工作在PEX设备的型号如下:

 HUAWEI

本系列交换机可以作为PEX设备，加入由以下产品作为父设备的IRF3:

- S10500
- S12500-S
- S7500E
- S7500E-X
- S7600
- S7600-X