

H3C CR16000-F 路由器

单板与光模块适配关系表

Copyright © 2019-2024 新华三技术有限公司及其许可者 版权所有，保留一切权利。

未经本公司书面许可，任何单位和个人不得擅自摘抄、复制本书内容的部分或全部，并不得以任何形式传播。

除新华三技术有限公司的商标外，本手册中出现的其它公司的商标、产品标识及商品名称，由各自权利人拥有。

由于产品版本升级或其他原因，本手册内容有可能变更。**H3C** 保留在没有任何通知或者提示的情况下对本手册的内容进行修改的权利。本手册仅作为使用指导，**H3C** 尽全力在本手册中提供准确的信息，但是 **H3C** 并不确保手册内容完全没有错误，本手册中的所有陈述、信息和建议也不构成任何明示或暗示的担保。

本系列产品支持多种光模块或线缆，不同接口支持的光模块或线缆类型不同，具体请参见下表。
更多光模块或线缆属性信息，请参见 [《H3C光模块手册》](#)。

单板名称	端口	支持的光模块	说明
CEPC-CP4RX	1-4	CFP2-100G-ER4-WDM1300	
		CFP2-100G-LR4-WDM1300	
		CFP2-100G-SR10-MM850	
CEPC-CP4RXA	1-4	CFP2-100G-ER4-WDM1300	
		CFP2-100G-LR4-WDM1300	
		CFP2-100G-SR10-MM850	
CEPC-CP4RX-L	1-4	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
		QSFP-40G-BIDI-SR-MM850	
		QSFP-40G-CSR4-MM850	
		QSFP-40G-ER4-WDM1300	
		QSFP-40G-LR4L-WDM1300	
		QSFP-40G-LR4-WDM1300	
		QSFP-40G-SR4-MM850	
CEPC-CQ8L	1-8	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	

单板名称	端口	支持的光模块	说明
CEPC-CQ8L1A	1-8	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
CEPC-CQ8L3A	1-8	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
CEPC-CQ8LA	1-8	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
CEPC-DQ2L1-G	1-2	QSFPDD-400G-FR4-WDM1300	
CEPC-XP24LX	1-24	SFP-XG-LH40-SM1550	

单板名称	端口	支持的光模块	说明
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
CEPC-XP48RX	1-48	SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
CEPC-XP4LX	1-4	SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
CSPC-GE16XP4L-E	1-16	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	

单板名称	端口	支持的光模块	说明
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
	1-4	SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
CSPC-GE24L-E	1-24	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	

单板名称	端口	支持的光模块	说明
		SFP-GE-FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
CSPC-GP24GE8XP2L-E	1-2	SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
	1-24	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE-FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
	1-8	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	

单板名称	端口	支持的光模块	说明
CSPC-GP24LA1		SFP-GE-T-D	
	1-16	SFP-FE-LH40-SM1310	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
	17-24	SFP-FE-LH40-SM1310	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
CSPC-GP24XP2LB	1-16	SFP-FE-LH40-SM1310	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
	17-24	SFP-FE-LH40-SM1310	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	

单板名称	端口	支持的光模块	说明
		SFP-FE-SX-MM1310-A	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
	33-34	XFP-LH40-SM1550-D	
		XFP-LH80-SM1550	
		XFP-LH80-SM1550-D	
		XFP-LX-SM1310	
		XFP-LX-SM1310-D	
		XFP-SX-MM850	
		XFP-SX-MM850-D	
CSPC-GP44XP4LCX	1-44	SFP-FE-LH40-SM1310	仅支持FE全双工
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
	45-48	SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
CSPC-GP48LB	1-48	SFP-FE-LH40-SM1310	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
CSPC-XLP6LCX	1-6	QSFP-40G-ER4-WDM1300	
		QSFP-40G-LR4-WDM1300	
		QSFP-40G-SR4-MM850	
CSPC-XP12LAX	1-12	SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
CSPC-XP12LCX	1-12	SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
CSPC-XP24LAX	1-24	SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	

单板名称	端口	支持的光模块	说明
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
CSPC-XP24LCX	1-24	SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
CSPC-XP2LA1	1-2	XFP-LH40-SM1550-D	
		XFP-LH80-SM1550	
		XFP-LH80-SM1550-D	
		XFP-LX-SM1310	
		XFP-LX-SM1310-D	
		XFP-SX-MM850	
		XFP-SX-MM850-D	
CSPC-XP4LB	1-4	XFP-LH40-SM1550-D	
		XFP-LH80-SM1550	
		XFP-LH80-SM1550-D	
		XFP-LX-SM1310	
		XFP-LX-SM1310-D	
		XFP-SX-MM850	
		XFP-SX-MM850-D	
CSPC-XP8LB	1-8	SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	

单板名称	端口	支持的光模块	说明
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
MIC-CLP2L	1-2	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
MIC-CLP4L	1-4	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
MIC-CP1L-V2	1	CFP2-100G-ER4-WDM1300	
		CFP2-100G-LR4-WDM1300	
		CFP2-100G-SR10-MM850	
MIC-CP2L	1-2	CFP2-100G-ER4-WDM1300	
		CFP2-100G-LR4-WDM1300	
		CFP2-100G-SR10-MM850	
MIC-CP2L-V2	1-2	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
		QSFP-40G-BIDI-SR-MM850	
		QSFP-40G-CSR4-MM850	
		QSFP-40G-ER4-WDM1300	
		QSFP-40G-LR4L-WDM1300	
		QSFP-40G-LR4-WDM1300	

单板名称	端口	支持的光模块	说明
MIC-CQ1L1	1	QSFP-40G-SR4-MM850	
		QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
		QSFP-40G-BIDI-SR-MM850	
		QSFP-40G-CSR4-MM850	
		QSFP-40G-ER4-WDM1300	
		QSFP-40G-LR4L-WDM1300	
		QSFP-40G-LR4-WDM1300	
		QSFP-40G-SR4-MM850	
MIC-CQ1L2	1	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
		QSFP-40G-BIDI-SR-MM850	
		QSFP-40G-CSR4-MM850	
		QSFP-40G-ER4-WDM1300	
		QSFP-40G-LR4L-WDM1300	
		QSFP-40G-LR4-WDM1300	

单板名称	端口	支持的光模块	说明
MIC-CQ1LF	1	QSFP-40G-SR4-MM850	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-SR4-MM850	
		QSFP-100G-ZR4-WDM1300	
		QSFP-40G-BIDI-SR-MM850	
		QSFP-40G-CSR4-MM850	
		QSFP-40G-ER4-WDM1300	
		QSFP-40G-LR4L-WDM1300	
		QSFP-40G-LR4-WDM1300	
		QSFP-40G-SR4-MM850	
		QSFP-50G-ER-SM1311	
		QSFP-50G-LR-SM1311	
MIC-CQ2L	1-2	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
		QSFP-40G-BIDI-SR-MM850	
		QSFP-40G-CSR4-MM850	
		QSFP-40G-ER4-WDM1300	
		QSFP-40G-LR4L-WDM1300	
		QSFP-40G-LR4-WDM1300	
		QSFP-40G-SR4-MM850	
MIC-GP10L1	1-10	SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
MIC-GP10LA	1-10	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1310-S	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	

单板名称	端口	支持的光模块	说明
		SFP-GE-T	
		SFP-GE-T-D	
MIC-GP10L-V2	1-10	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1310-S	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
MIC-GP20L	1-20	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1310-S	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
MIC-GP20L1	1-20	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	

单板名称	端口	支持的光模块	说明
MIC-GP4L	1-4	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1310-S	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
MIC-GP8L	1-8	SFP-FE-LH40-SM1310	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1310-S	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
MIC-PSP4L	1-4	SFP-2.5G-LX-SM1310	
MIC-QP1L	1	QSFP-40G-BIDI-SR-MM850	
		QSFP-40G-CSR4-MM850	
		QSFP-40G-ER4-WDM1300	
		QSFP-40G-LR4L-WDM1300	
		QSFP-40G-LR4-WDM1300	
		QSFP-40G-SR4-MM850	
MIC-SP4L	1-4	SFP-622M-LX-SM1310	
		SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
MIC-SP8L	1-8	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
MIC-TCP8L	1-8	SFP-622M-LX-SM1310	
		SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	

单板名称	端口	支持的光模块	说明
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-BIDI	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH40-SM1550-BIDI	
		SFP-GE-LH70-SM1490-BIDI	
		SFP-GE-LH70-SM1550-BIDI	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
MIC-XP10LF	1-10	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1330-BIDI	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
MIC-XP20L	1-20	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	

单板名称	端口	支持的光模块	说明
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
MIC-XP20LA	1-20	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	

单板名称	端口	支持的光模块	说明
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
MIC-XP2L	1-2	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	

单板名称	端口	支持的光模块	说明
MIC-XP2L-LAN	1-2	SFP-GE-FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
MIC-XP4L1	1-4	SFP-GE-FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1270-BIDI	
		SFP-XG-LH40-SM1330-BIDI	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1490-BIDI	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-BIDI	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1270-BIDI	
		SFP-XG-LX-SM1270-BIDI-S	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-LX-SM1330-BIDI	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
MIC-XP5L	1-5	SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	

单板名称	端口	支持的光模块	说明
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
	2-5	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
MIC-XP5L1	1-5	SFP-XG-LH40-SM1270-BIDI	
		SFP-XG-LH40-SM1330-BIDI	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1490-BIDI	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-BIDI	
		SFP-XG-LH80-SM1550-D	

单板名称	端口	支持的光模块	说明
		SFP-XG-LX-SM1270-BIDI	
		SFP-XG-LX-SM1270-BIDI-S	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-LX-SM1330-BIDI	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
	2-5	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
MIC-XP8L	1-8	SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	

单板名称	端口	支持的光模块	说明
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
NIC-CC1L	1	CFP2-100G-ER4-WDM1300	
		CFP2-100G-LR4-WDM1300	
		CFP2-100G-SR10-MM850	
NIC-CC2L	1-2	CFP2-100G-ER4-WDM1300	
		CFP2-100G-LR4-WDM1300	
		CFP2-100G-SR10-MM850	
NIC-CQ1L	1	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
NIC-CQ2L	1-2	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
NIC-CQ2LA	1-2	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	

单板名称	端口	支持的光模块	说明
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
NIC-GP20L	1-16	SFP-FE-LH40-SM1310	仅1-16口支持该光模块
		SFP-FE-LH80-SM1550	仅1-16口支持该光模块
		SFP-FE-LX-SM1310-D	仅1-16口支持该光模块
		SFP-FE-SX-MM1310-A	仅1-16口支持该光模块
		SFP-GE/FE-LX10-SM1310	仅1-16口支持FE光模块
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
	17-20	SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
NIC-GP24L	1-24	SFP-FE-LH40-SM1310	
		SFP-FE-LH80-SM1550	
		SFP-FE-LX-SM1310-A	
		SFP-FE-LX-SM1310-D	
		SFP-FE-SX-MM1310-A	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
NIC-GP24L1	1-24	SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
NIC-GP24L1A	1-24	SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
NIC-XP10L	1-10	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-BIDI	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH40-SM1550-BIDI	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH70-SM1490-BIDI	
		SFP-GE-LH70-SM1550-BIDI	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1270-BIDI	
		SFP-XG-LH40-SM1330-BIDI	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1490-BIDI	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-BIDI	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-LX-SM1330-BIDI	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
NIC-XP20L	1-20	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-BIDI	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH40-SM1550-BIDI	
		SFP-GE-LH70-SM1490-BIDI	
		SFP-GE-LH70-SM1550-BIDI	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1270-BIDI	
		SFP-XG-LH40-SM1330-BIDI	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1490-BIDI	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-BIDI	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-LX-SM1330-BIDI	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
NIC-XP20L1	1-20	SFP-GE-LH100-SM1550	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-BIDI	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH40-SM1550-BIDI	
		SFP-GE-LH70-SM1490-BIDI	
		SFP-GE-LH70-SM1550-BIDI	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1270-BIDI	
		SFP-XG-LH40-SM1330-BIDI	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1490-BIDI	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-BIDI	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-LX-SM1330-BIDI	
		SFP-XG-SX-MM850-A	

单板名称	端口	支持的光模块	说明
NIC-XP20L1A	1-20	SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
		SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-BIDI	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH40-SM1550-BIDI	
		SFP-GE-LH70-SM1490-BIDI	
		SFP-GE-LH70-SM1550-BIDI	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1270-BIDI	
		SFP-XG-LH40-SM1330-BIDI	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1490-BIDI	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-BIDI	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1270-BIDI	

单板名称	端口	支持的光模块	说明
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-LX-SM1330-BIDI	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
NIC-XP5L	1-5	SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
PIC-GP10L	1-10	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1310-S	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-BIDI-S	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-LX-SM1490-BIDI-S	
		SFP-GE-SX-MM850-A	

单板名称	端口	支持的光模块	说明
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
PIC-PS2G4L	1-6	SFP-2.5G-LH15-SM1310	
		SFP-2.5G-LH40-SM1310	
		SFP-2.5G-LX-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1310-S	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-BIDI-S	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-LX-SM1490-BIDI-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
PIC-PSP4L	1-4	SFP-2.5G-LH15-SM1310	
		SFP-2.5G-LH40-SM1310	
		SFP-2.5G-LX-SM1310	
PIC-PUP1L	1	XFP-LH40-SM1550-D	
		XFP-LH80-SM1550	
		XFP-LH80-SM1550-D	

单板名称	端口	支持的光模块	说明
PIC-TCP8L	1-8	XFP-POS-LH10-SM1310	
		SFP-622M-LX-SM1310	
		SFP-FE-LH40-SM1310	当PIC-TCP8L的接口为GE口时，不支持该光模块
		SFP-FE-LH80-SM1550	当PIC-TCP8L的接口为GE口时，不支持该光模块
		SFP-FE-LX-SM1310-A	当PIC-TCP8L的接口为GE口时，不支持该光模块
		SFP-FE-LX-SM1310-D	当PIC-TCP8L的接口为GE口时，不支持该光模块
		SFP-FE-SX-MM1310-A	当PIC-TCP8L的接口为GE口时，不支持该光模块
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1310-S	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-BIDI-S	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-LX-SM1490-BIDI-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
PIC-XP1L	1	XFP-LH40-SM1550-D	
		XFP-LH80-SM1550	
		XFP-LH80-SM1550-D	

单板名称	端口	支持的光模块	说明
		XFP-LX-SM1310	
		XFP-LX-SM1310-D	
		XFP-POS-LH10-SM1310	
		XFP-SX-MM850	
		XFP-SX-MM850-D	
RX-CEPC-CQ8LF	1-8	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
RX-NIC-CC1L	1	CFP2-100G-ER4-WDM1300	
		CFP2-100G-LR4-WDM1300	
		CFP2-100G-SR10-MM850	
RX-NIC-CC2L	1-2	CFP2-100G-ER4-WDM1300	
		CFP2-100G-LR4-WDM1300	
		CFP2-100G-SR10-MM850	
RX-NIC-CQ1LF	1	QSFP-100G-CWDM4-SM1300-A	
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
RX-NIC-CQ2LF	1-2	QSFP-100G-CWDM4-SM1300-A	

单板名称	端口	支持的光模块	说明
		QSFP-100G-ER4L-WDM1300	
		QSFP-100G-ER4-WDM1300	
		QSFP-100G-eSR4-MM850	
		QSFP-100G-LR4L-WDM1300	
		QSFP-100G-LR4-WDM1300	
		QSFP-100G-PSM4-SM1310	
		QSFP-100G-SR4-MM850	
		QSFP-100G-SWDM4-MM850	
		QSFP-100G-ZR4-WDM1300	
RX-NIC-GP20L	1-16	SFP-FE-LH40-SM1310	仅1-16口支持该光模块
		SFP-FE-LH80-SM1550	仅1-16口支持该光模块
		SFP-FE-LX-SM1310-D	仅1-16口支持该光模块
		SFP-FE-SX-MM1310-A	仅1-16口支持该光模块
		SFP-GE/FE-LX10-SM1310	仅1-16口支持FE光模块
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
	17-20	SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	

单板名称	端口	支持的光模块	说明
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
RX-NIC-LGQ2L	1-2	QSFP-50G-ER-SM1311	
		QSFP-50G-LR-SM1311	
RX-NIC-LGQ4L	1-4	QSFP-50G-ER-SM1311	
		QSFP-50G-LR-SM1311	
RX-NIC-XP10L	1-10	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-BIDI	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH40-SM1550-BIDI	
		SFP-GE-LH70-SM1490-BIDI	
		SFP-GE-LH70-SM1550-BIDI	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	

单板名称	端口	支持的光模块	说明
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1270-BIDI	
		SFP-XG-LH40-SM1330-BIDI	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1490-BIDI	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-BIDI	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-LX-SM1330-BIDI	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
RX-NIC-XP20L	1-20	SFP-GE/FE-LX10-SM1310	
		SFP-GE-LH100-SM1550	
		SFP-GE-LH40-SM1310	
		SFP-GE-LH40-SM1310-BIDI	
		SFP-GE-LH40-SM1310-D	
		SFP-GE-LH40-SM1550	
		SFP-GE-LH40-SM1550-BIDI	
		SFP-GE-LH70-SM1490-BIDI	
		SFP-GE-LH70-SM1550-BIDI	
		SFP-GE-LH80-SM1550	
		SFP-GE-LH80-SM1550-D	
		SFP-GE-LX-SM1310-A	
		SFP-GE-LX-SM1310-BIDI	
		SFP-GE-LX-SM1310-D	
		SFP-GE-LX-SM1310-S	

单板名称	端口	支持的光模块	说明
		SFP-GE-LX-SM1490-BIDI	
		SFP-GE-SX-MM850-A	
		SFP-GE-SX-MM850-D	
		SFP-GE-SX-MM850-S	
		SFP-GE-T	
		SFP-GE-T-D	
		SFP-XG-LH40-SM1270-BIDI	
		SFP-XG-LH40-SM1330-BIDI	
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1490-BIDI	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-BIDI	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-LX-SM1330-BIDI	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	
RX-NIC-XP5L	1-5	SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
RX-NIC-YGS4L	1-4	SFP-25G-LR-SM1310	
		SFP-25G-SR-MM850	

单板名称	端口	支持的光模块	说明
		SFP-XG-LH40-SM1550	
		SFP-XG-LH40-SM1550-D	
		SFP-XG-LH80-SM1550	
		SFP-XG-LH80-SM1550-D	
		SFP-XG-LX-SM1310	
		SFP-XG-LX-SM1310-D	
		SFP-XG-LX-SM1310-S	
		SFP-XG-SX-MM850-A	
		SFP-XG-SX-MM850-D	
		SFP-XG-SX-MM850-S	