

H3C S10500X-G 系列交换机

单板与光模块适配关系表

Copyright © 2024 新华三技术有限公司 版权所有，保留一切权利。

非经本公司书面许可，任何单位和个人不得擅自摘抄、复制本文档内容的部分或全部，并不得以任何形式传播。

除新华三技术有限公司的商标外，本手册中出现的其它公司的商标、产品标识及商品名称，由各自权利人拥有。

本文档中的信息可能变动，恕不另行通知。

1 单板与光模块适配关系

本系列产品支持多种光模块或线缆，不同接口支持的光模块或线缆类型不同，具体请参见单板与光模块适配关系表。

电缆仅用于本系列交换机之间互连，作为交换机部分软件特性（如：IRF）的专用线缆。

更多光模块或线缆属性信息，请参见[《H3C 光模块手册》](#)。

1.1 使用限制

拆分后的光接口不支持通过 `speed` 命令修改端口速率。

100GE 的光接口拆分为 10GE，只能使用 QSFP+ to SFP+ 线缆。

1.2 单板与光模块适配关系表

表1-1 单板与光模块适配关系表

单板名称	端口	支持的光模块	版本适配及说明
LSEM1CDQ2SF0	1~2	CAB-400G-QSFP-DD-2m	E7753P15
		LSWM1QSTK0	E7753P15
		LSWM1QSTK1	E7753P15
		LSWM1QSTK2	E7753P15
		QSFP-100G-CWDM4-SM1300-A	E7753P15
		QSFP-100G-D-AOC-10M	E7753P15
		QSFP-100G-D-AOC-20M	E7753P15
		QSFP-100G-D-AOC-7M	E7753P15
		QSFP-100G-D-CAB-1M	E7753P15
		QSFP-100G-D-CAB-3M	E7753P15
		QSFP-100G-D-CAB-5M	E7753P15
		QSFP-100G-ER4L-WDM1300	E7753P15
		QSFP-100G-eSR4-MM850	E7753P15
		QSFP-100G-LR4L-WDM1300	E7753P15
		QSFP-100G-LR4-WDM1300	E7753P15
		QSFP-100G-PSM4-SM1310	E7753P15
		QSFP-100G-SR4-MM850	E7753P15
QSFP-100G-SR4-MM850-A	E7753P15		
QSFP-100G-SR4-MM850-H	E805303		

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-SWDM4-MM850	E7753P15
		QSFP-40G-BIDI-SR-MM850	E7753P15
		QSFP-40G-BIDI-WDM850	E7753P15
		QSFP-40G-CSR4-MM850	E7753P15
		QSFP-40G-D-AOC-10M	E7753P15
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7753P15
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7753P15
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-ER4-WDM1300	E7753P15
		QSFP-40G-LR4L-WDM1300	E7753P15
		QSFP-40G-LR4-PSM1310	E7753P15
		QSFP-40G-LR4-PSM1310-A	E7753P15
		QSFP-40G-LR4-WDM1300	E7753P15
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7753P15
		QSFP56-200G-D-AOC-10m	R7755P01
		QSFP56-200G-D-AOC-20m	R7755P01
		QSFP56-200G-D-AOC-5m	R7755P01
		QSFP56-200G-D-AOC-7m	R7755P01
		QSFP56-200G-D-DAC-1m	R7755P01
		QSFP56-200G-D-DAC-2m	R7755P01
		QSFP56-200G-D-DAC-3m	R7755P01
		QSFP56-200G-FR4-WDM1300	E7755
		QSFP56-200G-SR4-MM850	E7755
		QSFPDD-400G-2QSFP56-200G-AOC-10m	R7755P01
		QSFPDD-400G-2QSFP56-200G-AOC-20m	R7755P01
		QSFPDD-400G-2QSFP56-200G-AOC-30m	R7755P01
		QSFPDD-400G-2QSFP56-200G-AOC-50m	R7755P01

单板名称	端口	支持的光模块	版本适配及说明
		QSFPDD-400G-2QSFP56-200G-AOC-5m	R7755P01
		QSFPDD-400G-2QSFP56-200G-AOC-7m	R7755P01
		QSFPDD-400G-FR4-WDM1300	R7755P01
		QSFPDD-400G-LR4-WDM1300-D C	R7755P01
		QSFPDD-400G-LR8-WDM1300	R7755P01
		QSFPDD-400G-SR8-MM850	E7753P15
LSEM1CGQ16SF0	1~16	HK-QSFP28-100G-850-DF-MM	E7753P1601
		LSWM1QSTK0	E7751P03
		LSWM1QSTK1	E7751P03
		LSWM1QSTK2	E7751P03
		LSWM1QSTK3	E7751P03
		LSWM1QSTK4	E7751P03
		LSWM1QSTK5	E7751P03
		QSFP-100G-4SFP-25G-CAB-1M	E7751P03
		QSFP-100G-4SFP-25G-CAB-3M	E7751P03
		QSFP-100G-4SFP-25G-CAB-5M	E7751P03
		QSFP-100G-BIDI-MM850	R7755P01
		QSFP-100G-CWDM4-SM1300-A	E7751P03
		QSFP-100G-D-AOC-10M	E7751P03
		QSFP-100G-D-AOC-20M	E7751P03
		QSFP-100G-D-AOC-7M	E7751P03
		QSFP-100G-D-CAB-1M	E7751P03
		QSFP-100G-D-CAB-3M	E7751P03
		QSFP-100G-D-CAB-5M	E7751P03
		QSFP-100G-ER4L-WDM1300	E7751P03
		QSFP-100G-eSR4-MM850	E7751P03
		QSFP-100G-LR4L-WDM1300	E7751P03
		QSFP-100G-LR4-WDM1300	E7751P03
		QSFP-100G-PSM4-SM1310	E7751P03
		QSFP-100G-SR4-MM850	E7751P03

单板名称	端口	支持的光模块	版本适配及说明		
		QSFP-100G-SR4-MM850-A	E7751P03		
		QSFP-100G-SR4-MM850-H	E805303		
		QSFP-100G-SWDM4-MM850	E7751P03		
		QSFP-40G-BIDI-SR-MM850	E7751P03		
		QSFP-40G-BIDI-WDM850	E7751P03		
		QSFP-40G-CSR4-MM850	E7751P03		
		QSFP-40G-D-AOC-10M	E7751P03		
		QSFP-40G-D-AOC-10M-H	R7755P01		
		QSFP-40G-D-AOC-20M	E7751P03		
		QSFP-40G-D-AOC-20M-H	R7755P01		
		QSFP-40G-D-AOC-7M	E7751P03		
		QSFP-40G-D-AOC-7M-H	R7755P01		
		QSFP-40G-ER4-WDM1300	E7751P03		
		QSFP-40G-LR4L-WDM1300	E7751P03		
		QSFP-40G-LR4-PSM1310	E7751P03		
		QSFP-40G-LR4-WDM1300	E7751P03		
		QSFP-40G-LX4-WDM1300	R7754P10		
		QSFP-40G-SR4-MM850	E7751P03		
		LSEM1CGQ36SF0	1~36	LSWM1QSTK0	E7753P15
				LSWM1QSTK1	E7753P15
LSWM1QSTK2	E7753P15				
LSWM1QSTK3	E7753P15				
LSWM1QSTK4	E7753P15				
LSWM1QSTK5	E7753P15				
QSFP-100G-4SFP-25G-CAB-1M	E7753P15				
QSFP-100G-4SFP-25G-CAB-3M	E7753P15				
QSFP-100G-4SFP-25G-CAB-5M	E7753P15				
QSFP-100G-BIDI-MM850	R7755P01				
QSFP-100G-CWDM4-SM1300-A	E7753P15				
QSFP-100G-D-AOC-10M	E7753P15				
QSFP-100G-D-AOC-20M	E7753P15				
QSFP-100G-D-AOC-7M	E7753P15				

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-D-CAB-1M	E7753P15
		QSFP-100G-D-CAB-3M	E7753P15
		QSFP-100G-D-CAB-5M	E7753P15
		QSFP-100G-eSR4-MM850	E7753P15
		QSFP-100G-LR4L-WDM1300	E7753P15
		QSFP-100G-LR4-WDM1300	E7753P15
		QSFP-100G-PSM4-SM1310	E7753P15
		QSFP-100G-SR4-MM850	E7753P15
		QSFP-100G-SR4-MM850-A	E7753P15
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	E7753P15
		QSFP-40G-BIDI-SR-MM850	E7753P15
		QSFP-40G-BIDI-WDM850	E7753P15
		QSFP-40G-CSR4-MM850	E7753P15
		QSFP-40G-D-AOC-10M	E7753P15
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7753P15
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7753P15
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-ER4-WDM1300	E7753P15
		QSFP-40G-LR4L-WDM1300	E7753P15
		QSFP-40G-LR4-PSM1310	E7753P15
		QSFP-40G-LR4-PSM1310-A	E7753P15
		QSFP-40G-LR4-WDM1300	E7753P15
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7753P15
LSEM1GT24GP16TSSD0	25~36	CAB-0.5M-SFP+	E7753P15, Cannot be used for IRF setup connections.
		CAB-1M-SFP+	E7753P15, Cannot be used for IRF setup connections.
		CAB-3M-SFP+	E7753P15, Cannot be used for IRF setup connections.

单板名称	端口	支持的光模块	版本适配及说明
		LSTM1STK	E7753P15, Cannot be used for IRF setup connections.
		LSWM1STK	E7753P15, Cannot be used for IRF setup connections.
		LSWM2STK	E7753P15, Cannot be used for IRF setup connections.
		LSWM3STK	E7753P15, Cannot be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	E7753P15
		SFP-FE-LX-SM1310-A	E7753P15
		SFP-FE-LX-SM1310-BIDI	E7753P15
		SFP-FE-LX-SM1310-D	E7753P15
		SFP-FE-LX-SM1550-BIDI	E7753P15
		SFP-FE-SX-MM1310-A	E7753P15
		SFP-GE-LH100-SM1550	E7753P15
		SFP-GE-LH40-SM1310	E7753P15
		SFP-GE-LH40-SM1310-BIDI	E7753P15
		SFP-GE-LH40-SM1310-D	E7753P15
		SFP-GE-LH40-SM1550	E7753P15
		SFP-GE-LH40-SM1550-BIDI	E7753P15
		SFP-GE-LH70-SM1490-BIDI	E7753P15
		SFP-GE-LH70-SM1550-BIDI	E7753P15
		SFP-GE-LH80-SM1550	E7753P15
		SFP-GE-LH80-SM1550-D	E7753P15
		SFP-GE-LX-SM1310-A	E7753P15
		SFP-GE-LX-SM1310-BIDI	E7753P15
		SFP-GE-LX-SM1310-D	E7753P15
		SFP-GE-LX-SM1310-S	E7753P15
		SFP-GE-LX-SM1490-BIDI	E7753P15
		SFP-GE-SX-MM850-A	E7753P15
		SFP-GE-SX-MM850-D	E7753P15
		SFP-GE-SX-MM850-S	E7753P15
		SFP-GE-T	E7753P15

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-T-D	E7753P15
		SFP-XG-LH40-SM1270-BIDI	E7753P15
		SFP-XG-LH40-SM1330-BIDI	E7753P15
		SFP-XG-LH40-SM1550	E7753P15
		SFP-XG-LH40-SM1550-D	E7753P15
		SFP-XG-LH80-SM1490-BIDI	E7753P15
		SFP-XG-LH80-SM1550	E7753P15
		SFP-XG-LH80-SM1550-BIDI	E7753P15
		SFP-XG-LH80-SM1550-D	E7753P15
		SFP-XG-LX-SM1270-BIDI	E7753P15
		SFP-XG-LX-SM1310	E7753P15
		SFP-XG-LX-SM1310-D	E7753P15
		SFP-XG-LX-SM1310-E	E7753P15
		SFP-XG-LX-SM1310-S	E7753P15
		SFP-XG-LX-SM1330-BIDI	E7753P15
		SFP-XG-SX-MM850-A	E7753P15
		SFP-XG-SX-MM850-D	E7753P15
		SFP-XG-SX-MM850-E	E7753P15
		SFP-XG-SX-MM850-S	E7753P15
	37~52	SFP-FE-LH40-SM1310	E7753P15
		SFP-FE-LX-SM1310-A	E7753P15
		SFP-FE-LX-SM1310-BIDI	E7753P15
		SFP-FE-LX-SM1310-D	E7753P15
		SFP-FE-LX-SM1550-BIDI	E7753P15
		SFP-FE-SX-MM1310-A	E7753P15
		SFP-GE-LH100-SM1550	E7753P15
		SFP-GE-LH40-SM1310	E7753P15
		SFP-GE-LH40-SM1310-BIDI	E7753P15
		SFP-GE-LH40-SM1310-D	E7753P15
		SFP-GE-LH40-SM1550	E7753P15
		SFP-GE-LH40-SM1550-BIDI	E7753P15
		SFP-GE-LH70-SM1490-BIDI	E7753P15

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LH70-SM1550-BIDI	E7753P15
		SFP-GE-LH80-SM1550	E7753P15
		SFP-GE-LH80-SM1550-D	E7753P15
		SFP-GE-LX-SM1310-A	E7753P15
		SFP-GE-LX-SM1310-BIDI	E7753P15
		SFP-GE-LX-SM1310-D	E7753P15
		SFP-GE-LX-SM1310-S	E7753P15
		SFP-GE-LX-SM1490-BIDI	E7753P15
		SFP-GE-SX-MM850-A	E7753P15
		SFP-GE-SX-MM850-D	E7753P15
		SFP-GE-SX-MM850-S	E7753P15
		SFP-GE-T	E7753P15
		SFP-GE-T-D	E7753P15
		LSEM1GT48TS24QSSD049~72	
CAB-1M-SFP+	E7753P16, Cannot be used for IRF setup connections.		
CAB-3M-SFP+	E7753P16, Cannot be used for IRF setup connections.		
LSTM1STK	E7753P16, Cannot be used for IRF setup connections.		
LSWM1STK	E7753P16, Cannot be used for IRF setup connections.		
LSWM2STK	E7753P16, Cannot be used for IRF setup connections.		
LSWM3STK	E7753P16, Cannot be used for IRF setup connections.		
SFP-2.5G-LX10-SM1310-DR-I	R7755P01		
SFP-FE-LH40-SM1310	E7753P16		
SFP-FE-LX-SM1310-A	E7753P16		
SFP-FE-LX-SM1310-BIDI	E7753P16		
SFP-FE-LX-SM1310-D	E7753P16		
SFP-FE-LX-SM1550-BIDI	E7753P16		
SFP-FE-SX-MM1310-A	E7753P16		
SFP-GE-LH100-SM1550	E7753P16		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LH40-SM1310	E7753P16
		SFP-GE-LH40-SM1310-BIDI	E7753P16
		SFP-GE-LH40-SM1310-D	E7753P16
		SFP-GE-LH40-SM1550	E7753P16
		SFP-GE-LH40-SM1550-BIDI	E7753P16
		SFP-GE-LH70-SM1490-BIDI	E7753P16
		SFP-GE-LH70-SM1550-BIDI	E7753P16
		SFP-GE-LH80-SM1550	E7753P16
		SFP-GE-LH80-SM1550-D	E7753P16
		SFP-GE-LX-SM1310-A	E7753P16
		SFP-GE-LX-SM1310-BIDI	E7753P16
		SFP-GE-LX-SM1310-D	E7753P16
		SFP-GE-LX-SM1310-S	E7753P16
		SFP-GE-LX-SM1490-BIDI	E7753P16
		SFP-GE-SX-MM850-A	E7753P16
		SFP-GE-SX-MM850-D	E7753P16
		SFP-GE-SX-MM850-S	E7753P16
		SFP-GE-T	E7753P16
		SFP-GE-T-D	E7753P16
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7753P16
		SFP-XG-LH40-SM1330-BIDI	E7753P16
		SFP-XG-LH40-SM1550	E7753P16
		SFP-XG-LH40-SM1550-D	E7753P16
		SFP-XG-LH80-SM1490-BIDI	E7753P16
		SFP-XG-LH80-SM1550	E7753P16
		SFP-XG-LH80-SM1550-BIDI	E7753P16
		SFP-XG-LH80-SM1550-D	E7753P16
		SFP-XG-LX-SM1270-BIDI	E7753P16
		SFP-XG-LX-SM1310	E7753P16

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LX-SM1310-D	E7753P16
		SFP-XG-LX-SM1310-E	E7753P16
		SFP-XG-LX-SM1330-BIDI	E7753P16
		SFP-XG-SX-MM850-A	E7753P16
		SFP-XG-SX-MM850-D	E7753P16
		SFP-XG-SX-MM850-E	E7753P16
		SFP-XG-SX-MM850-F1	E7753P16
	73~74	LSWM1QSTK0	E7753P16, Cannot be used for IRF setup connections.
		LSWM1QSTK1	E7753P16, Cannot be used for IRF setup connections.
		LSWM1QSTK2	E7753P16, Cannot be used for IRF setup connections.
		LSWM1QSTK3	E7753P16
		LSWM1QSTK4	E7753P16
		LSWM1QSTK5	E7753P16
		QSFP-40G-BIDI-SR-MM850	E7753P16
		QSFP-40G-BIDI-WDM850	E7753P16
		QSFP-40G-CSR4-MM850	E7753P16
		QSFP-40G-D-AOC-10M	E7753P16
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7753P16
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7753P16
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-ER4-WDM1300	E7753P16
		QSFP-40G-LR4L-WDM1300	E7753P16
		QSFP-40G-LR4-PSM1310	E7753P16
		QSFP-40G-LR4-WDM1300	E7753P16
		QSFP-40G-LX4-WDM1300	R7754P10
QSFP-40G-SR4-MM850	E7753P16		
LSEM1GT48TSSD0	49~52	CAB-0.5M-SFP+	E7751P02, Cannot be used for IRF setup connections.
		CAB-1M-SFP+	E7751P02, Cannot be used

单板名称	端口	支持的光模块	版本适配及说明
			for IRF setup connections.
		CAB-3M-SFP+	E7751P02, Cannot be used for IRF setup connections.
		LSTM1STK	E7751P02, Cannot be used for IRF setup connections.
		LSWM1STK	E7751P02, Cannot be used for IRF setup connections.
		LSWM2STK	E7751P02, Cannot be used for IRF setup connections.
		LSWM3STK	E7751P02, Cannot be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	E775305
		SFP-FE-LX-SM1310-A	E775305
		SFP-FE-LX-SM1310-BIDI	E775305
		SFP-FE-LX-SM1310-D	E775305
		SFP-FE-LX-SM1550-BIDI	E775305
		SFP-FE-SX-MM1310-A	E775305
		SFP-GE-LH100-SM1550	E7751P02
		SFP-GE-LH40-SM1310	E7751P02
		SFP-GE-LH40-SM1310-BIDI	E7751P02
		SFP-GE-LH40-SM1310-D	E7751P02
		SFP-GE-LH40-SM1550	E7751P02
		SFP-GE-LH40-SM1550-BIDI	E7751P02
		SFP-GE-LH70-SM1490-BIDI	E7751P02
		SFP-GE-LH70-SM1550-BIDI	E7751P02
		SFP-GE-LH80-SM1550	E7751P02
		SFP-GE-LH80-SM1550-D	E7751P02
		SFP-GE-LX-SM1310-A	E7751P02
		SFP-GE-LX-SM1310-BIDI	E7751P02
		SFP-GE-LX-SM1310-D	E7751P02
		SFP-GE-LX-SM1310-S	E7751P02
		SFP-GE-LX-SM1490-BIDI	E7751P02
		SFP-GE-SX-MM850-A	E7751P02

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-SX-MM850-D	E7751P02
		SFP-GE-SX-MM850-S	E7751P02
		SFP-GE-T	E7751P02
		SFP-GE-T-D	E7751P02
		SFP-XG-LH40-SM1270-BIDI	E7751P02
		SFP-XG-LH40-SM1330-BIDI	E7751P02
		SFP-XG-LH40-SM1550	E7751P02
		SFP-XG-LH40-SM1550-D	E7751P02
		SFP-XG-LH80-SM1490-BIDI	E7751P02
		SFP-XG-LH80-SM1550	E7751P02
		SFP-XG-LH80-SM1550-BIDI	E7751P02
		SFP-XG-LH80-SM1550-D	E7751P02
		SFP-XG-LX-SM1270-BIDI	E7751P02
		SFP-XG-LX-SM1310	E7751P02
		SFP-XG-LX-SM1310-D	E7751P02
		SFP-XG-LX-SM1310-E	E7751P02
		SFP-XG-LX-SM1330-BIDI	E7751P02
		SFP-XG-SX-MM850-A	E7751P02
		SFP-XG-SX-MM850-D	E7751P02
		SFP-XG-SX-MM850-E	E7751P02
SFP-XG-SX-MM850-F1	E7751P02		
LSEM1GV48TSSD0	49~52	CAB-0.5M-SFP+	E7753P16, Cannot be used for IRF setup connections.
		CAB-1M-SFP+	E7753P16, Cannot be used for IRF setup connections.
		CAB-3M-SFP+	E7753P16, Cannot be used for IRF setup connections.
		LSTM1STK	E7753P16, Cannot be used for IRF setup connections.
		LSWM1STK	E7753P16, Cannot be used for IRF setup connections.
		LSWM2STK	E7753P16, Cannot be used for IRF setup connections.
		LSWM3STK	E7753P16, Cannot be used for IRF setup connections.

单板名称	端口	支持的光模块	版本适配及说明
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	E7753P16
		SFP-FE-LX-SM1310-A	E7753P16
		SFP-FE-LX-SM1310-BIDI	E7753P16
		SFP-FE-LX-SM1310-D	E7753P16
		SFP-FE-LX-SM1550-BIDI	E7753P16
		SFP-FE-SX-MM1310-A	E7753P16
		SFP-GE-LH100-SM1550	E7753P16
		SFP-GE-LH40-SM1310	E7753P16
		SFP-GE-LH40-SM1310-BIDI	E7753P16
		SFP-GE-LH40-SM1310-D	E7753P16
		SFP-GE-LH40-SM1550	E7753P16
		SFP-GE-LH40-SM1550-BIDI	E7753P16
		SFP-GE-LH70-SM1490-BIDI	E7753P16
		SFP-GE-LH70-SM1550-BIDI	E7753P16
		SFP-GE-LH80-SM1550	E7753P16
		SFP-GE-LH80-SM1550-D	E7753P16
		SFP-GE-LX-SM1310-A	E7753P16
		SFP-GE-LX-SM1310-BIDI	E7753P16
		SFP-GE-LX-SM1310-D	E7753P16
		SFP-GE-LX-SM1310-S	E7753P16
		SFP-GE-LX-SM1490-BIDI	E7753P16
		SFP-GE-SX-MM850-A	E7753P16
		SFP-GE-SX-MM850-D	E7753P16
		SFP-GE-SX-MM850-S	E7753P16
		SFP-GE-T	E7753P16
		SFP-GE-T-D	E7753P16
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7753P16
		SFP-XG-LH40-SM1330-BIDI	E7753P16

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LH40-SM1550	E7753P16
		SFP-XG-LH40-SM1550-D	E7753P16
		SFP-XG-LH80-SM1490-BIDI	E7753P16
		SFP-XG-LH80-SM1550	E7753P16
		SFP-XG-LH80-SM1550-BIDI	E7753P16
		SFP-XG-LH80-SM1550-D	E7753P16
		SFP-XG-LX-SM1270-BIDI	E7753P16
		SFP-XG-LX-SM1310	E7753P16
		SFP-XG-LX-SM1310-D	E7753P16
		SFP-XG-LX-SM1310-E	E7753P16
		SFP-XG-LX-SM1330-BIDI	E7753P16
		SFP-XG-SX-MM850-A	E7753P16
		SFP-XG-SX-MM850-D	E7753P16
		SFP-XG-SX-MM850-E	E7753P16
		SFP-XG-SX-MM850-F1	E7753P16
		LSEM1QGS16SF0	1~16
LSWM1QSTK1	E7752P05		
LSWM1QSTK2	E7752P05		
LSWM1QSTK3	E7752P05		
LSWM1QSTK4	E7752P05		
LSWM1QSTK5	E7752P05		
QSFP-40G-BIDI-SR-MM850	E7752P05		
QSFP-40G-BIDI-WDM850	E7752P05		
QSFP-40G-CSR4-MM850	E7752P05		
QSFP-40G-D-AOC-10M	E7752P05		
QSFP-40G-D-AOC-10M-H	R7755P01		
QSFP-40G-D-AOC-20M	E7752P05		
QSFP-40G-D-AOC-20M-H	R7755P01		
QSFP-40G-D-AOC-7M	E7752P05		
QSFP-40G-D-AOC-7M-H	R7755P01		
QSFP-40G-ER4-WDM1300	E7752P05		
QSFP-40G-LR4L-WDM1300	E7752P05		

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-LR4-PSM1310	E7752P05
		QSFP-40G-LR4-WDM1300	E7752P05
		QSFP-40G-LX4-WDM1300	R7753P05
		QSFP-40G-SR4-MM850	E7752P05
LSEM1QGS36SF0	1~36	LSWM1QSTK0	E7754P02
		LSWM1QSTK1	E7754P02
		LSWM1QSTK2	E7754P02
		LSWM1QSTK3	E7754P02
		LSWM1QSTK4	E7754P02
		LSWM1QSTK5	E7754P02
		QSFP-40G-BIDI-SR-MM850	E7754P02
		QSFP-40G-BIDI-WDM850	E7754P02
		QSFP-40G-CSR4-MM850	E7754P02
		QSFP-40G-D-AOC-10M	E7754P02
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7754P02
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7754P02
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-ER4-WDM1300	E7754P02
		QSFP-40G-LR4L-WDM1300	E7754P02
		QSFP-40G-LR4-PSM1310	E7754P02
		QSFP-40G-LR4-PSM1310-A	E7754P02
		QSFP-40G-LR4-WDM1300	E7754P02
QSFP-40G-LX4-WDM1300	R7754P10		
QSFP-40G-SR4-MM850	E7754P02		
LSEM1RCGQ2TSSF0	1~16	CAB-0.5M-SFP+	E7758
		CAB-1M-SFP+	E7758
		CAB-3M-SFP+	E7758
		LSTM1STK	E7758
		LSWM1STK	E7758
		LSWM2STK	E7758

单板名称	端口	支持的光模块	版本适配及说明
		LSWM3STK	E7758
		SFP-GE-LH100-SM1550	E7758
		SFP-GE-LH40-SM1310	E7758
		SFP-GE-LH40-SM1310-BIDI	E7758
		SFP-GE-LH40-SM1310-D	E7758
		SFP-GE-LH40-SM1550	E7758
		SFP-GE-LH40-SM1550-BIDI	E7758
		SFP-GE-LH70-SM1490-BIDI	E7758
		SFP-GE-LH70-SM1550-BIDI	E7758
		SFP-GE-LH80-SM1550	E7758
		SFP-GE-LH80-SM1550-D	E7758
		SFP-GE-LX-SM1310-A	E7758
		SFP-GE-LX-SM1310-BIDI	E7758
		SFP-GE-LX-SM1310-D	E7758
		SFP-GE-LX-SM1310-S	E7758
		SFP-GE-LX-SM1490-BIDI	E7758
		SFP-GE-SX-MM850-A	E7758
		SFP-GE-SX-MM850-D	E7758
		SFP-GE-SX-MM850-S	E7758
		SFP-GE-T	E7758
		SFP-GE-T-D	E7758
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7758
		SFP-XG-LH40-SM1330-BIDI	E7758
		SFP-XG-LH40-SM1550	E7758
		SFP-XG-LH40-SM1550-D	E7758
		SFP-XG-LH80-SM1490-BIDI	E7758
		SFP-XG-LH80-SM1550	E7758
		SFP-XG-LH80-SM1550-BIDI	E7758
		SFP-XG-LH80-SM1550-D	E7758
		SFP-XG-LX-SM1270-BIDI	E7758
		SFP-XG-LX-SM1310	E7758

单板名称	端口	支持的光模块	版本适配及说明	
		SFP-XG-LX-SM1310-D	E7758	
		SFP-XG-LX-SM1310-E	E7758	
		SFP-XG-LX-SM1330-BIDI	E7758	
		SFP-XG-SX-MM850-A	E7758	
		SFP-XG-SX-MM850-D	E7758	
		SFP-XG-SX-MM850-E	E7758	
		SFP-XG-SX-MM850-F1	E7758	
	17~18		QSFP-100G-BIDI-MM850	E7758
			QSFP-100G-CWDM4-SM1300-A	E7758
			QSFP-100G-ER4L-WDM1300	E7758
			QSFP-100G-ER4-WDM1300	E7758
			QSFP-100G-LR4L-WDM1300	E7758
			QSFP-100G-LR4-WDM1300	E7758
			QSFP-100G-PSM4-SM1310	E7758
			QSFP-100G-SR4-MM850	E7758
			QSFP-100G-SR4-MM850-A	E7758
			QSFP-100G-SR4-MM850-H	E7758
			QSFP-100G-SWDM4-MM850	E7758
			QSFP-100G-ZR4-WDM1300	E7758
			QSFP-40G-BIDI-SR-MM850	E7758
			QSFP-40G-BIDI-WDM850	E7758
			QSFP-40G-CSR4-MM850	E7758
			QSFP-40G-ER4-WDM1300	E7758
			QSFP-40G-LR4L-WDM1300	E7758
			QSFP-40G-LR4-PSM1310	E7758
			QSFP-40G-LR4-PSM1310-A	E7758
			QSFP-40G-LR4-WDM1300	E7758
QSFP-40G-LX4-WDM1300	E7758			
QSFP-40G-SR4-MM850	E7758			
SFP-XG-LH40-SM1270-BIDI	E7758			
SFP-XG-LH40-SM1330-BIDI	E7758			
SFP-XG-LH40-SM1550	E7758			

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LH40-SM1550-D	E7758
		SFP-XG-LH80-SM1490-BIDI	E7758
		SFP-XG-LH80-SM1550	E7758
		SFP-XG-LH80-SM1550-BIDI	E7758
		SFP-XG-LH80-SM1550-D	E7758
		SFP-XG-LX-SM1270-BIDI	E7758
		SFP-XG-LX-SM1310	E7758
		SFP-XG-LX-SM1310-D	E7758
		SFP-XG-LX-SM1310-E	E7758
		SFP-XG-LX-SM1330-BIDI	E7758
		SFP-XG-SX-MM850-A	E7758
		SFP-XG-SX-MM850-D	E7758
		SFP-XG-SX-MM850-E	E7758
		SFP-XG-SX-MM850-F1	E7758
LSEM1SUPA0	MANAGEMENT	SFP-GE-LH100-SM1550	E7751P02
		SFP-GE-LH40-SM1310	E7751P02
		SFP-GE-LH40-SM1310-D	E7751P02
		SFP-GE-LH40-SM1550	E7751P02
		SFP-GE-LH80-SM1550	E7751P02
		SFP-GE-LH80-SM1550-D	E7751P02
		SFP-GE-LX-SM1310-A	E7751P02
		SFP-GE-LX-SM1310-BIDI	E7751P02
		SFP-GE-LX-SM1310-D	E7751P02
		SFP-GE-LX-SM1310-S	E7751P02
		SFP-GE-LX-SM1490-BIDI	E7751P02
		SFP-GE-SX-MM850-A	E7751P02
		SFP-GE-SX-MM850-D	E7751P02
		SFP-GE-SX-MM850-S	E7751P02
LSEM1SUPB0	MANAGEMENT	SFP-GE-LH100-SM1550	E7751P03
		SFP-GE-LH40-SM1310	E7751P03
		SFP-GE-LH40-SM1310-D	E7751P03
		SFP-GE-LH40-SM1550	E7751P03

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LH80-SM1550	E7751P03
		SFP-GE-LH80-SM1550-D	E7751P03
		SFP-GE-LX-SM1310-A	E7751P03
		SFP-GE-LX-SM1310-BIDI	E7751P03
		SFP-GE-LX-SM1310-D	E7751P03
		SFP-GE-LX-SM1310-S	E7751P03
		SFP-GE-LX-SM1490-BIDI	E7751P03
		SFP-GE-SX-MM850-A	E7751P03
		SFP-GE-SX-MM850-D	E7751P03
		SFP-GE-SX-MM850-S	E7751P03
LSEM1TGS16GP32SD0	1~16, 33~48	SFP-FE-LH40-SM1310	E7752P05
		SFP-FE-LX-SM1310-A	E7752P05
		SFP-FE-LX-SM1310-BIDI	E7752P05
		SFP-FE-LX-SM1310-D	E7752P05
		SFP-FE-LX-SM1550-BIDI	E7752P05
		SFP-FE-SX-MM1310-A	E7752P05
		SFP-GE-LH100-SM1550	E7752P05
		SFP-GE-LH40-SM1310	E7752P05
		SFP-GE-LH40-SM1310-BIDI	E7752P05
		SFP-GE-LH40-SM1310-D	E7752P05
		SFP-GE-LH40-SM1550	E7752P05
		SFP-GE-LH40-SM1550-BIDI	E7752P05
		SFP-GE-LH70-SM1490-BIDI	E7752P05
		SFP-GE-LH70-SM1550-BIDI	E7752P05
		SFP-GE-LH80-SM1550	E7752P05
		SFP-GE-LH80-SM1550-D	E7752P05
		SFP-GE-LX-SM1310-A	E7752P05
		SFP-GE-LX-SM1310-BIDI	E7752P05
		SFP-GE-LX-SM1310-D	E7752P05
		SFP-GE-LX-SM1310-S	E7752P05
SFP-GE-LX-SM1490-BIDI	E7752P05		
SFP-GE-SX-MM850-A	E7752P05		

单板名称	端口	支持的光模块	版本适配及说明	
		SFP-GE-SX-MM850-D	E7752P05	
		SFP-GE-SX-MM850-S	E7752P05	
		SFP-GE-T	E7752P05	
		SFP-GE-T-D	E7752P05	
	17~32		CAB-0.5M-SFP+	E7752P05, Cannot be used for IRF setup connections.
			CAB-1M-SFP+	E7752P05, Cannot be used for IRF setup connections.
			CAB-3M-SFP+	E7752P05, Cannot be used for IRF setup connections.
			LSTM1STK	E7752P05, Cannot be used for IRF setup connections.
			LSWM1STK	E7752P05, Cannot be used for IRF setup connections.
			LSWM2STK	E7752P05, Cannot be used for IRF setup connections.
			LSWM3STK	E7752P05, Cannot be used for IRF setup connections.
			SFP-2.5G-LX10-SM1310-DR-I	R7755P01
			SFP-FE-LH40-SM1310	E7752P05
			SFP-FE-LX-SM1310-A	E7752P05
			SFP-FE-LX-SM1310-BIDI	E7752P05
			SFP-FE-LX-SM1310-D	E7752P05
			SFP-FE-LX-SM1550-BIDI	E7752P05
			SFP-FE-SX-MM1310-A	E7752P05
			SFP-GE-LH100-SM1550	E7752P05
			SFP-GE-LH40-SM1310	E7752P05
			SFP-GE-LH40-SM1310-BIDI	E7752P05
			SFP-GE-LH40-SM1310-D	E7752P05
			SFP-GE-LH40-SM1550	E7752P05
			SFP-GE-LH40-SM1550-BIDI	E7752P05
			SFP-GE-LH70-SM1490-BIDI	E7752P05
			SFP-GE-LH70-SM1550-BIDI	E7752P05
			SFP-GE-LH80-SM1550	E7752P05
SFP-GE-LH80-SM1550-D	E7752P05			

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LX-SM1310-A	E7752P05
		SFP-GE-LX-SM1310-BIDI	E7752P05
		SFP-GE-LX-SM1310-D	E7752P05
		SFP-GE-LX-SM1310-S	E7752P05
		SFP-GE-LX-SM1490-BIDI	E7752P05
		SFP-GE-SX-MM850-A	E7752P05
		SFP-GE-SX-MM850-D	E7752P05
		SFP-GE-SX-MM850-S	E7752P05
		SFP-GE-T	E7752P05
		SFP-GE-T-D	E7752P05
		SFP-XG-LH40-SM1270-BIDI	E7752P05
		SFP-XG-LH40-SM1330-BIDI	E7752P05
		SFP-XG-LH40-SM1550	E7752P05
		SFP-XG-LH40-SM1550-D	E7752P05
		SFP-XG-LH80-SM1550	E7752P05
		SFP-XG-LH80-SM1550-D	E7752P05
		SFP-XG-LX-SM1270-BIDI	E7752P05
		SFP-XG-LX-SM1310-D	E7752P05
		SFP-XG-LX-SM1310-E	E7752P05
		SFP-XG-LX-SM1330-BIDI	E7752P05
		SFP-XG-SX-MM850-D	E7752P05
		SFP-XG-SX-MM850-E	E7752P05
		SFP-XG-SX-MM850-F1	E7752P05
LSEM1TGS24SD0	1~24	CAB-0.5M-SFP+	E7751P02, Cannot be used for IRF setup connections.
		CAB-1M-SFP+	E7751P02, Cannot be used for IRF setup connections.
		CAB-3M-SFP+	E7751P02, Cannot be used for IRF setup connections.
		LSTM1STK	E7751P02, Cannot be used for IRF setup connections.
		LSWM1STK	E7751P02, Cannot be used for IRF setup connections.
		LSWM2STK	E7751P02, Cannot be used for IRF setup connections.

单板名称	端口	支持的光模块	版本适配及说明
		LSWM3STK	E7751P02, Cannot be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	R7755P01
		SFP-FE-LX-SM1310-A	R7755P01
		SFP-FE-LX-SM1310-BIDI	R7755P01
		SFP-FE-LX-SM1310-D	R7755P01
		SFP-FE-LX-SM1550-BIDI	R7755P01
		SFP-FE-SX-MM1310-A	R7755P01
		SFP-GE-LH100-SM1550	E7751P02
		SFP-GE-LH40-SM1310	E7751P02
		SFP-GE-LH40-SM1310-BIDI	E7751P02
		SFP-GE-LH40-SM1310-D	E7751P02
		SFP-GE-LH40-SM1550	E7751P02
		SFP-GE-LH40-SM1550-BIDI	E7751P02
		SFP-GE-LH70-SM1490-BIDI	E7751P02
		SFP-GE-LH70-SM1550-BIDI	E7751P02
		SFP-GE-LH80-SM1550	E7751P02
		SFP-GE-LH80-SM1550-D	E7751P02
		SFP-GE-LX-SM1310-A	E7751P02
		SFP-GE-LX-SM1310-BIDI	E7751P02
		SFP-GE-LX-SM1310-D	E7751P02
		SFP-GE-LX-SM1310-S	E7751P02
		SFP-GE-LX-SM1490-BIDI	E7751P02
		SFP-GE-SX-MM850-A	E7751P02
		SFP-GE-SX-MM850-D	E7751P02
		SFP-GE-SX-MM850-S	E7751P02
		SFP-GE-T	E7751P02
		SFP-GE-T-D	E7751P02
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7751P02

单板名称	端口	支持的光模块	版本适配及说明		
		SFP-XG-LH40-SM1330-BIDI	E7751P02		
		SFP-XG-LH40-SM1550	E7751P02		
		SFP-XG-LH40-SM1550-D	E7751P02		
		SFP-XG-LH80-SM1490-BIDI	E7751P02		
		SFP-XG-LH80-SM1550	E7751P02		
		SFP-XG-LH80-SM1550-BIDI	E7751P02		
		SFP-XG-LH80-SM1550-D	E7751P02		
		SFP-XG-LX-SM1270-BIDI	E7751P02		
		SFP-XG-LX-SM1310	E7751P02		
		SFP-XG-LX-SM1310-D	E7751P02		
		SFP-XG-LX-SM1310-E	E7751P02		
		SFP-XG-LX-SM1330-BIDI	E7751P02		
		SFP-XG-SX-MM850-A	E7751P02		
		SFP-XG-SX-MM850-D	E7751P02		
		SFP-XG-SX-MM850-E	E7751P02		
		SFP-XG-SX-MM850-F1	E7751P02		
		LSEM1TGS48QSSF0	1~48	CAB-0.5M-SFP+	E7752P05
				CAB-1M-SFP+	E7752P05
CAB-3M-SFP+	E7752P05				
LSTM1STK	E7752P05				
LSWM1STK	E7752P05				
LSWM2STK	E7752P05				
LSWM3STK	E7752P05				
SFP-2.5G-LX10-SM1310-DR-I	R7755P01				
SFP-GE-LH100-SM1550	E7752P05				
SFP-GE-LH40-SM1310	E7752P05				
SFP-GE-LH40-SM1310-BIDI	E7752P05				
SFP-GE-LH40-SM1310-D	E7752P05				
SFP-GE-LH40-SM1550	E7752P05				
SFP-GE-LH40-SM1550-BIDI	E7752P05				
SFP-GE-LH70-SM1490-BIDI	E7752P05				
SFP-GE-LH70-SM1550-BIDI	E7752P05				

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LH80-SM1550	E7752P05
		SFP-GE-LH80-SM1550-D	E7752P05
		SFP-GE-LX-SM1310-A	E7752P05
		SFP-GE-LX-SM1310-BIDI	E7752P05
		SFP-GE-LX-SM1310-D	E7752P05
		SFP-GE-LX-SM1310-S	E7752P05
		SFP-GE-LX-SM1490-BIDI	E7752P05
		SFP-GE-SX-MM850-A	E7752P05
		SFP-GE-SX-MM850-D	E7752P05
		SFP-GE-SX-MM850-S	E7752P05
		SFP-GE-T	E7752P05
		SFP-GE-T-D	E7752P05
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7752P05
		SFP-XG-LH40-SM1330-BIDI	E7752P05
		SFP-XG-LH40-SM1550	E7752P05
		SFP-XG-LH40-SM1550-D	E7752P05
		SFP-XG-LH80-SM1550	E7752P05
		SFP-XG-LH80-SM1550-D	E7752P05
		SFP-XG-LX-SM1270-BIDI	E7752P05
		SFP-XG-LX-SM1310-D	E7752P05
		SFP-XG-LX-SM1310-E	E7752P05
		SFP-XG-LX-SM1310-S	E7752P05
		SFP-XG-LX-SM1330-BIDI	E7752P05
		SFP-XG-SX-MM850-D	E7752P05
		SFP-XG-SX-MM850-E	E7752P05
		SFP-XG-SX-MM850-F1	E7752P05
		SFP-XG-SX-MM850-S	E7752P05
	49~52	LSWM1QSTK0	E7752P05
		LSWM1QSTK1	E7752P05

单板名称	端口	支持的光模块	版本适配及说明
		LSWM1QSTK2	E7752P05
		LSWM1QSTK3	E7752P05
		LSWM1QSTK4	E7752P05
		LSWM1QSTK5	E7752P05
		QSFP-40G-BIDI-SR-MM850	E7752P05
		QSFP-40G-BIDI-WDM850	E7752P05
		QSFP-40G-CSR4-MM850	E7752P05
		QSFP-40G-D-AOC-10M	E7752P05
		QSFP-40G-D-AOC-20M	E7752P05
		QSFP-40G-D-AOC-7M	E7752P05
		QSFP-40G-ER4-WDM1300	E7752P05
		QSFP-40G-LR4L-WDM1300	E7752P05
		QSFP-40G-LR4-PSM1310	E7752P05
		QSFP-40G-LR4-WDM1300	E7752P05
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7752P05
LSEM1TGS48SD0	1~48	CAB-0.5M-SFP+	E7751P02, Cannot be used for IRF setup connections.
		CAB-1M-SFP+	E7751P02, Cannot be used for IRF setup connections.
		CAB-3M-SFP+	E7751P02, Cannot be used for IRF setup connections.
		LSTM1STK	E7751P02, Cannot be used for IRF setup connections.
		LSWM1STK	E7751P02, Cannot be used for IRF setup connections.
		LSWM2STK	E7751P02, Cannot be used for IRF setup connections.
		LSWM3STK	E7751P02, Cannot be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	R7755P01
		SFP-FE-LX-SM1310-A	R7755P01
		SFP-FE-LX-SM1310-BIDI	R7755P01
SFP-FE-LX-SM1310-D	R7755P01		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-FE-LX-SM1550-BIDI	R7755P01
		SFP-FE-SX-MM1310-A	R7755P01
		SFP-GE-LH100-SM1550	E7751P02
		SFP-GE-LH40-SM1310	E7751P02
		SFP-GE-LH40-SM1310-BIDI	E7751P02
		SFP-GE-LH40-SM1310-D	E7751P02
		SFP-GE-LH40-SM1550	E7751P02
		SFP-GE-LH40-SM1550-BIDI	E7751P02
		SFP-GE-LH70-SM1490-BIDI	E7751P02
		SFP-GE-LH70-SM1550-BIDI	E7751P02
		SFP-GE-LH80-SM1550	E7751P02
		SFP-GE-LH80-SM1550-D	E7751P02
		SFP-GE-LX-SM1310-A	E7751P02
		SFP-GE-LX-SM1310-BIDI	E7751P02
		SFP-GE-LX-SM1310-D	E7751P02
		SFP-GE-LX-SM1310-S	E7751P02
		SFP-GE-LX-SM1490-BIDI	E7751P02
		SFP-GE-SX-MM850-A	E7751P02
		SFP-GE-SX-MM850-D	E7751P02
		SFP-GE-SX-MM850-S	E7751P02
		SFP-GE-T	E7751P02
		SFP-GE-T-D	E7751P02
		SFP-XG-LH40-SM1270-BIDI	E7751P02
		SFP-XG-LH40-SM1330-BIDI	E7751P02
		SFP-XG-LH40-SM1550	E7751P02
		SFP-XG-LH40-SM1550-D	E7751P02
		SFP-XG-LH80-SM1490-BIDI	E7751P02
		SFP-XG-LH80-SM1550	E7751P02
		SFP-XG-LH80-SM1550-BIDI	E7751P02
		SFP-XG-LH80-SM1550-D	E7751P02
		SFP-XG-LX-SM1270-BIDI	E7751P02
		SFP-XG-LX-SM1310	E7751P02

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LX-SM1310-D	E7751P02
		SFP-XG-LX-SM1310-E	E7751P02
		SFP-XG-LX-SM1330-BIDI	E7751P02
		SFP-XG-SX-MM850-A	E7751P02
		SFP-XG-SX-MM850-D	E7751P02
		SFP-XG-SX-MM850-E	E7751P02
		SFP-XG-SX-MM850-F1	E7751P02
LSEM1YGS48CQSF0	1~48	CAB-0.5M-SFP+	E7751P03
		CAB-1M-SFP+	E7751P03
		CAB-3M-SFP+	E7751P03
		HK-SFP28-25G-850-DF-MM	E7753P1601
		LSTM1STK	E7751P03
		LSWM1STK	E7751P03
		LSWM2STK	E7751P03
		LSWM3STK	E7751P03
		SFP-25G-CSR-MM850	R7755P03
		SFP-25G-D-AOC-10M	E7751P03
		SFP-25G-D-AOC-20M	E7751P03
		SFP-25G-D-AOC-3M	E7751P03
		SFP-25G-D-AOC-5M	E7751P03
		SFP-25G-D-AOC-7M	E7751P03
		SFP-25G-D-CAB-1M	E7751P03
		SFP-25G-LR-SM1310	E7751P03
		SFP-25G-SR-MM850	E7751P03
		SFP-25G-SR-MM850-H	E805303
		SFP-GE-LH100-SM1550	E7751P03
		SFP-GE-LH40-SM1310	E7751P03
		SFP-GE-LH40-SM1310-BIDI	E7751P03
		SFP-GE-LH40-SM1310-D	E7751P03
		SFP-GE-LH40-SM1550	E7751P03
SFP-GE-LH40-SM1550-BIDI	E7751P03		
SFP-GE-LH70-SM1490-BIDI	E7751P03		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LH70-SM1550-BIDI	E7751P03
		SFP-GE-LH80-SM1550	E7751P03
		SFP-GE-LH80-SM1550-D	E7751P03
		SFP-GE-LX-SM1310-A	E7751P03
		SFP-GE-LX-SM1310-BIDI	E7751P03
		SFP-GE-LX-SM1310-D	E7751P03
		SFP-GE-LX-SM1310-S	E7751P03
		SFP-GE-LX-SM1490-BIDI	E7751P03
		SFP-GE-SX-MM850-A	E7751P03
		SFP-GE-SX-MM850-D	E7751P03
		SFP-GE-SX-MM850-S	E7751P03
		SFP-GE-T	E7751P03
		SFP-GE-T-D	E7751P03
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7751P03
		SFP-XG-LH40-SM1330-BIDI	E7751P03
		SFP-XG-LH40-SM1550	E7751P03
		SFP-XG-LH40-SM1550-D	E7751P03
		SFP-XG-LH80-SM1550	E7751P03
		SFP-XG-LH80-SM1550-D	E7751P03
		SFP-XG-LX-SM1270-BIDI	E7751P03
		SFP-XG-LX-SM1310	E7751P03
		SFP-XG-LX-SM1310-D	E7751P03
		SFP-XG-LX-SM1310-E	E7751P03
		SFP-XG-LX-SM1330-BIDI	E7751P03
		SFP-XG-SX-MM850-A	E7751P03
		SFP-XG-SX-MM850-D	E7751P03
		SFP-XG-SX-MM850-E	E7751P03
		SFP-XG-SX-MM850-F1	E7751P03
	13~44	SFP-25G-D-CAB-5M	E7751P03

单板名称	端口	支持的光模块	版本适配及说明
	49~52	HK-QSFP28-100G-850-DF-MM	E7753P1601
		LSWM1QSTK0	E7751P03
		LSWM1QSTK1	E7751P03
		LSWM1QSTK2	E7751P03
		LSWM1QSTK3	E7751P03
		LSWM1QSTK4	E7751P06
		LSWM1QSTK5	E7751P12
		QSFP-100G-4SFP-25G-CAB-1M	E7751P03
		QSFP-100G-4SFP-25G-CAB-3M	E7751P03
		QSFP-100G-CWDM4-SM1300-A	E7751P03
		QSFP-100G-D-AOC-10M	E7751P03
		QSFP-100G-D-AOC-20M	E7751P03
		QSFP-100G-D-AOC-7M	E7751P03
		QSFP-100G-D-CAB-1M	E7751P03
		QSFP-100G-D-CAB-3M	E7751P03
		QSFP-100G-ER4L-WDM1300	E7751P03
		QSFP-100G-eSR4-MM850	E7751P03
		QSFP-100G-LR4L-WDM1300	E7751P03
		QSFP-100G-LR4-WDM1300	E7751P03
		QSFP-100G-PSM4-SM1310	E7751P03
		QSFP-100G-SR4-MM850	E7751P03
		QSFP-100G-SR4-MM850-A	E7751P03
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	E7751P03
		QSFP-40G-BIDI-SR-MM850	E7751P03
		QSFP-40G-BIDI-WDM850	E7751P03
		QSFP-40G-CSR4-MM850	E7751P03
		QSFP-40G-D-AOC-10M	E7751P03
		QSFP-40G-D-AOC-20M	E7751P03
		QSFP-40G-D-AOC-7M	E7751P03
		QSFP-40G-ER4-WDM1300	E7751P03
		QSFP-40G-LR4L-WDM1300	E7751P03

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-LR4-PSM1310	E7751P03
		QSFP-40G-LR4-WDM1300	E7751P03
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7751P03
	9~48	SFP-25G-D-CAB-3M	E7751P03
LSEM2TGS16GP32SD0	1~16,33~48,17~32	SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	R7755P01
		SFP-FE-LX-SM1310-A	R7755P01
		SFP-FE-LX-SM1310-BIDI	R7755P01
		SFP-FE-LX-SM1310-D	R7755P01
		SFP-FE-LX-SM1550-BIDI	R7755P01
		SFP-FE-SX-MM1310-A	R7755P01
		SFP-GE-LH100-SM1550	R7754P10
		SFP-GE-LH40-SM1310	R7754P10
		SFP-GE-LH40-SM1310-BIDI	R7754P10
		SFP-GE-LH40-SM1310-D	R7754P10
		SFP-GE-LH40-SM1550	R7754P10
		SFP-GE-LH40-SM1550-BIDI	R7754P10
		SFP-GE-LH70-SM1490-BIDI	R7754P10
		SFP-GE-LH70-SM1550-BIDI	R7754P10
		SFP-GE-LH80-SM1550	R7754P10
		SFP-GE-LH80-SM1550-D	R7754P10
		SFP-GE-LX-SM1310-A	R7754P10
		SFP-GE-LX-SM1310-BIDI	R7754P10
		SFP-GE-LX-SM1310-D	R7754P10
		SFP-GE-LX-SM1310-S	R7754P10
		SFP-GE-LX-SM1490-BIDI	R7754P10
		SFP-GE-SX-MM850-A	R7754P10
		SFP-GE-SX-MM850-D	R7754P10
		SFP-GE-SX-MM850-S	R7754P10
		SFP-GE-T	R7754P10
SFP-GE-T-D	R7754P10		

单板名称	端口	支持的光模块	版本适配及说明
	17~32	CAB-0.5M-SFP+	R7754P10, Cannot be used for IRF setup connections.
		CAB-1M-SFP+	R7754P10, Cannot be used for IRF setup connections.
		CAB-3M-SFP+	R7754P10, Cannot be used for IRF setup connections.
		LSTM1STK	R7754P10, Cannot be used for IRF setup connections.
		LSWM1STK	R7754P10, Cannot be used for IRF setup connections.
		LSWM2STK	R7754P10, Cannot be used for IRF setup connections.
		LSWM3STK	R7754P10, Cannot be used for IRF setup connections.
		SFP-XG-LH40-SM1270-BIDI	R7754P10
		SFP-XG-LH40-SM1330-BIDI	R7754P10
		SFP-XG-LH40-SM1550	R7754P10
		SFP-XG-LH40-SM1550-D	R7754P10
		SFP-XG-LH80-SM1490-BIDI	R7754P10
		SFP-XG-LH80-SM1550	R7754P10
		SFP-XG-LH80-SM1550-BIDI	R7754P10
		SFP-XG-LH80-SM1550-D	R7754P10
		SFP-XG-LX-SM1270-BIDI	R7754P10
		SFP-XG-LX-SM1310	R7754P10
		SFP-XG-LX-SM1310-D	R7754P10
		SFP-XG-LX-SM1310-E	R7754P10
		SFP-XG-LX-SM1330-BIDI	R7754P10
		SFP-XG-SX-MM850-A	R7754P10
SFP-XG-SX-MM850-D	R7754P10		
SFP-XG-SX-MM850-E	R7754P10		
SFP-XG-SX-MM850-F1	R7754P10		
LSEM2TGS48SD0	1~48	CAB-0.5M-SFP+	E775309, Cannot be used for IRF setup connections.
		CAB-1M-SFP+	E775309, Cannot be used for IRF setup connections.
		CAB-3M-SFP+	E775309, Cannot be used for IRF setup connections.

单板名称	端口	支持的光模块	版本适配及说明
		LSTM1STK	E775309, Cannot be used for IRF setup connections.
		LSWM1STK	E775309, Cannot be used for IRF setup connections.
		LSWM2STK	E775309, Cannot be used for IRF setup connections.
		LSWM3STK	E775309, Cannot be used for IRF setup connections.
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-FE-LH40-SM1310	R7755P01
		SFP-FE-LX-SM1310-A	R7755P01
		SFP-FE-LX-SM1310-BIDI	R7755P01
		SFP-FE-LX-SM1310-D	R7755P01
		SFP-FE-LX-SM1550-BIDI	R7755P01
		SFP-FE-SX-MM1310-A	R7755P01
		SFP-GE-LH100-SM1550	E775309
		SFP-GE-LH40-SM1310	E775309
		SFP-GE-LH40-SM1310-BIDI	E775309
		SFP-GE-LH40-SM1310-D	E775309
		SFP-GE-LH40-SM1550	E775309
		SFP-GE-LH40-SM1550-BIDI	E775309
		SFP-GE-LH70-SM1490-BIDI	E775309
		SFP-GE-LH70-SM1550-BIDI	E775309
		SFP-GE-LH80-SM1550	E775309
		SFP-GE-LH80-SM1550-D	E775309
		SFP-GE-LX-SM1310-A	E775309
		SFP-GE-LX-SM1310-BIDI	E775309
		SFP-GE-LX-SM1310-D	E775309
		SFP-GE-LX-SM1310-S	E775309
		SFP-GE-LX-SM1490-BIDI	E775309
		SFP-GE-SX-MM850-A	E775309
		SFP-GE-SX-MM850-D	E775309
		SFP-GE-SX-MM850-S	E775309
		SFP-GE-T	E775309

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-T-D	E775309
		SFP-XG-LH40-SM1270-BIDI	E775309
		SFP-XG-LH40-SM1330-BIDI	E775309
		SFP-XG-LH40-SM1550	E775309
		SFP-XG-LH40-SM1550-D	E775309
		SFP-XG-LH80-SM1490-BIDI	E775309
		SFP-XG-LH80-SM1550	E775309
		SFP-XG-LH80-SM1550-BIDI	E775309
		SFP-XG-LH80-SM1550-D	E775309
		SFP-XG-LX-SM1270-BIDI	E775309
		SFP-XG-LX-SM1310	E775309
		SFP-XG-LX-SM1310-D	E775309
		SFP-XG-LX-SM1310-E	E775309
		SFP-XG-LX-SM1330-BIDI	E775309
		SFP-XG-SX-MM850-A	E775309
		SFP-XG-SX-MM850-D	E775309
		SFP-XG-SX-MM850-E	E775309
		SFP-XG-SX-MM850-F1	E775309
LSEM3CDQ2SF0	1~2	CAB-400G-QSFP-DD-2m	E7754P02
		LSWM1QSTK0	E7754P02
		LSWM1QSTK1	E7754P02
		LSWM1QSTK2	E7754P02
		QSFP-100G-CWDM4-SM1300-A	E7754P02
		QSFP-100G-D-AOC-10M	E7754P02
		QSFP-100G-D-AOC-20M	E7754P02
		QSFP-100G-D-AOC-7M	E7754P02
		QSFP-100G-D-CAB-1M	E7754P02
		QSFP-100G-D-CAB-3M	E7754P02
		QSFP-100G-D-CAB-5M	E7754P02
		QSFP-100G-ER4L-WDM1300	E7754P02
		QSFP-100G-eSR4-MM850	E7754P02
		QSFP-100G-LR4L-WDM1300	E7754P02

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-LR4-WDM1300	E7754P02
		QSFP-100G-PSM4-SM1310	E7754P02
		QSFP-100G-SR4-MM850	E7754P02
		QSFP-100G-SR4-MM850-A	E7754P02
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	E7754P02
		QSFP-40G-BIDI-SR-MM850	E7754P02
		QSFP-40G-BIDI-WDM850	E7754P02
		QSFP-40G-CSR4-MM850	E7754P02
		QSFP-40G-D-AOC-10M	E7754P02
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7754P02
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7754P02
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-ER4-WDM1300	E7754P02
		QSFP-40G-LR4L-WDM1300	E7754P02
		QSFP-40G-LR4-PSM1310	E7754P02
		QSFP-40G-LR4-PSM1310-A	E7754P02
		QSFP-40G-LR4-WDM1300	E7754P02
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7754P02
		QSFP56-200G-D-AOC-10m	R7755P01
		QSFP56-200G-D-AOC-20m	R7755P01
		QSFP56-200G-D-AOC-5m	R7755P01
		QSFP56-200G-D-AOC-7m	R7755P01
		QSFP56-200G-D-DAC-1m	R7755P01
		QSFP56-200G-D-DAC-2m	R7755P01
		QSFP56-200G-D-DAC-3m	R7755P01
		QSFP56-200G-FR4-WDM1300	E7755
		QSFP56-200G-SR4-MM850	E7755
		QSFPDD-400G-2QSFP56-200G-AOC-10m	R7755P01

单板名称	端口	支持的光模块	版本适配及说明
		QSFPDD-400G-2QSFP56-200G-AOC-20m	R7755P01
		QSFPDD-400G-2QSFP56-200G-AOC-30m	R7755P01
		QSFPDD-400G-2QSFP56-200G-AOC-50m	R7755P01
		QSFPDD-400G-2QSFP56-200G-AOC-5m	R7755P01
		QSFPDD-400G-2QSFP56-200G-AOC-7m	R7755P01
		QSFPDD-400G-FR4-WDM1300	R7755P01
		QSFPDD-400G-LR4-WDM1300-DC	R7755P01
		QSFPDD-400G-LR8-WDM1300	R7755P01
		QSFPDD-400G-SR8-MM850	E7754P02
LSEM3CGQ16SF0	1~16	LSWM1QSTK0	E7753P01
		LSWM1QSTK1	E7753P01
		LSWM1QSTK2	E7753P01
		LSWM1QSTK3	E7753P01
		LSWM1QSTK4	E7753P01
		LSWM1QSTK5	E7753P01
		QSFP-100G-4SFP-25G-CAB-1M	E7753P01
		QSFP-100G-4SFP-25G-CAB-3M	E7753P01
		QSFP-100G-4SFP-25G-CAB-5M	E7753P01
		QSFP-100G-BIDI-MM850	R7755P01
		QSFP-100G-CWDM4-SM1300-A	E7753P01
		QSFP-100G-D-AOC-10M	E7753P01
		QSFP-100G-D-AOC-20M	E7753P01
		QSFP-100G-D-AOC-7M	E7753P01
		QSFP-100G-D-CAB-1M	E7753P01
		QSFP-100G-D-CAB-3M	E7753P01
		QSFP-100G-D-CAB-5M	E7753P01
		QSFP-100G-ER4L-WDM1300	E7753P01
		QSFP-100G-eSR4-MM850	E7753P01
		QSFP-100G-LR4L-WDM1300	E7753P01

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-LR4-WDM1300	E7753P01
		QSFP-100G-PSM4-SM1310	E7753P01
		QSFP-100G-SR4-MM850	E7753P01
		QSFP-100G-SR4-MM850-A	E7753P01
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	E7753P01
		QSFP-40G-BIDI-SR-MM850	E7753P01
		QSFP-40G-BIDI-WDM850	E7753P01
		QSFP-40G-CSR4-MM850	E7753P01
		QSFP-40G-D-AOC-10M	E7753P01
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7753P01
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7753P01
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-ER4-WDM1300	E7753P01
		QSFP-40G-LR4L-WDM1300	E7753P01
		QSFP-40G-LR4-PSM1310	E7753P01
		QSFP-40G-LR4-WDM1300	E7753P01
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7753P01
LSEM3CGQ36SF0	1~36	LSWM1QSTK0	E7754P02
		LSWM1QSTK1	E7754P02
		LSWM1QSTK2	E7754P02
		LSWM1QSTK3	E7754P02
		LSWM1QSTK4	E7754P02
		LSWM1QSTK5	E7754P02
		QSFP-100G-4SFP-25G-CAB-1M	E7754P02
		QSFP-100G-4SFP-25G-CAB-3M	E7754P02
		QSFP-100G-4SFP-25G-CAB-5M	E7754P02
		QSFP-100G-BIDI-MM850	R7755P01
		QSFP-100G-CWDM4-SM1300-A	E7754P02

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-D-AOC-10M	E7754P02
		QSFP-100G-D-AOC-20M	E7754P02
		QSFP-100G-D-AOC-7M	E7754P02
		QSFP-100G-D-CAB-1M	E7754P02
		QSFP-100G-D-CAB-3M	E7754P02
		QSFP-100G-D-CAB-5M	E7754P02
		QSFP-100G-eSR4-MM850	E7754P02
		QSFP-100G-LR4L-WDM1300	E7754P02
		QSFP-100G-LR4-WDM1300	E7754P02
		QSFP-100G-PSM4-SM1310	E7754P02
		QSFP-100G-SR4-MM850	E7754P02
		QSFP-100G-SR4-MM850-A	E7754P02
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	E7754P02
		QSFP-40G-BIDI-SR-MM850	E7754P02
		QSFP-40G-BIDI-WDM850	E7754P02
		QSFP-40G-CSR4-MM850	E7754P02
		QSFP-40G-D-AOC-10M	E7754P02
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7754P02
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7754P02
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-ER4-WDM1300	E7754P02
		QSFP-40G-LR4L-WDM1300	E7754P02
		QSFP-40G-LR4-PSM1310	E7754P02
		QSFP-40G-LR4-PSM1310-A	E7754P02
		QSFP-40G-LR4-WDM1300	E7754P02
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7754P02
LSEM3QGS16SF0	1~16	LSWM1QSTK0	E7753P01
		LSWM1QSTK1	E7753P01

单板名称	端口	支持的光模块	版本适配及说明
		LSWM1QSTK2	E7753P01
		LSWM1QSTK3	E7753P01
		LSWM1QSTK4	E7753P01
		LSWM1QSTK5	E7753P01
		QSFP-40G-BIDI-SR-MM850	E7753P01
		QSFP-40G-BIDI-WDM850	E7753P01
		QSFP-40G-CSR4-MM850	E7753P01
		QSFP-40G-D-AOC-10M	E7753P01
		QSFP-40G-D-AOC-20M	E7753P01
		QSFP-40G-D-AOC-7M	E7753P01
		QSFP-40G-ER4-WDM1300	E7753P01
		QSFP-40G-LR4L-WDM1300	E7753P01
		QSFP-40G-LR4-PSM1310	E7753P01
		QSFP-40G-LR4-WDM1300	E7753P01
		QSFP-40G-LX4-WDM1300	R7753P05
		QSFP-40G-SR4-MM850	E7753P01
		LSEM3QGS36SF0	1~36
LSWM1QSTK1	E7754P02		
LSWM1QSTK2	E7754P02		
LSWM1QSTK3	E7754P02		
LSWM1QSTK4	E7754P02		
LSWM1QSTK5	E7754P02		
QSFP-40G-BIDI-SR-MM850	E7754P02		
QSFP-40G-BIDI-WDM850	E7754P02		
QSFP-40G-CSR4-MM850	E7754P02		
QSFP-40G-D-AOC-10M	E7754P02		
QSFP-40G-D-AOC-20M	E7754P02		
QSFP-40G-D-AOC-7M	E7754P02		
QSFP-40G-ER4-WDM1300	E7754P02		
QSFP-40G-LR4L-WDM1300	E7754P02		
QSFP-40G-LR4-PSM1310	E7754P02		
QSFP-40G-LR4-PSM1310-A	E7754P02		

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-LR4-WDM1300	E7754P02
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7754P02
LSEM3SUPA0	MANAGEMENT	SFP-GE-LH100-SM1550	E7753P01
		SFP-GE-LH40-SM1310	E7753P01
		SFP-GE-LH40-SM1310-D	E7753P01
		SFP-GE-LH40-SM1550	E7753P01
		SFP-GE-LH80-SM1550	E7753P01
		SFP-GE-LH80-SM1550-D	E7753P01
		SFP-GE-LX-SM1310-A	E7753P01
		SFP-GE-LX-SM1310-BIDI	E7753P01
		SFP-GE-LX-SM1310-D	E7753P01
		SFP-GE-LX-SM1310-S	E7753P01
		SFP-GE-LX-SM1490-BIDI	E7753P01
		SFP-GE-SX-MM850-A	E7753P01
		SFP-GE-SX-MM850-D	E7753P01
		SFP-GE-SX-MM850-S	E7753P01
LSEM3SUPB0	MANAGEMENT	SFP-GE-LH100-SM1550	E7753P01
		SFP-GE-LH40-SM1310	E7753P01
		SFP-GE-LH40-SM1310-D	E7753P01
		SFP-GE-LH40-SM1550	E7753P01
		SFP-GE-LH80-SM1550	E7753P01
		SFP-GE-LH80-SM1550-D	E7753P01
		SFP-GE-LX-SM1310-A	E7753P01
		SFP-GE-LX-SM1310-BIDI	E7753P01
		SFP-GE-LX-SM1310-D	E7753P01
		SFP-GE-LX-SM1310-S	E7753P01
		SFP-GE-LX-SM1490-BIDI	E7753P01
		SFP-GE-SX-MM850-A	E7753P01
		SFP-GE-SX-MM850-D	E7753P01
		SFP-GE-SX-MM850-S	E7753P01
LSEM3TGS48QSSF0	1~48	CAB-0.5M-SFP+	E7753P01

单板名称	端口	支持的光模块	版本适配及说明
		CAB-1M-SFP+	E7753P01
		CAB-3M-SFP+	E7753P01
		LSTM1STK	E7753P01
		LSWM1STK	E7753P01
		LSWM2STK	E7753P01
		LSWM3STK	E7753P01
		SFP-2.5G-LX10-SM1310-DR-I	R7755P01
		SFP-GE-LH100-SM1550	E7753P01
		SFP-GE-LH40-SM1310	E7753P01
		SFP-GE-LH40-SM1310-BIDI	E7753P01
		SFP-GE-LH40-SM1310-D	E7753P01
		SFP-GE-LH40-SM1550	E7753P01
		SFP-GE-LH40-SM1550-BIDI	E7753P01
		SFP-GE-LH70-SM1490-BIDI	E7753P01
		SFP-GE-LH70-SM1550-BIDI	E7753P01
		SFP-GE-LH80-SM1550	E7753P01
		SFP-GE-LH80-SM1550-D	E7753P01
		SFP-GE-LX-SM1310-A	E7753P01
		SFP-GE-LX-SM1310-BIDI	E7753P01
		SFP-GE-LX-SM1310-D	E7753P01
		SFP-GE-LX-SM1310-S	E7753P01
		SFP-GE-LX-SM1490-BIDI	E7753P01
		SFP-GE-SX-MM850-A	E7753P01
		SFP-GE-SX-MM850-D	E7753P01
		SFP-GE-SX-MM850-S	E7753P01
		SFP-GE-T	E7753P01
		SFP-GE-T-D	E7753P01
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7753P01
		SFP-XG-LH40-SM1330-BIDI	E7753P01

单板名称	端口	支持的光模块	版本适配及说明
		SFP-XG-LH40-SM1550	E7753P01
		SFP-XG-LH40-SM1550-D	E7753P01
		SFP-XG-LH80-SM1550	E7753P01
		SFP-XG-LH80-SM1550-D	E7753P01
		SFP-XG-LX-SM1270-BIDI	E7753P01
		SFP-XG-LX-SM1310-D	E7753P01
		SFP-XG-LX-SM1310-E	E7753P01
		SFP-XG-LX-SM1310-S	E7753P01
		SFP-XG-LX-SM1330-BIDI	E7753P01
		SFP-XG-SX-MM850-D	E7753P01
		SFP-XG-SX-MM850-E	E7753P01
		SFP-XG-SX-MM850-F1	E7753P01
		SFP-XG-SX-MM850-S	E7753P01
		49~52	LSWM1QSTK0
	LSWM1QSTK1		E7753P01
	LSWM1QSTK2		E7753P01
	LSWM1QSTK3		E7753P01
	LSWM1QSTK4		E7753P01
	LSWM1QSTK5		E7753P01
	QSFP-40G-BIDI-SR-MM850		E7753P01
	QSFP-40G-BIDI-WDM850		E7753P01
QSFP-40G-CSR4-MM850	E7753P01		
QSFP-40G-D-AOC-10M	E7753P01		
QSFP-40G-D-AOC-10M-H	R7755P01		
QSFP-40G-D-AOC-20M	E7753P01		
QSFP-40G-D-AOC-20M-H	R7755P01		
QSFP-40G-D-AOC-7M	E7753P01		
QSFP-40G-D-AOC-7M-H	R7755P01		
QSFP-40G-ER4-WDM1300	E7753P01		
QSFP-40G-LR4L-WDM1300	E7753P01		
QSFP-40G-LR4-PSM1310	E7753P01		
QSFP-40G-LR4-WDM1300	E7753P01		

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7753P01
LSEM3YGS48CQSF0	1~48	CAB-0.5M-SFP+	E7753P01
		CAB-1M-SFP+	E7753P01
		CAB-3M-SFP+	E7753P01
		LSTM1STK	E7753P01
		LSWM1STK	E7753P01
		LSWM2STK	E7753P01
		LSWM3STK	E7753P01
		SFP-25G-CSR-MM850	R7755P03
		SFP-25G-D-AOC-10M	E7753P01
		SFP-25G-D-AOC-20M	E7753P01
		SFP-25G-D-AOC-3M	E7753P01
		SFP-25G-D-AOC-5M	E7753P01
		SFP-25G-D-AOC-7M	E7753P01
		SFP-25G-D-CAB-1M	E7753P01
		SFP-25G-LR-SM1310	E7753P01
		SFP-25G-SR-MM850	E7753P01
		SFP-25G-SR-MM850-H	E805303
		SFP-GE-LH100-SM1550	E7753P01
		SFP-GE-LH40-SM1310	E7753P01
		SFP-GE-LH40-SM1310-BIDI	E7753P01
		SFP-GE-LH40-SM1310-D	E7753P01
		SFP-GE-LH40-SM1550	E7753P01
		SFP-GE-LH40-SM1550-BIDI	E7753P01
		SFP-GE-LH70-SM1490-BIDI	E7753P01
		SFP-GE-LH70-SM1550-BIDI	E7753P01
		SFP-GE-LH80-SM1550	E7753P01
		SFP-GE-LH80-SM1550-D	E7753P01
		SFP-GE-LX-SM1310-A	E7753P01
SFP-GE-LX-SM1310-BIDI	E7753P01		
SFP-GE-LX-SM1310-D	E7753P01		

单板名称	端口	支持的光模块	版本适配及说明
		SFP-GE-LX-SM1310-S	E7753P01
		SFP-GE-LX-SM1490-BIDI	E7753P01
		SFP-GE-SX-MM850-A	E7753P01
		SFP-GE-SX-MM850-D	E7753P01
		SFP-GE-SX-MM850-S	E7753P01
		SFP-GE-T	E7753P01
		SFP-GE-T-D	E7753P01
		SFP-XG-D-AOC-10M-H	R7755P01
		SFP-XG-D-AOC-20M-H	R7755P01
		SFP-XG-D-AOC-7M-H	R7755P01
		SFP-XG-LH40-SM1270-BIDI	E7753P01
		SFP-XG-LH40-SM1330-BIDI	E7753P01
		SFP-XG-LH40-SM1550	E7753P01
		SFP-XG-LH40-SM1550-D	E7753P01
		SFP-XG-LH80-SM1550	E7753P01
		SFP-XG-LH80-SM1550-D	E7753P01
		SFP-XG-LX-SM1270-BIDI	E7753P01
		SFP-XG-LX-SM1310	E7753P01
		SFP-XG-LX-SM1310-D	E7753P01
		SFP-XG-LX-SM1310-E	E7753P01
		SFP-XG-LX-SM1330-BIDI	E7753P01
		SFP-XG-SX-MM850-A	E7753P01
		SFP-XG-SX-MM850-D	E7753P01
		SFP-XG-SX-MM850-E	E7753P01
	13~44	SFP-25G-D-CAB-5M	E7753P01
	49~52	LSWM1QSTK0	E7753P01
		LSWM1QSTK1	E7753P01
		LSWM1QSTK2	E7753P01
		LSWM1QSTK3	E7753P01
		LSWM1QSTK4	E7753P01
		LSWM1QSTK5	E7753P01
		QSFP-100G-4SFP-25G-CAB-1M	E7753P01

单板名称	端口	支持的光模块	版本适配及说明
		QSFP-100G-4SFP-25G-CAB-3M	E7753P01
		QSFP-100G-CWDM4-SM1300-A	E7753P01
		QSFP-100G-D-AOC-10M	E7753P01
		QSFP-100G-D-AOC-20M	E7753P01
		QSFP-100G-D-AOC-7M	E7753P01
		QSFP-100G-D-CAB-1M	E7753P01
		QSFP-100G-D-CAB-3M	E7753P01
		QSFP-100G-ER4L-WDM1300	E7753P01
		QSFP-100G-eSR4-MM850	E7753P01
		QSFP-100G-LR4L-WDM1300	E7753P01
		QSFP-100G-LR4-WDM1300	E7753P01
		QSFP-100G-PSM4-SM1310	E7753P01
		QSFP-100G-SR4-MM850	E7753P01
		QSFP-100G-SR4-MM850-A	E7753P01
		QSFP-100G-SR4-MM850-H	E805303
		QSFP-100G-SWDM4-MM850	E7753P01
		QSFP-40G-BIDI-SR-MM850	E7753P01
		QSFP-40G-BIDI-WDM850	E7753P01
		QSFP-40G-CSR4-MM850	E7753P01
		QSFP-40G-D-AOC-10M	E7753P01
		QSFP-40G-D-AOC-10M-H	R7755P01
		QSFP-40G-D-AOC-20M	E7753P01
		QSFP-40G-D-AOC-20M-H	R7755P01
		QSFP-40G-D-AOC-7M	E7753P01
		QSFP-40G-D-AOC-7M-H	R7755P01
		QSFP-40G-ER4-WDM1300	E7753P01
		QSFP-40G-LR4L-WDM1300	E7753P01
		QSFP-40G-LR4-PSM1310	E7753P01
		QSFP-40G-LR4-WDM1300	E7753P01
		QSFP-40G-LX4-WDM1300	R7754P10
		QSFP-40G-SR4-MM850	E7753P01
	9~48	SFP-25G-D-CAB-3M	E7753P01

