

知 h3c icg 1000WEB密码忘记了

PPP

zhiliao_43321

2017-12-01 发表

组网及说明

h3c icg 1000 路由器WEB密码忘记了要怎么恢复，恢复后默认的用户名密码是多少？

问题描述

h3c icg 1000 路由器WEB密码忘记了要怎么恢复，恢复后默认的用户名密码是多少？

解决方法

应该是ACG1000，不是路由器哦，是应用控制网关设备。ACG1000的web登录密码和console密码一致，密码找回可参考：

第一步：重启设备，在console口上立刻按住ctrl+B，进入如下boot界面：

Bootloader V1.4.1(Build time: Aug 18 2014 - 14:12:35)

Flash: 4 MB

Press Ctrl+C to stop auto start : 03

Semptian cn50MC1100#

Semptian cn50MC1100#

Semptian cn50MC1100#

第二步：输入run menuboot_cf命令，从CF卡中运行menuboot程序：

Semptian cn50MC1100# run menuboot_cf

.....

[71.764985] EXT3-fs: sdb: couldn't mount because of unsupported optional features (240).

***** Please use the interface to communicate ge0*****

```
=====
|      BOOT MENU(V2.0-20150126)      |
| 1. Upgrade image by FTP.           |
| 2. Upgrade menuboot by FTP.        |
| 3. Check and repare file system.   |
| 4. Reset administrator passowrd.   |
| 5. Producing test.                 |
| 6. Aging test.                     |
| 7. Display production and aging recored. |
| 8. Advance functions.              |
| 0. Reboot.                         |
|                                   |
|                                   |
=====
```

第三步：选择4重置用户名密码

Please input your choice[0-8]:4

Rest admin password success.

第四步：选择0重启设备

```
=====
|      BOOT MENU(V2.0-20150126)      |
| 1. Upgrade image by FTP.           |
| 2. Upgrade menuboot by FTP.        |
| 3. Check and repare file system.   |
| 4. Reset administrator passowrd.   |
| 5. Producing test.                 |
| 6. Aging test.                     |
| 7. Display production and aging recored. |
| 8. Advance functions.              |
| 0. Reboot.                         |
|                                   |
|                                   |
=====
```

Please input your choice[0-8]:0

Sent SIGKILL to all processes

Requesting system reboot

建议咨询相关售后再执行

--	--

