

组网及说明

为了进一步保证设备安全，需配置ACL对高危端口进行拦截。

S1850版本信息如下：

H3C Comware Platform Software

Comware Software, Version 5.20.99, Release 1102

Copyright (c) 2004-2017 New H3C Technologies Co., Ltd. All rights reserved.

H3C S1850-28P uptime is 0 week, 5 days, 6 hours, 8 minutes

H3C S1850-28P

128M bytes DRAM

32M bytes Flash Memory

Config Register points to Flash

Hardware Version is Ver.A

Bootrom Version is 102

[SubSlot 0] 24GE+4SFP Hardware Version is Ver.A

配置步骤

1、创建ACL，对高危端口进行拦截：

```
acl number 3210
```

```
rule 0 deny tcp destination-port eq 135
```

```
rule 1 deny udp destination-port eq 135
```

```
rule 2 deny tcp destination-port eq 137
```

```
rule 3 deny udp destination-port eq netbios-ns
```

```
rule 4 deny tcp destination-port eq 138
```

```
rule 5 deny udp destination-port eq netbios-dgm
```

```
rule 6 deny udp destination-port eq netbios-ssn
```

```
rule 7 deny tcp destination-port eq 139
```

```
rule 8 deny tcp destination-port eq 445
```

```
rule 9 deny udp destination-port eq 445
```

```
rule 10 deny tcp destination-port eq 3389
```

```
rule 11 deny udp destination-port eq 3389
```

```
rule 20 deny tcp source-port eq 135
```

```
rule 21 deny udp source-port eq 135
```

```
rule 22 deny tcp source-port eq 137
```

```
rule 23 deny udp source-port eq netbios-ns
```

```
rule 24 deny tcp source-port eq 138
```

```
rule 25 deny udp source-port eq netbios-dgm
```

```
rule 26 deny udp source-port eq netbios-ssn
```

```
rule 27 deny tcp source-port eq 139
```

```
rule 28 deny tcp source-port eq 445
```

```
rule 29 deny udp source-port eq 445
```

```
rule 30 deny tcp source-port eq 3389
```

```
rule 31 deny udp source-port eq 3389
```

```
rule 1500 permit ip
```

2、将ACL下发到端口：

```
int range gi 1/0/1 gi 1/0/24
```

```
packet-filter 3210 inbound
```

```
packet-filter 3210 outbound
```

```
quit
```

配置关键点