

知 某局点 UIS 升级预检查失败

刘伟 2021-01-11 发表

组网及说明

无

问题描述

某局点UIS需要执行升级操作，由E0715升级至E0716，升级之后查看UIS版本为E0716，后台查看onestor版本为R2130（正常升级之后E0716配套版本为R2130P01），发现onestor版本升级未完成，准备再次执行升级操作，执行升级预检查之后提示报错：

```
httpd not running, trying to start
apache2
Apache server is running
ERROR: offline upgrade is executing
[ERROR] Pre-check the status of ONEStor environment failed!
[DEBUG] Onestor precheck,recovery environment,change port to 10001.
apache2
Stopping Apache ..... [OK]
apache2
Gracefully restarting apache2: httpd not running, trying to start
apache2
Apache server is running
warning: Permanently added '10.82.248.116' (ECDSA) to the list of known hosts.
apache2
Stopping Apache ..... [OK]
apache2
Gracefully restarting apache2: httpd not running, trying to start
httpd not running, trying to start
apache2
Apache server is running
[ERROR] Pre-check ONEStor has not pass!
[root@B12-UIS-server-01 upgrade.e0716]#
```

过程分析

- 1、查看前台各存储是否暂停（包含共享存储和模板存储）
- 2、按照升级指导书中的常见问题进行解决
 - (1) 在主节点执行以下命令，手动清除标记文件。 echo 0 > /opt/h3c/upd/updflag/nodeFile
 - (2) 再次执行离线升级预检查。

执行完成之后仍然如上图报错 //正常执行完这一步之后预检查就能通过

- 3、若执行上述两步仍然无法预检查通过，执行下面的操作

- (1) 进入升级包中，ls -al查看升级包

```
[root@B12-UIS-server-01 upgrade.e0716]#  
[root@B12-UIS-server-01 upgrade.e0716]# ls 0al  
ls: cannot access 0al: No such file or directory  
[root@B12-UIS-server-01 upgrade.e0716]# ls -al  
total 252  
drwxr-xr-x 3 root root 4096 Dec 31 01:26 .  
dr-xr-x--- 7 root root 4096 Dec 31 01:25 ..  
-rw-r--r-- 1 root root 1588 Aug 8 16:05 .cas_upgrade_errorcodes  
-rwx--x--x 1 root root 16560 Aug 8 16:05 lich_upgrade.sh.x  
drwxr-xr-x 3 root root 4096 Dec 31 01:25 package  
-fw-r--r-- 1 root root 31 Dec 31 01:52 .precheck_onestor_result.txt  
-fw-r--r-- 1 root root 49 Aug 8 16:05 README.txt  
-rwxr-xr-x 1 root root 99 Aug 8 16:05 uis_upgrade.sh  
-rwx--x--x 1 root root 57048 Aug 8 16:05 uis_upgrade.sh.x  
-rwx--x--x 1 root root 15976 Aug 8 16:05 ump_upgrade.sh.x  
-rwxr-xr-x 1 root root 7017 Aug 8 16:05 upgrade-cvks.pyc  
-rwxr-xr-x 1 root root 148 Aug 8 16:05 upgrade.sh  
-rwx--x--x 1 root root 97328 Aug 8 16:05 upgrade.sh.x  
-rwxr-xr-x 1 root root 36 Aug 8 16:05 upgrade-slave_cvm.sh  
-rwx--x--x 1 root root 15648 Aug 8 16:05 upgrade-slave_cvm.sh.x  
-rwxr-xr-x 1 root root 248 Aug 8 16:05 upgrade-special_cvk.sh  
[root@B12-UIS-server-01 upgrade.e0716]#  
[root@B12-UIS-server-01 upgrade.e0716]#
```

- (2) 找到.precheck_onestor_result.txt的文件，进行删除

```
01:26 .  
01:25 ..  
16:05 .cas_upgrade_errorcodes  
16:05 lich_upgrade.sh.x  
01:25 package  
01:52 .precheck_onestor_result.txt  
16:05 README.txt  
16:05 uis_upgrade.sh  
16:05 uis_upgrade.sh.x  
16:05 ump_upgrade.sh.x  
16:05 upgrade-cvks.pyc  
16:05 upgrade.sh  
16:05 upgrade.sh.x  
16:05 upgrade-slave_cvm.sh  
16:05 upgrade-slave_cvm.sh.x  
16:05 upgrade-special_cvk.sh  
6]#  
-1#
```

- (3) 删除之后重复12两步操作

解决方法

删除或移动

```
check_onestor_result.txt
```

的文件（该文件记录了升级预检查是出现的预检查结果，正常情况下不会影响到预检查失败）

若参照该方法无法解决，请联系技术工程师。

