

知 S7503X 配置远程镜像vlan多目的端口在目的设备抓包只有单向流量

镜像 李敏 2021-12-14 发表

组网及说明

无

问题描述

配置远程镜像vlan多目的端口在目的设备抓包只有出方向流量，没有进方向流

过程分析

dis mirroring-group 1 Mirroring group 1: Type: Remote source Status: Active Mirroring port: Ten-GigabitEthernet1/2/0/37 Both Reflector port: Ten-GigabitEthernet1/2/0/27 Remote probe VLAN: 4093 dis v
lan 4093 VLAN ID: 4093 VLAN type: Static Route interface: Configured Description: mirroring-vlan Na
me: VLAN 4093 Tagged ports: None Untagged ports: Ten-GigabitEthernet1/2/0/25 Ten-
GigabitEthernet1/2/0/26 Ten-GigabitEthernet1/2/0/28 # interface Ten-GigabitEthernet1/2/0/27 port lin
k-mode bridge description mirroring-group 1 reflector-port mirroring-group 1 reflector-port # interface
Vlan-interface4093 # 有配置interface Vlan-interface4093

解决方法

删除掉interface Vlan-interface4093

