

问题描述

ADCampus6.3前台页面登录卡顿，服务器后台查看磁盘时延很高

```
[root@device-ucenter01 ~]#  
[root@device-ucenter01 ~]#  
[root@device-ucenter01 ~]# iostat -d /dev/sdb1 -m -x 1  
Linux 3.10.0-957.27.2.el7.x86_64 (device-ucenter01) 2023年02月05日 _x86_64_ (64 CPU)  
Device:            rrqm/s    wrqm/s      r/s      w/s    rMB/s    wMB/s avgrq-sz avgqu-sz  await  r_await  w_await  svctm  %util  
sdb1                0.00      0.00      0.00    35.60     0.00     0.21  11.97     0.02   0.55   3.76     0.55   0.18   0.63  
  
Device:            rrqm/s    wrqm/s      r/s      w/s    rMB/s    wMB/s avgrq-sz avgqu-sz  await  r_await  w_await  svctm  %util  
sdb1                0.00      0.00      0.00     2.00     0.00     0.01   8.00     2.93  928.50   0.00  928.50  500.50  100.10  
  
Device:            rrqm/s    wrqm/s      r/s      w/s    rMB/s    wMB/s avgrq-sz avgqu-sz  await  r_await  w_await  svctm  %util  
sdb1                0.00      0.00      0.00    10.00     0.00     0.11  21.60     6.23  695.50   0.00  695.50  100.00  100.00  
  
Device:            rrqm/s    wrqm/s      r/s      w/s    rMB/s    wMB/s avgrq-sz avgqu-sz  await  r_await  w_await  svctm  %util  
sdb1                0.00      0.00      0.00     9.00     0.00     0.07  15.11     7.23  825.22   0.00  825.22  111.00   99.90  
  
Device:            rrqm/s    wrqm/s      r/s      w/s    rMB/s    wMB/s avgrq-sz avgqu-sz  await  r_await  w_await  svctm  %util  
sdb1                0.00      0.00      0.00     2.00     0.00     0.01   8.00     1.55  800.00   0.00  800.00  500.00  100.00  
  
^C  
[root@device-ucenter01 ~]#
```

查看CC和PR的状态正在执行，处于active状态，如何关闭？

```
[root@device-ucenter01 ~]#  
[root@device-ucenter01 ~]# uptime  
17:44:29 up 447 days, 3:37, 3 users, load average: 100.42, 91.08, 90.68  
[root@device-ucenter01 ~]# sudo /opt/MegaRAID/storcli/storcli64 /call show cc  
CLI Version = 007.1705.0000.0000 Mar 31, 2021  
Operating system = Linux 3.10.0-957.27.2.el7.x86_64  
Controller = 0  
Status = Success  
Description = None  
  
Controller Properties :  
=====  
  
-----  
Ctrl_Prop          Value  
-----  
CC Operation Mode   Concurrent  
CC Execution Delay   168 hours  
CC Next Starttime   02/04/2023, 03:00:00  
CC Current State     Active  
CC Number of iterations 72  
CC Number of VD completed 1  
CC Excluded VDs     None  
-----
```

```
[root@device-ucenter01 ~]# sudo /opt/MegaRAID/storcli/storcli64 /call show pr  
CLI Version = 007.1705.0000.0000 Mar 31, 2021  
Operating system = Linux 3.10.0-957.27.2.el7.x86_64  
Controller = 0  
Status = Success  
Description = None  
  
Controller Properties :  
=====  
  
-----  
Ctrl_Prop          Value  
-----  
PR Mode            Auto  
PR Execution Delay  168 hours  
PR Iterations completed 72  
PR Next Start time  02/04/2023, 03:00:00  
PR on SSD           Disabled  
PR Current State    Active 0  
PR Excluded VDs     None  
PR MaxConcurrentPd 248  
-----
```

解决方法

如果发现CC和PR的状态是running/active的状态，可以参考如下命令暂时停止

```
/opt/MegaRAID/storcli/storcli64 /c0 stop patrolread
```

```
/opt/MegaRAID/storcli/storcli64 /call /vall stop cc
```

