

知 3par升级固件后admithw报错的处理方法 (报错内容是Checking if the rights assigned to extended roles need to be updated... Permission denied)

存储系统 高阳 2023-09-19 发表

问题描述

3par升级固件后admithw报错的处理方法 (报错内容是Checking if the rights assigned to extended roles need to be updated... Permission denied)

过程分析

通过分析日志来看是报用户也就是3paradm的权限不足导致admithw失败

通过搜索发现和这个cfi吻合CFI: 23047 admithw fails with "Permission denied" when 3paradm used for creatorole/setrole updates

cli% admithw Checking nodes...

Checking volumes...

Checking system LDs... Checking ports...

Checking state of disks...

Checking for drive table upgrade packages Checking cabling...

Checking cage firmware...

Checking if this is an upgrade that added new types of drives...

Checking for disks to admit...

Checking for drive table upgrade packages 0 disks admitted

Checking admin volume... Admin volume exists.

Checking if logging LDs need to be created... No new logging LDs need to be created Checking if preserved data LDs need to be created... No new preserved data LDs need to be created Checking if system scheduled tasks need to be created...

Checking if the rights assigned to extended roles need to be updated... Permission denied

解决方法

workaround:

先用root登陆后执行admithw后，再用3paradm登陆执行admithw问题解决

根除此问题根据cfi介绍需要升级到3.3.1ga版本

