

配置步骤

方法一：保存到AC本地：

```
# 在flash:/archive/目录下备份配置文件，文件名前缀为my_archive.  
<Sysname> mkdir flash:/archive // 创建一个archive的文件夹  
Creating directory flash:/archive... Done.  
<Sysname> system-view  
[Sysname] archive configuration location flash:/archive filename-prefix my_archive // 配置路径即可  
<WX5540H>archive configuration // 需要现在 [ ] 视图下配置 archive configuration 才能在<>视图  
下用  
The running configuration will be saved to an archive file. Continue? [Y/N]:y  
The archive configuration file my_archive_1.cfg is saved.
```

方法二：保存到远程电脑，需要开启FTP / TFTP服务器

```
[WX5540H]archive configuration server tftp 192.168.100.100 filename-prefix test // test是文件前缀名  
<WX5540H>archive configuration  
The running configuration will be saved to an archive file. Continue? [Y/N]:y  
The archive configuration file test_20231115_144020.cfg is saved.
```

通用操作方法：

查看配置

```
<WX5540H>dis archive configuration  
Location: tftp://192.168.100.100/  
Filename prefix: test  
Archive history:  
No. TimeStamp      FileName  
! 1 Wed Nov 15 14:26:38 2023 test_20231115_142638.cfg  
# 2 Wed Nov 15 14:40:20 2023 test_20231115_144020.cfg  
The exclamation mark (!) indicate that the remote archiving attempt failed.  
The pound sign (#) indicates the most recent archive file.
```

Tips:

```
[WX5540H]archive configuration server user xx // 用户名  
[WX5540H]archive configuration server password xx // 密码  
[WX5540H]archive configuration interval xx // 自动备份时间  
[WX5540H]archive configuration server tftp 192.168.100.100 directory /home/admins/h3c/  
filename-prefix test // 配置文件路径，需要相对路径
```

