

CloudOS E5132P03H05升级组件失败, 提示部署失败, 事件描述提示: Failed to upload image



后台查看 sys-app 容器日志，发现报错跟harbor证书有关系：

确认了下harbor证书时间发现，harbor证书过期了

参考附件文档进行harbor证书续期操作。

(注: harbor证书续期时执行续期脚本一直报错, 提示 resource ware provided, but no name, label selector. or --all flag specified

```

cloudos-harbor-E5132-certificate-upgrade]#
cloudos-harbor-E5132-certificate-upgrade]# sh cloudos-certificate-upgrade.sh
[Step 1]: Starting convert harbor nginx certificates...
configmap/harbor-nginx-config replaced
[Step 2]: Restart harbor nginx services
error: resource(s) were provided, but no name, label selector, or --all flag specified
cloudos-harbor-E5132-certificate-upgrade]#
cloudos-harbor-E5132-certificate-upgrade]#
cloudos-harbor-E5132-certificate-upgrade]# bash cloudos-certificate-upgrade.sh
[Step 1]: Starting convert harbor nginx certificates...
configmap/harbor-nginx-config replaced
[Step 2]: Restart harbor nginx services
error: resource(s) were provided, but no name, label selector, or --all flag specified
cloudos-harbor-E5132-certificate-upgrade]#
cloudos-harbor-E5132-certificate-upgrade]#

```

原因：脚本问题，oc 命令的 project 不在default命令空间

解决方法：在执行脚本前先执行下 oc project default 就行了：

```

1010 2024-01-06 02:35:32 oc get cm
1011 2024-01-06 02:35:00 oc project default
1012 2024-01-06 02:35:03 oc get cm

```

附件下载：Harbor证书延期脚本.rar