

知 HPE Virtual Connect 密码长度无法修改为小于8位的处理方法

VC Virtual Connect 尹东江 2017-12-21 发表

某局点用户咨询将Virtual Connect 用户密码设置为4位时，总是提示报错“8-40 alphanumeric and special characters”，无法设置成功，希望确认如何设置低于8位的密码；

有报错提示：“8-40 alphanumeric and special characters”，无法输入4位密码：
例如新建用户名“hello”，密码为“1234”，就会提示输入不正确

Add Local User

User Information

Username: * hello
1 - 31 alphanumeric characters including - and _.

Password: * ****
8 - 40 alphanumeric and special characters.

Confirm Password: * ****
Must match password.

Full Name:
0 - 63 alphanumeric characters.

Contact Info:
0 - 127 alphanumeric and special characters.

Roles:

- Domain
- Network
- Server
- Storage

Operations for selected Role(s):

- Firmware Update (VCSU)
- Save Domain Configuration
- Restore Domain Configuration
- Export Support Files
- Port Monitoring

Virtual Connect 密码默认为8位，因此小于8位提示输入不正确，可以尝试在Advanced User Account Settings 中修改默认密码最小位数。

在Virtual Connect 的Local users 中找到Advanced User Account Settings ，进入password policy ,修改密码位数，例如将最小密码位数设置为4位，点击“Apply”应用。

Advanced User Account Settings

Password Policy

Require Strong Passwords

Minimum Password Length: 4 (3 - 40 characters)

设置后再次进入Local User Accounts界面，点击“ADD”添加用户“hello”密码为“1234”成功。

Add Local User

User Information

Username: *
1 - 31 alphanumeric characters including - and _.

Password: *
4 - 40 alphanumeric and special characters.

Confirm Password: *
Must match password.

Full Name:
0 - 63 alphanumeric characters.

Contact Info:
0 - 127 alphanumeric and special characters.

1. 如果需要设置小于8位的密码，修改密码前需要先在Virtual Connect 中修改最小密码位数；
2. 如果在Virtual Connect 中勾选了Require Strong Passwords 选项，则密码最小需要8位，无法修改为更小。

Password Policy

Require Strong Passwords 

Minimum Password Length   (3 - 40 characters)