

### 问题描述

承载控制器纳管的路由器，一致在刷带有ERROR的错误日志

```
0: 'IfCategoryPolicyRun' under element '/rpc/get/filter/top/MQC'  
%Aug 21 2024 08:00:00: %E01 XMLAGENT/6/XML_SCHEMA_ERROR: schema check failed.Unexpected element 'http://www.h3c.com/netconf/data:1:  
0: 'SDWAN' under element '/rpc/get/filter/top'  
%Aug 21 2024 08:00:00: %E01 XMLAGENT/6/XML_SCHEMA_ERROR: schema check failed.Unexpected element 'http://www.h3c.com/netconf/data:1:  
0: 'SDWAN' under element '/rpc/get/filter/top'  
%Aug 21 2024 08:00:00: %E01 XMLAGENT/6/XML_SCHEMA_ERROR: schema check failed.Unexpected element 'http://www.h3c.com/netconf/data:1:  
0: 'RIR' under element '/rpc/get/filter/top'  
%Aug 21 2024 08:00:00: %E01 XMLAGENT/6/XML_SCHEMA_ERROR: schema check failed.Unexpected element 'http://www.h3c.com/netconf/data:1:  
0: 'ospfv3' under element '/rpc/get/filter/top'  
%Aug 21 2024 08:00:00: %E01 XMLAGENT/6/XML_SCHEMA_ERROR: schema check failed.Unexpected element 'http://www.h3c.com/netconf/data:1:  
0: 'SilentInterfaces' under element '/rpc/get/filter/top/OSPF'  
%Aug 21 2024 08:00:00: %E01 XMLAGENT/6/XML_SCHEMA_ERROR: schema check failed.Unexpected element 'http://www.h3c.com/netconf/data:1:  
0: 'SilentAllInterfaces' under element '/rpc/get/filter/top/OSPF'
```

### 过程分析

现场分析器采用了netconf采集，存在多余的配置，承载场景路由器未进行配置/不存在该功能导致提示unexpected element 报错。

### 解决方法

采集模版里可以去掉

MQC\_IfCategoryPolicyRun RIR\_RirTuneIQuality SDWAN\_SdwanSiteTte SDWAN\_SdwanTteConnections IETF\_ospfv3\_instance\_private OSPF\_SilentAllInterfaces OSPF\_SilentInterfaces