

### 问题描述

交换机每隔10分钟就会报如下日志:

```
dis logbuffer re
```

```
%Apr 11 17:55:06:038 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6766-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 17:45:06:037 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6763-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 17:35:06:035 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6760-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 17:25:06:035 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6757-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 17:15:06:037 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6754-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 17:05:06:037 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6751-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 16:55:06:035 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6748-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 16:45:06:038 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6745-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 16:35:06:040 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6742-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 16:25:06:035 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6739-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 16:15:06:035 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6736-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 16:05:06:037 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6733-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 15:55:06:037 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6730-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 15:45:06:035 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6727-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
%Apr 11 15:35:06:035 2013 leaf-1.3 CFGMAN/5/CFGMAN_CFGCHANGED: -EventIndex=6724-CommandSource=snmp-COnfigSource=startup-COnfigDestination=running; Configuration changed.
```

### 解决方法

该日志没有影响, 实际也没有配置发生变化。

目前, director会周期性的测试snmp的读写连通性, 测试写需要尝试set一次, 目前的机制是把sysname用原先的值再set一次, 如果成功, 则snmp写可达。

设备侧定位, 获知设备打出configuration changed的判断规则是10分钟内有set写操作, 这样, 设备侧就会将director的snmp测试报文误认为配置改变而不断打印日志。