

## 组网及说明

### 1. 配置需求或说明

#### 1.1 适用产品系列

本案例适用于如：HP/Aruba 2620 24/48 Switch、HP/Aruba 2620 24/48 PoE+ Switch、HP/Aruba 2620 24 PPOE+ Switch等系列的交换机。

#### 1.2 组网图

无。

## 配置步骤

### 1. 操作步骤


#### 1.1 连接交换机，进入用户名提示界面

```
RESTRICTED RIGHTS LEGEND
Confidential computer software. Valid license from Hewlett Packard Enterprise
Development LP required for possession, use or copying. Consistent with FAR
12.211 and 12.212, Commercial Computer Software, Computer Software
Documentation, and Technical Data for Commercial Items are licensed to the
U.S. Government under vendor's standard commercial license.

We'd like to keep you up to date about:
* Software feature updates
* New product announcements
* Special events
Please register your products now at: www.hpe.com/networking/register

Username: █
```

#### 1.2 使用尖头物体，按下Clear按键，即可清除用户名密码



#### 1.3 清除密码后自动进入#模式

```
|Procure# █
```

#### 1.4 如清除密码后进入>模式，输入enable仍提示用户名密码，再次执行步骤2即可

```
Procure> enable
Username: █
```

## 配置关键点