



# EUDEMON忘记登录密码怎么清除

刘云昌 2006-05-24 发表

重启设备，按Ctrl + B进入bootrom菜单，输入密码：8060后显示：

```
=====<MAIN-BOOTROM MENU>=====
| <1> Boot With Default Mode          |
| <2> Boot From Flash                  |
| <3> Enter Serial SubMenu             |
| <4> Enter Ethernet SubMenu           |
| <5> Change Flash Boot File           |
| <6> Modify Bootrom Password          |
| <7> Reboot                           |
=====
```

Enter your choice(1-7):

然后按Ctrl + Z进入隐含菜单：

```
=====<HIDDEN SUB-MENU>=====
| <1> Enter Debugging Environment      |
| <2> Erase Flash                       |
| <3> Delete file from Flash           |
| <4> Display Flash Files              |
| <5> Enter Flash-Aging Test           |
| <6> Exit To Main Menu                |
=====
```

Enter your choice(1-6):

然后选择3删除配置：

BE CAREFUL!

This may cause your system fail to start!

Please input the file name you want to delete,

(e.g. Eudemon.bin)-->vrpcfg.cfg

This Would Take Long Time,Wait Please...

Delete it? Yes or No(Y/N)y

Deleting File...Done.

再回到主菜单，将设备重启即可。