## TippingPoint IPS软件升级方法

胡俊 2007-03-20 发表

	TippingPoint IPS软件升级方法
1 手动升级	
通过LSM登陆到	https://x.x.x.x
近八System>> U	dale >> 105 and DV Opdale
	System 🛞
	Configuration
	Management Port Management Routing
	High Availability
	Time Options
	SMS/NMS
	🗄 Logs
	Auto DV Configuration
	System Snapshots
	图表 1 LSM->SYSTEM 菜单
进入手动升级界词	
SYSTEM - Upd	- Manual Software Update
Step 1: Check for DV or	S updates from the <u>Threat Management Center</u> and save any new versions to your PC.
Step 2: Set current state Current State: Re	"Ready OK". 6/ OK (reset status)
Step 3: Make sure the p	age you downloaded is smaller than: 63 MB. actions new results more space than articlicated. To aid, delete one or more of the previously installed TOS insoen.
Step 4: Set High Prior	Preference: Traded
Layer-2 Falls	Enabled
Select " pkg" file "The installation	d press instak TOS updates will reboot the Tipping-Point device.
	图表 2 LSM软件升级页面
从TMC下载TOS	₩版本到本地.
查看"Current Sta	э"是否为"Ready",如果不是,点击"reset status",直到状态为"Ready";
确保升级文件正确	,TP的空间足够,否则可点击"previously installed TOS images"删除
以則合竹的105) "Sot High Priority	.件; Proforonco"目指"目不按升级晶作设为宣伏生级协理" 估能后 亥兹按
把升级操作优先	他讲程处理"Laver-2 Fallback"是指在升级过程中是否将设备设置为
"二层回退",设置为	"二层回退"后,系统将不对数据流进行检测.由于系统升级可能会导致
数据包检查缓慢,	]了确保升级成功,建议使能这两项.
点击"浏览",选择低	存在本地的TOS/DV文件(.pkg格式).
ADV在所有型号的	ITP上通用,TOS根据设备型号不一定相同.
8.0.2.0	
查找范围 (L): 200+ 10	50 C on the second seco
Recent	(共語: 1965 文件 修改日期: 2006-12-18 10:14
100 A	, delete one or more of the <u>previously installed TOS inseps</u>
我的文档	
RADIELE	rotat
和上常居	
文件名 (1):	▼ 11并@)
文件类型 (1)	所有文件(*.*) 東湖
	图表3软件升级
选择文件后,点击	nstall"系统将进行升级.
SYSTEM - Update - F	gress
	The Lipidate is 55% complete. Status: Lipidatina - Lipidatina: CK
	图表 4 软件升级
如果升级TOS 系	在升级完成后会自动重启.如果升级DV.系统不会重启。 重新启动后

## Please wait while the system reboots. Log on will be available in 1589 seconds.

## 图表 5 软件升级

升级后确认,点击LSM左上角的"System Summary"显示"TippingPoint Version":

Current User: unityone | Auto Log Off 3537 Log Off (System Summary)

图表 6 System Summary

TippingPoint Versions:				
Model No:	50			
TOS Version:	2.2.5.6533			
Digital Vaccine:	2.2.0.7147			
Boot Time:	2007-01-07 11:46:42 GMT+9			
Product Code:	TPT-UNITYONE-50			
Serial No:	U50C-3002-4706			

图表 7 Version

## 2 DV自动升级

DV自动升级是指系统能自动从TMC下载最新的DV更新(TOS不能自动更新). 自动升级的前提是TP管理以太口如果能接入internet,并设置正确的DNS.

进入"system">>"Configuration">>"Management Port",给管理以太口设置正确的IP地址

	System 🚷
网关和DNS服务	Configuration (Management Port) Management Port) Management Port Management Port Mana
inagement Port:	
P Address.	10.0.0254IP和捷码
fost Name:	k00.200.200.0
fost Location	r sou
tosi Location	Foundation
reraual Gateway:	[10.0.0.1] [10.0.0.0.1] [10.0.0.1] [10.0.0.1] [10.0.0.1] [10.0.0.1] [10.0.0.1] [10.0.0.1] [10.0.0.1] [10.0.0.1] [10.0.0.0.1] [10.0.0.0.1] [10.0.0.0.1] [10.0.0.0.1] [10.0.0.0.0.1] [10.0.0.0.0.0.0.0] [10.0.0.0.0.0.0.0.0] [10.0.0.0.0.0.0.0.0] [10.0.0.0.0.0.0.0.0.0] [10.0.0.0.0.0.0.0.0.0.0] [10.0.0.0.0.0.0.0.0.0.0.0] [10.0.0.0.0.0.0.0.0.0.0.0.0.0.0.0] [10.0.0.0.0.0.0.0.0.0.0.0.0.0.0.0] [10.0.0.0.0.0.0.0.0.0.0.0.0.0.0.0.0.0.0.
Serial Number:	U50C-3002-4706
INS Primary Server	1.1.1.1 DHS
NS Secondary Server	
DNS Domain Name 置后点击右下角 入"System">>"	图表 8 Management Port配置 甬的"Apply" 完成. 'Auto DV Configuration"进行自动升级设置:
NNS Domain Name 置后点击右下f 六 "System">>"	图表 8 Management Port配置 有的"Apply" 完成. 'Auto DV Configuration"进行自动升级设置:
NS Domsin Name 置后点击右下f ?入"System">>"	图表 8 Management Port配置 和的"Apply" 完成。 Auto DV Configuration"进行自动升级设置:
NNS Domain Name 置后点击右下角 :入"System">>" SYSTEM - Update - A Anto Dy Update	B表 8 Management Port配置 和的"Apply" 完成。 Auto DV Configuration"进行自动升级设置:
NNS Domain Name 置后点击右下角 :入"System">>* * System">>* * Anto DV Update Status	图表 8 Management Port配置 和的"Apply" 完成. Auto DV Configuration"进行自动升级设置:
NS Domain Name 置后点击右下角 入"System">>" System">>" Auto DV Update Status Auto DV Update	图表 8 Management Port配置 有的"Apply" 完成. Auto DV Configuration"进行自动升级设置:
NS Domain Name 置后点击右下角 入 "System">> " A "System">> " System">> " Auto DV Update Status AutoOV: Perodate	图表 8 Management Port配置 有的"Apply" 完成. Auto DV Configuration"进行自动升级设置:
NS Domain Name 置后点击右下角 入 "System">>* * System">>* * System">>* * Auto DV Update Status Auto: * © Periods: © Calendar:	B表 8 Management Port配置 有的"Apply" 完成. Auto DV Configuration"进行自动升级设置:

"Periodic"是指设置每多少天升级,比如设置从"这个星期二开始"每三天升级一次.

"Calendars"是指设置每周的星期几升级. 确保DNS和网关配置正确. 设置完成后,选择"Apply"确认.选择"Update Now"立即进行升级.