

## 知 Why does the configuration fail to be deleted on mid-range routers (V1.74-0105)

冷志宇 2007-09-27 发表

### Q: Why does the configuration fail to be deleted on mid-range routers (V1.74-0105)?

**A:** New options are added for the commands of deleting configuration and rebooting on the mid-range router (V1.74-0105). If you neglect them, you may find that the original configuration still exists after running the **delete** and **reboot** commands. For example:

```
[Router]delete
```

This will erase the configuration in NVRAM.

The router configurations will be erased to reconfigure

Are you sure?[Y/N]y

Now erasing the configuration in nvram.

Please wait for a while.....

Erase the configuration in NVRAM successfully

Please reboot the router

```
[Router]reboot
```

WARNING: Configuration has been changed ! Save configuration ? [Y/N]y

Now writing the running config to nvram .

Please wait for a while.....

write the running config to nvram successfully

WARNING: System will REBOOT! Continue ?[Y/N]y

System is now rebooting, please wait

While rebooting the system, you are prompted whether to save the configuration. If you choose **Yes**, the configuration still exists after reboot. If you choose **No**, there are no problems.