M S3610_5510交换机在配置MCE功能时出现"VPN-Table is full"提示的解决方 法

岳斌 2007-11-20 发表

S3610/5510交换机在配置MCE功能时出现"VPN-Table is full"提示的解决方法

在S3610/5510上配置MCE功能时,应先配置"switch-mode mce"命令,并按提示重启 设备,之后使用"display switch-mode"命令查看设备是否工作在MCE模式,如果是才 可以开始配置,否则会提示"VPN-Table is full"。

具体操作过程如下:

[H3C]ip vpn-instance test?

[H3C]ip vpn-instance test

VPN-Table is full

[H3C]switch-mode mce

Changes to the running system mode have been stored, but cannot take effect until the next reboot.

Use 'display switch-mode' to see what system mode is currently active.

<H3C>reboot

系统重启后.....

<H3C>dis switch-mode

The current system mode is Multi-Instance CE mode.

Number of VLANs: 1024 Number of VPN-Instances: 15

Max number of IPv4 unicast route entries: Max number of IPv4 multicast route entries: 512 Max number of IPv6 unicast route entries: 0

The system mode which will take effect after reboot is Multi-Instance CE mode.

<H3C>sys

System View: return to User View with Ctrl+Z.

[H3C]ip vpn-instance?

STRING<1-31> Name of VPN-Instance

[H3C]ip vpn-instance test [H3C-vpn-instance-test]