

知 S3610_5510交换机在配置MCE功能时出现“VPN-Table is full”提示的解决方法

岳斌 2007-11-20 发表

S3610/5510交换机在配置MCE功能时出现“VPN-Table is full”提示的解决方法

在S3610/5510上配置MCE功能时，应先配置“switch-mode mce”命令，并按提示重启设备，之后使用“display switch-mode”命令查看设备是否工作在MCE模式，如果是才可以开始配置，否则会提示“VPN-Table is full”。

具体操作过程如下：

```
[H3C]ip vpn-instance test ?
```

```
<cr>
```

```
[H3C]ip vpn-instance test
```

```
VPN-Table is full
```

```
[H3C]switch-mode mce
```

```
Changes to the running system mode have been stored, but cannot take effect until the next reboot.
```

```
Use 'display switch-mode' to see what system mode is currently active.
```

```
<H3C>reboot
```

```
系统重启后.....
```

```
<H3C>dis switch-mode
```

```
The current system mode is Multi-Instance CE mode.
```

```
Number of VLANs:          1024
```

```
Number of VPN-Instances:   15
```

```
Max number of IPv4 unicast route entries: 15360
```

```
Max number of IPv4 multicast route entries: 512
```

```
Max number of IPv6 unicast route entries: 0
```

```
The system mode which will take effect after reboot is Multi-Instance CE mode.
```

```
<H3C>sys
```

```
System View: return to User View with Ctrl+Z.
```

```
[H3C]ip vpn-instance ?
```

```
STRING<1-31> Name of VPN-Instance
```

```
[H3C]ip vpn-instance test
```

```
[H3C-vpn-instance-test]
```