

WA2200系列Fat AP的WEP加密功能的典型配置

宋斌 2008-08-21 发表


WA2200系列Fat AP的WEP加密功能的典型配置

Comware Software, Version 5.20, Ess 1104P02

一、组网需求

WA2200、交换机、便携机（安装有11b/g无线网卡）

二、组网图



- n WA2200上配置两个vlan: vlan 256和vlan 1000
- n vlan 256为业务vlan, 所有的无线客户端都属于vlan 256; vlan 1000为管理vlan
- n 管理vlan的IP地址为10.10.1.50/24, 业务vlan的IP地址为192.168.1.1/24
- n 服务集标识SSID为H3C-wep, 采用WEP加密方式, 密码为12345

三、WA2200的完整配置

```
#  
version 5.20, Ess 1104P02  
#  
sysname H3C  
#  
password-control login-attempt 3 exceed lock-time 120  
#  
domain default enable system  
#  
vlan 1  
#  
vlan 256  
#  
vlan 1000  
#  
domain system  
access-limit disable  
state active  
idle-cut disable  
self-service-url disable  
#  
dhcp server ip-pool pool1  
network 192.168.1.0 mask 255.255.255.0  
gateway-list 192.168.1.254  
expired day 3  
#  
wlan rrm  
11a mandatory-rate 6 12 24  
11a supported-rate 9 18 36 48 54  
11b mandatory-rate 1 2  
11b supported-rate 5.5 11  
11g mandatory-rate 1 2 5.5 11  
11g supported-rate 6 9 12 18 24 36 48 54  
#  
wlan service-template 1 crypto  
ssid H3C-wep  
authentication-method open-system
```

```
cipher-suite wep40
wep default-key 1 wep40 pass-phrase 12345
service-template enable
#
interface NULL0
#
interface Vlan-interface256
ip address 192.168.1.1 255.255.255.0
#
interface Vlan-interface1000
ip address 10.10.1.50 255.255.255.0
#
interface Ethernet1/0/1
port link-type trunk
port trunk permit vlan all
#
interface Ethernet1/0/2
#
interface WLAN-BSS1
port access vlan 256
#
interface WLAN-Radio1/0/1
channel 1
max-power 15
service-template 1 interface wlan-bss 1
#
interface WLAN-Radio1/0/2
#
dhcp enable
#
user-interface con 0
user-interface vty 0 4
#
return
```