

IX3000产品如何清除系统日志

一、组网需求:

无

二、组网图:

无

三、配置步骤:

该案例使用于IX3000 V1R1版本。

登陆Linux命令行, 执行下面命令:

```
[root@wan2]# cd /usr/local/H3C/bin
```

```
[root@wan2 bin]# ./clearlog.sh
```

```
=====
=====
```

```
Warning: you are about to clear all log record !!!
```

```
=====
=====
```

```
Are you want to do it (Y)es/(N)o? [N] y
```

```
Shutting down kernel logger: [ OK ]
```

```
Shutting down system logger:
```

```
Message from syslogd@wan2 at Tue Jun 24 14:54:51 2008 ...
```

```
wan2 last message repeated 5 times
```

```
[ OK ]
```

```
Starting system logger: [ OK ]
```

```
Starting kernel logger: [ OK ]
```

四、配置关键点:

对于B6074P11及以前的版本, clearlog.sh脚本在/usr/local/H3C/tools目录下。

对于B6083E01L03及以后的版本, clearlog.sh脚本在/usr/local/H3C/bin目录下。