



Secpath firewall自动重启堆栈收集信息

张岚 2009-02-20 发表

V3平台

在诊断模式下获取calltrace和reg信息:

```
[SecPath100F_SUB-hidecmd]en -----> 隐含模式下键入en
```

```
input password (1-12 characters) : -----> 密码huawei-3com
```

This mode is for huawei engineers to test. Running these commands could result in exceptions. Please do not run these commands without directions of huawei engineers.

```
[SecPath100F_SUB-diagnose]trapdebug calltrace \
```

```
|-----> 分别获取calltrace和reg信息反馈
```

```
[SecPath100F_SUB-diagnose]trapdebug reg /
```

注意: 不要使用[SecPath100F_SUB-diagnose]trapdebug test, 否则设备立即重启。

V5平台

```
[H3C]_hidecmd
```

Now you enter a hidden command view for developer's testing, some commands may affect operation by wrong use, please carefully use it with our engineer's direction.

```
[H3C-hidecmd]display exception 10 ver
```

查看保存的10次堆栈信息。