



Divide the 40G interface into 4 10G interfaces

Switches

龚训杰

2020-10-12 Published

Problem Description

Divide the 40G interface into 4 10G interfaces

Solution

Split the 40GE interface FortyGigE1/0/1 into four 10GE interfaces.

<System> system-view

[System] interface fortygige 1/0/1

[System-FortyGigE1/0/1] **using tengige**

The interface FortyGigE1/0/1 will be deleted. Continue? [Y/N]:y

#Combine the 10GE interface split from the 40GE interface into a 40GE interface.

<System> system-view

[System] interface ten-gigabitethernet1/0/1:1

[System-Ten-GigabitEthernet1/0/1:1] **using fortygige**

The interfaces Ten-GigabitEthernet1/0/1:1 through Ten-GigabitEthernet1/0/1:4 will be deleted. Continue? [Y/N]:y