

# 知 The Information Required For License Registration

Switches Wireless 龚训杰 2020-06-16 Published

## Network Topology

Item	Description	Remarks
License key	Enter the license key provided on the paper license.	Required.
H3C device S/N	Enter the device serial number, a string of 20 characters. You can use the display license device-id command on the device to display the device serial number.	Required.
Device information file	Upload the device DID file. You can use the display license device-id command on the device to display the file path and use FTP or TFTP to download the DID file to the device.	Required.
Customer company/organization	Enter the name of the company or organization that uses the device.	Required.
Company/organization	Enter your company or organization name.	Required.
First name	Enter your first name.	Required.
Last name	Enter your last name.	Optional.
Phone number	Enter your phone number.	Required.
Email address	Enter your email address. H3C will send a copy of the activation file or key to your email box in addition to providing a link to the activation file on the registration result page.	Required.
Zip code	Enter the zip code of your region.	Optional.
Address	Enter your address.	Optional.
Project name	Enter the name of the project that uses the device.	Optional.
Verify code	Enter the code literally as is displayed on the image to the right of the text box.	Required.

## Configuration Steps

1. **License key** : You can find it in the box sent to you by H3C.

2. **H3C device S/N**: You have many ways to check the serial number, here we list 2 ways:

(A) View through the bar code photos on the outside of the device, and manually record.

(B) Use the command [**display device manuinfo**] to check it and save.

### display device manuinfo

```
Slot 1 CPU 0: DEVICE_NAME:WX5540E
DEVICE_SERIAL_NUMBER:210235A0VSB151000017
MAC_ADDRESS:586AB1F33980
MANUFACTURING_DATE:2015-03-18
VENDOR_NAME:H3C
```

3. **DID file (Device information file)**: The did file is required in registering license. You need to TFTP to get it from device.

Step is like:

```
display license device-id slot 1
SN: 210235A0VSB151000017
SN CHECK_SUM: 015ACCB8
Device ID: cfa0:/license/210235A0VSB151000017.did
dir
```

Directory of cfa0:

```
14 -rw-    973 Jun 12 2020 19:13:20  ifindex.dat
15 drw-    - Sep 14 2019 08:23:18  license
16 drw-    - Feb 03 2020 23:56:54  logfile
```

```
cd cfa0:/license
```

```
dir
```

Directory of cfa0:/license

```
0 -rw-    8072 Nov 19 2016 03:37:40  111
1 -rw-    8688 May 11 2018 01:17:28  123.cfg
2 -rw-    1029 Jun 08 2020 15:50:18  210235A0VSB151000017.did
```

4. **Other contact information**, such as company name or phone number, fill in as required.

## Key Configuration

1. How to use tftp to get or put files?

You can check the attachment file [TFTP English]

2. How to register license?

You can refer to the attachment [Registering license ]  
or refer to this link file:

<https://zhiliao.h3c.com/Theme/details/112903>

3.How to install an activation file?

Use TFTP to import .ak format files to the device, and follow these steps:

1. Enter system view.

**system-view**

2. Install an activation file.

**license activation-file install file-name slot slot-number**

附件下载: TFTP English.pdf Registering license.pdf